



PRODUCT SELECTION AND APPLICATION

In the selection and application of molded-case circuit breakers, consideration should be given to the following factors:

1. Voltage of the circuit
2. Ampacity of the circuit
3. Frequency of the power source
4. Fault current available
5. Operating conditions

VOLTAGE OF CIRCUIT

The system voltage should not exceed the listed voltage rating of the circuit breaker.

AMPACITY OF CIRCUIT

The listed continuous current rating of the circuit breaker should not exceed the allowable ampacity of the conductors. Where the allowable ampacity of the conductor does not correspond to listed current ratings for circuit breakers, the next larger breaker rating is permitted, providing it does not exceed the conductor ampacity by more than 25%. An exception to this rule is permitted for motor circuits or other circuits where high inrush currents may persist for an appreciable time. (See National Electric Code Table 430-146, Overcurrent Protection for Motors).

FREQUENCY OF POWER SOURCE

I-T-E molded-case circuit breakers are calibrated for use on direct current or 60-cycle alternating current. For 400-cycle operation, derating is not necessary for one-, two- or three-pole EQ®-P, EQ-B, E, EH and EF breakers. All larger frame sizes, however, do require derating for 400-cycle operation. In these cases, consult your local I-T-E Sales Office.

FAULT CURRENT AVAILABLE

The interrupting rating of the circuit breaker should be at least equal to the maximum available short circuit current at the point of application. The short circuit current from some power sources, such as engine driven generators, is limited, and the instantaneous trip of the circuit breaker, when adjustable, should be set to open such low magnitude faults without delay.

OPERATING CONDITIONS

I-T-E molded-case circuit breakers are calibrated for operation at 40C, as specified by the Underwriters' Laboratories, Inc. Sound engineering practice dictates that continuous loads should not exceed 80% of the breaker rating for most types of enclosures. Refer to Table 1 for the continuous current ratings of breakers at various ambients.

TABLE 1

**EQ® and ET® Circuit Breaker Continuous Current Ratings at Various Ambients
(Based on Calibration for 40C)**

Breaker Type(s)	Rating Amperes	Applied in Ambients of		
		40C	50C	60C
EQ-T	15	15	12	10
	20	20	18	16
	30	30	27	25
	40	40	37	35
EQP, EQ-B	15	15	13	11
	20	20	19	17
	30	30	27	25
	40	40	38	36
	50	50	47	44
	70	70	66	63
	90	90	86	81
EQ-225	100	100	97	92
	125	125	110	92
	150	150	141	131
	175	175	162	149
	200	200	182	161
E, EH, EF, HF, CF	225	225	198	180
	15	15	13	10
	20	20	17	15
	30	30	27	24
	40	40	37	35
	50	50	48	44
	70	70	66	63
	90	90	82	74
	100	100	93	84
FJ	70	70	60	47
	90	90	79	70
	100	100	89	77
	125	125	107	90
	150	150	130	110
	175	175	152	138
	200	200	172	147
JJ, JKL, HJKL, CJJKL*	225	225	192	170
	70	70	63	58
	90	90	80	70
	100	100	92	83
	125	125	113	102
	150	150	142	128
	175	175	162	150
	200	200	182	165
	225	225	205	185
	250	250	225	200
	275	275	240	206
	300	300	270	235
KM, HLM, CM†	350	350	310	265
	400	400	363	318
	125	125	118	103
	150	150	135	118
	175	175	157	138
	200	200	185	158
	225	225	206	178
	250	250	227	198
	275	275	250	213
	300	300	270	233
KP	350	350	316	279
	400	400	365	346
	500	500	455	430
	600	600	550	510
	700	700	640	610
	800	800	730	700
	800	800	730	670
	1000	1000	925	825
	1200	1200	1100	1000
HP, CP	800	800	730	670
	1000	1000	925	825
	1200	1200	1100	1000
	1400	1400	1300	1200
	1600	1600	1450	1350

* JJ-frame breaker available in ratings from 250 through 400 ampere only; HJKL- and CJJKL-frame breakers available in ratings from 125 through 400 ampere only.

† HLM- and CM-frame breakers available in ratings from 400 through 800 ampere only.



PRODUCT SELECTION AND APPLICATION (continued)

OPERATING CONDITIONS (continued)

When the type of load is unusual, intermittent, or one which involves momentary peak currents, such as motor loads, consideration should be given to the heating effect on the protective device over a period of time. The duty cycle of a motor which is started and stopped frequently may require a circuit breaker with a higher rating than an infrequently started motor. Resistance welder applications require a careful analysis of the duty cycle in order to select the proper size breaker for primary short circuit protection.

The presence of excessive dust, moisture, corrosive fumes or explosive atmosphere requires the use of enclosures suitable for such atmospheres. (See Sections 2.7.1 and 2.7.5.) For applications in regions where fungus growth may occur, circuit breakers should be treated with a fungus-resistant material. (See Sections 2.6.1 and 2.6.5.)

PROTECTION OF CONDUCTORS—GENERAL

The primary function of a circuit breaker is the protection of the insulation of conductors and thermal-magnetic breakers automatically adjust for temperature changes that closely parallel the temperature correction factors for conductors. For application at temperatures above 30C, conductors should be derated in accordance with the National Electric Code for both ambient temperature and continuous loading. Conductors which are loaded continuously should be derated to 80% of their allowable ampacity. Refer to Table 2.

PROTECTION OF NON-MOTOR LOAD CONDUCTORS

Refer to Tables 1 and 2, and match the current rating of the circuit breaker to the allowable ampacity of the conductor. If the ampacity of the conductor falls between standard breaker ratings, select the higher breaker-current rating. Be sure to check the voltage and interrupting rating of the circuit breaker to assure that they are adequate for the electrical system.

* These ampacities relate only to conductors described in NEC Table 310-2(a).

** The ampacities for Types FEP, FEPB, RHH and THHN conductors for sizes AWG 14, 12 and 10 shall be the same as designated for 75C conductors in this Table.

† The ampacities for Types RHH and THHN conductors for sizes AWG 12, 10 and 8 shall be the same as designated for 75C conductors in this Table.

‡ For three-wire, single-phase service and sub-service circuits, the allowable ampacity of RH, RH-RW, RHH, RHW, and THW aluminum conductors shall be for sizes #2-100 Amp., #1-110 Amp., #1/0-125 Amp., #2/0-150 Amp., #3/0-170 Amp. and #4/0-200 Amp.

TABLE 2

Ampacities of Insulated Conductors
(From 1965 National Electric Code)

Not More Than Three Conductors in Raceway or Cable or Direct Burial (Based on Room Temperature of 30C., 86F.)

Size AWG MCM	Temperature Rating of Conductor*					
	60C (140F)	75C (167F)	85- 90C (185F)	101C (230F)	125C (257F)	200C (392F)
COPPER CONDUCTORS (FROM NEC TABLE 310-12)						
14	15	15	25**	30	30	30
12	20	20	30**	35	40	40
10	30	30	40**	45	50	55
8	40	45	50	60	65	70
6	55	65	70	80	85	95
4	70	85	90	105	115	120
3	80	100	105	120	130	145
2	95	115	120	135	145	165
1	110	130	140	160	170	190
0	125	150	155	190	200	225
00	145	175	185	215	230	250
000	165	200	210	245	265	285
0000	195	230	235	275	310	340
250	215	255	270	315	335	—
300	240	285	300	345	380	—
350	260	310	325	390	420	—
400	280	335	360	420	450	—
500	320	380	405	470	500	—
600	355	420	455	525	545	—
700	385	460	490	560	600	—
750	400	475	500	580	620	—
800	410	490	515	600	640	—
900	435	520	555	—	—	—
1000	455	545	585	680	730	—
1250	495	590	645	—	—	—
1500	520	625	700	785	—	—
1750	545	650	735	—	—	—
2000	560	665	775	840	—	—
ALUMINUM CONDUCTORS (FROM NEC TABLE 310-14)						
12	15	15	25†	25	30	30
10	25	25	30†	35	40	45
8	30	40	40†	45	50	55
6	40	50	55	60	65	75
4	55	65	70	80	90	95
3	65	75	80	95	100	115
2†	75	90	95	105	115	130
1†	85	100	110	125	135	150
0†	100	120	125	150	160	180
00†	115	135	145	170	180	200
000†	130	155	165	195	210	225
0000†	155	180	185	215	245	270
250	170	205	215	250	270	—
300	190	230	240	275	305	—
350	210	250	260	310	335	—
400	225	270	290	335	360	—
500	260	310	330	380	405	—
600	285	340	370	425	440	—
700	310	375	395	455	485	—
750	320	385	405	470	500	—
800	330	395	415	485	520	—
900	355	425	455	—	—	—
1000	375	445	480	560	600	—
1250	405	485	530	—	—	—
1500	435	520	580	650	—	—
1750	455	545	615	—	—	—
2000	470	560	650	705	—	—
CORRECTION FACTORS, ROOM TEMPERATURES OVER 30C (86F)						
C	F					
40	104	.82	.88	.90	.94	.95
45	113	.71	.82	.85	.90	.92
50	122	.58	.75	.80	.87	.89
55	131	.41	.67	.74	.83	.86
60	140		.58	.67	.79	.83
70	158		.35	.52	.71	.76
75	167		—	.43	.66	.72
80	176		—	.30	.61	.69
90	194				.50	.61
100	212				—	.51
120	248		—	—	—	.69
140	284		—	—	—	.59



PRODUCT SELECTION AND APPLICATION (continued)

PROTECTION OF MOTOR CIRCUITS

Molded-case circuit breakers are used in motor circuits as a disconnecting means and for short-circuit protection, and should be used in conjunction with motor-running overcurrent-protection devices. The circuit breaker should have a continuous-current rating of not less than 115% of the motor full-load current, and its characteristics should permit the motor to start without nuisance tripping from motor-inrush current.

Motor Branch Circuits

When the breaker is mounted at a distance from the motor starter, thermal-magnetic circuit breakers conform to

the National Electrical Code requirements for motor branch and feeder circuit protection when properly applied in conjunction with motor-running overcurrent protective devices. The recommended circuit-breaker ratings shown in Table 3 provide adequate time delay for starting the majority of three-phase induction motors.

Motor Feeder Circuits

To determine the ampere rating of the circuit breaker needed to protect a motor feeder, add the rating of the breaker used to protect the largest motor branch circuit in the group to the full-load currents of the remaining motors in the group.

**TABLE 3—EQ® AND ET® CIRCUIT BREAKERS (Thermal-Magnetic Trip)
For Use With Alternating-Current Combination Motor Starters
3-PHASE INDUCTION-TYPE MOTORS**

Motor Horsepower Rating	208 or 220 V Motors			440 V Motors			550 V Motors		
	240 V Circuit Breaker Data‡			480 V Circuit Breaker Data‡			600 V Circuit Breaker Data‡		
	Frame	Catalog Number	Rating, Amperes	Frame	Catalog Number	Rating, Amperes	Frame	Catalog Number	Rating, Amperes
EQ®-P*	QP3-B015	15		EH	EH3-B015	15	EF	EF3-B015	15
	QP3-B015	15			EH3-B015	15		EF3-B015	15
	QP3-B015	15			EH3-B015	15		EF3-B015	15
	QP3-B015	15			EH3-B015	15		EF3-B015	15
	QP3-B015	15			EH3-B015	15		EF3-B015	15
	QP3-B020	20			EH3-B015	15		EF3-B015	15
EQ-P*	QP3-B030	30		EH	EH3-B015	15	EF	EF3-B015	15
	QP3-B050	50			EH3-B030	30		EF3-B020	20
	QP3-B050	50			EH3-B030	30		EF3-B030	30
	QP3-B100	100			EH3-B040	40		EF3-B040	40
	QP3-B100	100			EH3-B050	50		EF3-B050	50
	QJ3-B125	125		EQ-225	EH3-B070	70	EF	EF3-B050	50
EQ-225	QJ3-B150	150			EH3-B100	100		EF3-B070	70
	QJ3-B175	175			EH3-B100	100		EF3-B100	100
	QJ3-B200	200			EH3-B100	100		EF3-B100	100
	QJ3-B225	225			FJ3-B125	125		EF3-B100	100
	JL3-B350	350			JL3-B125	125		FJ3-B125	125
	JL3-B400	400		JKL†	FJ3-B175	175	JKL	JL3-B125	125
JKL†	JL3-B400	400			JL3-B175	175		FJ3-B175	175
	JL3-B400	400			FJ3-B200	200		JL3-B175	175
	JL3-B400	400			JL3-B200	200		FJ3-B200	200
	KM3-B600	600			FJ3-B225	225		JL3-B200	200
	KM3-B800	800			JL3-B225	225		FJ3-B225	225
	KM3-B800	800			JL3-B350	350		JL3-B225	225
KM	JKL†	JKL†		JKL†	JL3-B400	400	JKL†	JL3-B350	350
	JKL†	JKL†			JL3-B400	400		JL3-B400	400
	JKL†	JKL†			KM	600		JL3-B400	400
	JKL†	JKL†			KM3-B600	600		KM	500
	JKL†	JKL†			KM3-B700	700		KM3-B500	500
	JKL†	JKL†			KM3-B800	800		KM3-B600	600
JKL†	JKL†	JKL†			JKL†	JKL†	JKL	KM3-B800	800
	JKL†	JKL†			JKL†	JKL†		JL3-B400	400
	JKL†	JKL†			JKL†	JKL†		JL3-B400	400
	JKL†	JKL†			JKL†	JKL†		JL3-B400	400
	JKL†	JKL†			JKL†	JKL†		JL3-B400	400
	JKL†	JKL†			JKL†	JKL†		JL3-B400	400

‡ Note: Recommended circuit breakers are for full-voltage, resistor or reactor starting with motors of Code Letters B to E. Special consideration may be necessary for auto-transformer starting. For recommended instantaneous trip settings of FJ, JJ, JKL and KM frame circuit breakers, see Table 4.

* For bolted applications, substitute the EQ-B breaker for the EQ-P.

† For non-interchangeable trip applications, substitute the JJ breaker for the JKL.



PRODUCT SELECTION AND APPLICATION (continued)

When the circuit breaker is mounted immediately ahead of the motor starter, ETI magnetic-trip breakers are recommended for use in combination motor starters to provide selective short-circuit protection for the motor branch circuit. The adjustable instantaneous-trip feature of the ETI circuit breaker provides for a trip setting slightly above the peak

motor-inrush current. With this setting, no delay is introduced in opening the circuit when a fault occurs. This circuit breaker has no time-delay element and therefore must be used in conjunction with, and immediately ahead of, the motor-running overcurrent-protective device. (See Table 4.)

**TABLE 4—ETI CIRCUIT BREAKERS (Magnetic-Trip Only)
For Use With Alternating-Current Motor Starters
3-PHASE INDUCTION-TYPE MOTORS**

Motor Horsepower Rating						Frame	Catalog Number	Continuous Amps	Circuit Breaker Data					Trip Setting Position				
110 Volts	208 Volts	220 Volts	440 Volts	550 Volts	Frame				Lo	2	3	4	Hi	110 Volts	208 Volts	220 Volts	440 Volts	550 Volts
—	—	—	—	½	EF	EF3-A003	3	7	10	12	16	21	—	—	—	—	3	2
—	—	—	—	¾		EF3-A003	3	7	10	12	16	21	—	—	—	—	4	3
—	—	—	—	1		EF3-A003	3	7	10	12	16	21	—	—	—	—	4	—
—	—	—	—	1½		EF3-A005	5	14	18	22	29	41	—	3	3	3	3	3
—	—	—	—	2		EF3-A005	5	14	18	22	29	41	—	—	—	4	4	4
½	¾	¾	2	3	EF	EF3-A010	10	27	36	45	58	84	3	2	2	2	2	3
¾	1	1	3	—		EF3-A010	10	27	36	45	58	84	4	3	3	4	—	—
—	1½	1½	—	—		EF3-A010	10	27	36	45	58	84	—	4	4	—	—	—
—	2	2	—	5		EF3-A010	10	27	36	45	58	84	Hi	Hi	Hi	Hi	Hi	Hi
—	—	—	5	—	EF	EF3-A025	25	75	105	125	170	210	—	—	—	2	—	—
—	1½	3	7½	7½		EF3-A025	25	75	105	125	170	210	2	2	2	3	2	2
—	2	5	5	10		EF3-A025	25	75	105	125	170	210	4	4	4	4	3	3
—	—	—	—	15		EF3-A025	25	75	105	125	170	210	—	—	—	—	4	—
—	—	7½	7½	15		EF3-L050	50	160	210	260	330	470	—	3	3	3	3	3
—	—	10	10	20		EF3-L050	50	160	210	260	330	470	—	4	4	4	4	4
—	15	15	25	30	EF	EF3-H050	50	320	400	475	565	670	—	3	3	2	2	2
—	—	—	30	40		EF3-H050	50	320	400	475	565	670	—	—	—	3	3	3
—	20	20	40	50		EF3-A100	100	475	630	750	930	1125	—	2	2	2	2	2
—	25	25	50	60		EF3-A100	100	475	630	750	930	1125	—	3	3	3	3	3
—	30	30	60	75		EF3-A100	100	475	630	750	930	1125	—	4	4	4	4	4
—	40	40	75	100	FJ or JKL	FJ3-A225	225	960	1200	1550	1850	2000	—	2	2	2	2	2
—	50	50	100	125		JL3-A225	225	960	1200	1450	1800	2000	—	3	3	3	3	3
—	60	60	125	150		JL3-L400	400	1900	2300	2700	3100	3500	—	4	4	4	4	4
—	75	75	150	200	JKL	JL3-L400	400	1900	2300	2700	3100	3500	—	2	2	2	2	2
—	100	100	200	250		JL3-H400	400	3200	3600	4100	5100	5600	—	3	3	3	3	3
—	125	125	250	300		KM3-L800	800	3200	3600	4100	5100	5600	—	4	4	4	4	4
—	150	150	300	400	KM	KM3-L800	800	3200	3600	4100	5100	5600	—	3	3	3	3	3
—	200	200	400	500		KM3-L800	800	3200	3600	4100	5100	5600	—	Hi	4	4	4	4
—	250	250	500	—		KM3-H800	800	5000	6100	6700	7400	8000	—	4	3	3	—	—

For further information or assistance in the selection and application of molded-case circuit breakers, consult your local I-T-E Distributor or Sales Office.