




February 1991
Supersedes Dimension Sheet 29-170,
pages 35-36, dated November 1981
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Type NB and MARK 75® Type HNB

Page 35: Type NB, MARK 75® Type HNB
Page 36: Mounting Block for Type NB,
MARK 75 HNB, SELTRONIC™ Types NC,
MARK 75 HNC


AB DE-ION® Circuit Breakers

Type NB, MARK 75® Type HNB Breakers




Drilling Plans

For Mounting Bolts
(Front Connected Terminals)




For Rear Connected Studs
(Insulated Panel)




Style No.	A
623B222G01	5 1/2
623B222G02	8
623B222G03	10 1/2

Bolted Rear Connected Studs For 700 to 800 Amps




Style No.	A
623B222G01	5 1/2
623B222G02	8
623B222G03	10 1/2

For 900 to 1200 Amps Only




Front Cover Cutout



Ⓢ Changed since previous issue.



Mounting Block for Type NB, NC, MARK 75® Type HNB, HNC Breakers






L-Frame OPTIM Three-Pole


Westinghouse Series C® Molded Case Circuit Breakers L-Frame 70-600 Amperes

Front View

Removable Terminal
Cover **Must Be in
Place** While in Service



Side View









Terminal Catalog No.	Wire Range (MCM)	Number of Cables	Torque
Copper Only Cable (Supplied in Kit Form)			
T602LD	250-350	2	275 Lb-in. (31.1 Nm)
Copper or Aluminum Cable (Supplied in Kit Form)			
TA602LD	250-350	2	275 Lb-in. (31.1 Nm)
TA603LD	400-500	2	275 Lb-in. (31.1 Nm)
TA401LD	4/0-600	1	400 Lb-in. (45.2 Nm)
TA450LD	4-4/0	2	275 Lb-in. (31.1 Nm)



Westinghouse Series C® Molded Case Circuit Breakers, L-Frame, 70-600 Amperes

L-Frame OPTIM Three-Pole Breakers, *Continued*

Drilling Plans



Reproduced from drawings 1493D63 and 1493D67

Dimensions in parentheses in millimeters
 Dimensions for estimating purposes only

Cutler-Hammer

Westinghouse & Cutler-Hammer Products
 Five Parkway Center
 Pittsburgh, Pennsylvania, U.S.A. 15220

EATON

Printed in U.S.A.

March 1996


March 1996
New Information
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

N-Frame OPTIM Three-Pole


Westinghouse Series C® Molded Case Circuit Breakers N-Frame 400-1200 Amperes

N-Frame OPTIM Three-Pole Breakers

Front View




Side View



Load End

Dimensions

Breaker Status	A	B
ON	7.90 (200.66)	8.30 (210.82)
TRIPPED	6.50 (165.10)	6.90 (175.26)
OFF	5.70 (144.78)	6.10 (154.94)
RESET	5.60 (142.24)	6.00 (152.40)



Reproduced from drawing 1484D70

Dimensions in parentheses in millimeters

Dimensions for estimating purposes only

March 1996




Westinghouse Series C Molded Case Circuit Breakers, N-Frame, 400-1200 Amperes


N-Frame OPTIM Three-Pole Breakers, *Continued*

Drilling Plans


Rear Connected





Front Connected



Front Cover Cutout



Terminal Extensions for 100% Rating



Load End

Line End

Terminal Arrangements

Catalog Number	Wire Range	Number of Cables	Torque Lb-in
Aluminum or Copper Cable			
TA700NB1	#1-500 MCM	2	375
TA1000NB1	3/0-400 MCM	3	375
TA1200NB1	4/0-500 MCM	4	375
TA1201NB1	500-750 MCM	3	450
Copper Cable Only			
T700NB1	2/0-500 MCM	2	300
T1000NB1	3/0-500 MCM	3	300
T1200NB3	3/0-400 MCM	4	275

Drilling Plan for Rear Connecting Studs

Amp Rating	Hole Diameter
700 & 800	1.188 (30.175) Diameter
900-1200	1.312 (33.325) Diameter

Reproduced from drawing 1484D70

Dimensions in parentheses in millimeters

Dimensions for estimating purposes only

Cutler-Hammer

Westinghouse & Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220



Cutler-Hammer logo




Mailed to: E, D, C/29-100A, 31-400A,
31-500A

R-Frame OPTIM Three-Pole

Front View



Side View




Terminal Catalog Number	Terminal Material (Body)	Screw Head Type	Wire Range	Wire Type	Torque
T1600RD	Copper	Socket	1-600(4) (50-300(4))	Cu	375 Lb.-in. (42.38 Nm)
TA1600RD	Aluminum	Socket	500-1000(4) (300-500(4))	Cu/Al	550 Lb.-in. (62.15 Nm)

Dimensions for estimating purposes only



Westinghouse Series C® Molded Case Circuit Breakers, R-Frame, 800-2500 Amperes

R-Frame OPTIM Three-Pole Breakers, 2500 Amp Frame, *Continued*



Reproduced from drawings 1495D63 and 1495D67

Dimensions in parentheses in millimeters

Dimensions for estimating purposes only

Cutler-Hammer

Westinghouse & Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220





Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220

Supersedure Notice
29-120
Page 1

April 1995
New Information
Mailed to: E, D, C/29-100A, 31-400A, 31-500A

AB DE-ION® Circuit Breakers

Technical Data 29-120, pages 33-34, dated April 1992 has been superseded by
Selection Data 29-120C, pages 1-2, dated March 1995. Please remove from your
catalog and files.

www.ElectricalPartManuals.com



Cutler-Hammer

Dimension Sheet

29-170G

Page 1

June 1995
New Information
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Type GD Circuit Breakers

Page 1: Type GD One-Pole

Page 2: Type GD Two-Pole

Series C® Molded Case Circuit Breakers G-Frame 15-100 Amperes

Type GD One-Pole Only



Suitable for Cable Mounting, Line and Load

Terminal, Line and Load Side


Type Terminal	Breaker Amperes	Wire Type and Size
Clamp and Binding Screw	15-20	#14-#10 Cu/Al
Pressure Collar	25-100	#10-1/0 Cu/Al

Clamp Supplied on
15 thru 20 Amp Ratings
Wire Range #14-10 Cu/Al


Line End





Clamp Supplied on
15 thru 20 Amp Ratings
Wire Range #14-10 Cu/Al



Load End



Pressure Connectors are
Supplied on 25 thru 100 Amp
Ratings Wire Range #10-1/0
Cu/Al



Reproduced from drawing 1374D14

Dimensions in parentheses in millimeters

EAT•N








Series C Molded Case Circuit Breakers, G-Frame, 15-100 Amperes

Type GD Two-Pole Only

Suitable for Cable Mounting, Line and Load

Terminals, Load and Load Side

Type Terminal	Breaker Amperes	Wire Type and Size
Clamp and Binding Screw	15-20	#14 -#10 Cu/Al
Pressure Collar	25-100	#10-1/0 Cu/Al



Reproduced from drawing 1374D15

Dimensions in parentheses in millimeters

Cutler-Hammer

Westinghouse & Cutler-Hammer Products
 Five Parkway Center
 Pittsburgh, Pennsylvania, U.S.A. 15220



Cutler-Hammer

Dimension Sheet

29-170G

Page 3

June 1995
New Information
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Types GD, GDB Bolt-On Panelboard
Circuit Breakers

Page 3: Type GD Three-Pole
Page 4: Type GDB Bolt-On One-Pole

Series C® Molded Case Circuit Breakers G-Frame 15-100 Amperes


Type GD Three-Pole Only

Suitable for Cable Mounting, Line and Load


Terminals, Load and Load Side

Type Terminal	Breaker Amperes	Wire Type and Size
Clamp and Binding Screw	15-20	#14-#10 Cu/Al
Pressure Collar	25-100	#10-1/0 Cu/Al



Line End



.141 (3.57) Dia. 4 Holes
.281 (7.14) Dia C Bores
.18 (4.57) Deep
For Mounting Purposes



Load End



Reproduced from drawing 1374D16

Dimensions in parentheses in millimeters

EATON




Series C Molded Case Circuit Breakers, G-Frame, 15-100 Amperes

Type GDB Bolt-On One-Pole Only


Terminals, Load Side Only

Type Terminal	Breaker Amperes	Wire Type and Size
Clamp	15-20	#14-#10 Cu/Al
Pressure	25-100	#10-1/0 Cu/Al

Line End



Load End



Reproduced from drawing 1372D97

Dimensions in parentheses in millimeters

Cutler-Hammer

Westinghouse & Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220

EATON

Printed in U.S.A.

June 1995



Cutler-Hammer

Dimension Sheet
29-170G

Page 5

June 1995
New Information
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Type GDB Bolt-On Panelboard
Circuit Breakers

Page 5: Type GDB Bolt-On Two-Pole
Page 6: Type GDB Bolt-On Three-Pole

Series C® Molded Case Circuit Breakers G-Frame 15-100 Amperes


Type GDB Bolt-On Two-Pole Only

Terminals, Load Side Only


Type Terminal	Breaker Amperes	Wire Type and Size
Clamp	15-20	#14-#10 Cu/Al
Pressure	25-100	#10-1/0 Cu/Al

Line End


.234 (5.95) Diameter Holes



Load End



Clamp Supplied on 15 thru 20 Amp
Ratings Wire Range #14-#10 Cu/Al



Reproduced from drawing 1373D57

Dimensions in parentheses in millimeters

EATON



Series C Molded Case Circuit Breakers, G-Frame, 15-100 Amperes



Type GDB Bolt-On Three-Pole Breakers

Terminals, Load Side Only

Type Terminal	Breaker Amperes	Wire Type and Size
Clamp	15-20	#14-#10 Cu/Al
Pressure	25-100	#10-1/0 Cu/Al


Line End

.234 (5.95) Diameter Holes



Load End

Clamp Supplied on 15 thru
20 Amp Ratings Wire Range
#14-#10 Cu/Al

Reproduced from drawing 1370D84

Dimensions in parentheses in millimeters

Cutler-Hammer

Westinghouse & Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220

Printed in U.S.A.

June 1995





Cutler-Hammer

Dimension Sheet

29-170G

Page 7

June 1995

New Information

Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Types GC, GHC Circuit Breakers

Page 7: Types GC, GHC One-Pole

Page 8: Types GC, GHC Two-Pole

Series C® Molded Case Circuit Breakers G-Frame 15-100 Amperes

Types GC, GHC One-Pole Only



Suitable for Cable Mounting, Line and Load

Terminals, Line and Load Side


Type Terminal	Breaker Amperes	Wire Type and Size
Clamp and Binding Screw	15-20	#14-#10 Cu/Al
Pressure Collar	25-100	#10-1/0 Cu/Al

Clamp Supplied on
15 thru 20 Amp Ratings
Wire Range #14-10 Cu/Al

Line End




Clamp Supplied on
15 thru 20 Amp Ratings
Wire Range #14-10 Cu/Al



Load End

Q of Handle



ON
TRIP
18°
8°
7°
12°
OFF
RESET

Reproduced from drawing 1374D14

Dimensions in parentheses in millimeters

EAT•N



Series C Molded Case Circuit Breakers, G-Frame, 15-100 Amperes

Types GC, GHC Two-Pole Only


Suitable for Cable Mounting, Line and Load

Terminals, Load and Load Side


Type Terminal	Breaker Amperes	Wire Type and Size
Clamp and Binding Screw	15-20	#14-#10 Cu/Al
Pressure Collar	25-100	#10-1/0 Cu/Al

Clamp Supplied on 15 thru 20 Amp Ratings Wire Range #14-10 Cu/Al

Line End





.141 (3.57) Dia. 2 Holes
.281 (7.14) Dia C-Bores
.218 (5.54) Deep
For Mounting Purposes





Clamp Supplied on 15 thru 20 Amp Ratings Wire Range #14-10 Cu/Al

Load End



Pressure Connectors are Supplied on 25 thru 100 Amp Ratings Wire Range #10-1/0 Cu/Al



Reproduced from drawing 1374D15

Dimensions in parentheses in millimeters

Cutler-Hammer

Westinghouse & Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220



Cutler-Hammer

Dimension Sheet

29-170G

Page 9

June 1995
New Information
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Types GC, GHC and GB, GHB
Circuit Breakers

Page 9: Types GC, GHC Three-Pole
Page 10: Types GB, GHB One-Pole

Series C® Molded Case Circuit Breakers G-Frame 15-100 Amperes


Types GC, GHC Three-Pole Only

Suitable for Cable Mounting, Line and Load


Terminals, Load and Load Side

Type Terminal	Breaker Amperes	Wire Type and Size
Clamp and Binding Screw	15-20	#14-#10 Cu/Al
Pressure Collar	25-100	#10-1/0 Cu/Al



Line End



.141 (3.57) Dia. 4 Holes
.281 (7.14) Dia C'Bores
.18 (4.57) Deep
For Mounting Purposes



Load End



Reproduced from drawing 1374D16

Dimensions in parentheses in millimeters

EATON




Series C Molded Case Circuit Breakers, G-Frame, 15-100 Amperes

Types GB, GHB Bolt-On One-Pole Only



Terminals, Load Side Only

Type Terminal	Breaker Amperes	Wire Type and Size
Clamp	15-20	#14-#10 Cu/Al
Pressure	25-100	#10-1/0 Cu/Al

Line End



Load End



Reproduced from drawing 1372D97

Dimensions in parentheses in millimeters

Cutler-Hammer

Westinghouse & Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220

Printed in U.S.A.

June 1995

EATON



Series C® Molded Case Circuit Breakers G-Frame 15-100 Amperes


Types GB, GHB Bolt-On Two-Pole Only

Terminals, Load Side Only

Type Terminal	Breaker Amperes	Wire Type and Size
Clamp	15-20	#14-#10 Cu/Al
Pressure	25-100	#10-1/0 Cu/Al


Line End

.234 (5.95) Diameter Holes



Load End

Clamp Supplied on 15 thru 20 Amp
Ratings Wire Range #14-#10 Cu/Al





Series C Molded Case Circuit Breakers, G-Frame, 15-100 Amperes


Types GB, GHB Bolt-On Three-Pole Breakers

Terminals, Load Side Only


Type Terminal	Breaker Amperes	Wire Type and Size
Clamp	15-20	#14 - #10 Cu/Al
Pressure	25-100	#10-1/0 Cu/Al

Line End


.234 (5.95) Diameter Holes



Load End



Clamp Supplied on 15 thru
20 Amp Ratings Wire Range
#14- #10 Cu/Al




Reproduced from drawing 1370D84

Dimensions in parentheses in millimeters

Cutler-Hammer

Westinghouse & Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220



Cutler-Hammer

Dimension Sheet
29-170H


Page 1

July 1996
New Information
Mailed to: E, D, C/29-100A


Series C[®] HMCP Motor Circuit Protectors 3-600 Amperes

F-Frame


Front View




Line End



Load End



Side View



MCP Continuous Rating	Hole Size			Current Limiter Pockets
	.203 (5.15)	.234 (5.94)	.266 (6.75)	
3	X			N
5	X			N
7	X			N
10	X			Y
15	X			Y
25		X		N
30		X		N
50		X		Y
70		X		Y
100			X	N
150			X	Y

Breaker Status	Dimension				
	A	B	C	D	E
On	3.07 (77.94)	2.92 (74.13)	3.96 (100.54)	3.40 (86.32)	3.33 (84.54)
Tripped	2.65 (67.28)	2.57 (65.25)	4.06 (103.08)	2.99 (75.91)	2.98 (75.66)
Off	2.08 (52.81)	2.14 (54.33)	4.12 (104.60)	2.42 (61.44)	2.56 (64.99)
Reset	1.98 (50.27)	2.05 (52.04)	4.11 (104.35)	2.30 (58.39)	2.48 (62.96)

Note: For 2 Pole MCP, Current Carrying Parts Omitted From Center Pole





Series C HMCP Motor Circuit Protectors, 3-600 Amperes

F-Frame

Front Cover Cutout

Drilling Plans



Reproduced from drawing 1490D54

Dimensions in parentheses in millimeters

Cutler-Hammer

Westinghouse & Cutler-Hammer Products
 Five Parkway Center
 Pittsburgh, Pennsylvania, U.S.A. 15220

EATON

Printed in U.S.A.


July 1996

July 1996
New Information
Mailed to: E, D, C/29-100A


Series C[®] HMCP Motor Circuit Protectors 3-600 Amperes

J-Frame

Front View




Side View





J-Frame


Drilling Plans



Breaker Mounting


Rear Connecting Studs

Breaker Shown in OFF Position



Load End


Reproduced from drawings 1491D65 and 1491D67



Front Cover Cutout

Drawout Support Blocks

Breaker Mounting Holes
Use .250-20 (M6X1) X
2.875 (73.025) Pan Head
Screw With Sems.
Tightening Torque
65 Lb-in (7.34) Nm.



Load End

Breaker Status	Dimension						Hdl. Oper. Force
	A	B	C	D	E	F	
On	5.24 (132.10)	5.12 (130.05)	5.54 (140.72)	5.49 (139.45)	4.77 (121.56)	4.72 (119.89)	32 Lb. (142.3 Nm)
Tripped	4.79 (121.67)	4.71 (119.63)	5.10 (129.54)	5.10 (129.54)	4.87 (123.70)	4.85 (123.19)	
Off	4.02 (102.11)	4.06 (103.12)	4.33 (109.82)	4.45 (113.03)	4.91 (124.71)	4.95 (125.73)	22 Lb. (97.9 Nm)
Reset	3.91 (99.31)	3.96 (100.58)	4.21 (106.93)	4.36 (110.74)	4.90 (124.46)	4.95 (125.73)	38 Lb. (169.0 Nm)

Dimensions in parentheses in millimeters

Cutler-Hammer

Westinghouse & Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220

Printed in U.S.A.

July 1996



Cutler-Hammer


Dimension Sheet
29-170H

Page 5


July 1996
New Information
Mailed to: E, D, C/29-100A

Series C[®] HMCP Motor Circuit Protectors 3-600 Amperes

**K-Frame
Front View**



Side View



Breaker Status	Dimensions						Handle Force ¹
	A	B	C	D	E	F	
On	5.39 (136.9)	5.20 (132.1)	5.69 (144.5)	5.61 (142.5)	4.72 (119.9)	4.77 (121.2)	30 lbs. (13.61 kgs.)
Tripped	4.77 (121.2)	4.69 (119.1)	5.08 (129.0)	5.11 (129.8)	4.89 (124.2)	4.89 (124.2)	—
Off	4.16 (105.7)	4.21 (106.9)	4.46 (113.3)	4.64 (117.9)	4.95 (125.7)	4.91 (124.7)	25 lbs. (11.34 kgs.)
Reset	4.07 (103.4)	4.14 (105.2)	4.57 (116.1)	4.56 (115.8)	4.95 (125.7)	4.90 (124.5)	35 lbs. (15.87 kgs.)

¹ All handle forces measured approximately 0.125 (3.17) from top of handle.

Reproduced from drawings 1492D63 and 1492D67
Dimensions in parentheses in millimeters


EATON




Series C HMCP Motor Circuit Protectors, 3-600 Amperes

K-Frame Drilling Plans





Rear Connected Studs



Front Connected Terminals



Front Cover Cutout



Reproduced from drawings 1492D63 and 1492D67
 Dimensions in parentheses in millimeters

Cutler-Hammer

Westinghouse & Cutler-Hammer Products
 Five Parkway Center
 Pittsburgh, Pennsylvania, U.S.A. 15220


EATON

July 1996
New Information
Mailed to: E, D, C/29-100A


Series C[®] HMCP Motor Circuit Protectors 3-600 Amperes

L-Frame

Front View



Side View



Handle Forces (From End of Handle)^①








On	45 lbs.
Off	50 lbs.
Reset	60 lbs.

① Measurements taken approximately 3/16 in. from end of handle.



Series C HMCP Motor Circuit Protectors, 3-600 Amperes

L-Frame Drilling Plans



Plug-In Block Mounting Panel

Reproduced from drawings 1493D63 and 1493D67

Dimensions in parentheses in millimeters

Cutler-Hammer

Westinghouse & Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220

E.T.N



February 1993
New Information
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Page 65: Types REA, REH One, Two, and
Three-Pole

Page 66: Type RE One, Two, and Three-Pole

AB DE-ION® Circuit Breakers

Type REA One, Two, and Three-Pole Breakers




Fig. 1
1 Pole Type REA

Fig. 2
2 Pole Type REA

Fig. 3
3 Pole Type REA

Type REH One, Two, and Three-Pole Breakers




Fig. 1
1 Pole Type REH


Fig. 2
2 Pole Type REH

Fig. 3
3 Pole Type REH



AB DE-ION® Circuit Breakers

Type RE One, Two, and Three-Pole Breakers





WESTINGHOUSE

Printed in U.S.A.

Westinghouse Electric Corporation
Distribution and Control Business Unit
Electrical Components Division
Pittsburgh, Pennsylvania, U.S.A. 15220

February 1993




June, 1989
Supersedes Dimension Sheet 29-170,
pages 23-24, dated October, 1977
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Page 23: Types CA, CAH, and HCA 225
Amperes


Page 24: Types JA, KA, MARK 75®
Type HKA 225 Amperes

AB DE-ION® Circuit Breakers


Type CA and CAH Breakers



Drilling Plan



Front Cover Cutout



Line End

Saf-T-Vue Cover (When Included)

$\frac{1}{8}$ Diameter $\frac{5}{16}$ Deep
Accepts #6 Thread
Cutting Screw

$\frac{3}{4}$ Rad.

$8\frac{1}{2}^\circ$ Tripped

$16\frac{1}{2}^\circ$ On

17° Reset

$10\frac{1}{2}^\circ$ Off

$\frac{5}{16}$ Thick 4° Taper

Load End

Removable Trip Unit Available in
Type KA or HKA Breaker Only

$\frac{9}{32}$ Diameter Mounting Holes

$\frac{1}{2}$ Diameter Counterbore (4) Holes

Magnetic
Trip
Adjustment

Support Blocks not Supplied With
Breaker Must be Ordered Separately

Current Carrying Parts
Omitted from Center Pole
for 2 Pole Breaker

Rear Con

Breaker Rating, Amps.	Catalog Number	Wire Range, Type No. of Cables
-----------------------	----------------	-----------------------------------

70-225	TA225LA1	1 #6-350 MCM Cu, or 1 #4-350 MCM Al
--------	----------	--

70-225	T225LA	1 #6-350 MCM
70-225⑤	T225LBF	1 #6-250 MCM

Do not Use More Than
25 ft. Lbs. Torque
to Tighten Nuts

Poles	Ampere Rating	Kit Style Number	Thread Size
2	70-225	313C644G29	1/2 - 13
3	70-225	313C644G30	1/2 - 13

The diagram shows a side view of a mounting panel assembly. Key dimensions include:

- Total length: $6\frac{9}{16}$
- Distance from left end to center of first hole: $2\frac{1}{8}$
- Hole diameter: $\frac{3}{8}$
- Thread specification for first hole: $\frac{3}{8}-16$ Thread
- Distance between centers of two holes: $17\frac{32}$
- Distance from center of second hole to right end: $6\frac{9}{16}$
- Panel thickness: $\frac{1}{16}$
- Distance from left end to center of second hole: $1\frac{1}{16}$
- Distance from center of second hole to center of third hole: $3\frac{5}{8}$
- Thread specification for third hole: $\frac{1}{2}-13$ Thread
- Labels: "More Than", "S. Torque", "N Nuts", "Breaker", "Mounting Panel"

Stud Ampere Rating	Stud Style Number	Panel - Thickness A	Tube Length		Tube Style Number
			B	C	
225A short	656D565G01	$\frac{3}{4}$ to 1	$2\frac{1}{32}$		456D983H05
225A long	656D565G02	$\frac{3}{4}$ to 1		$3\frac{1}{32}$	456D983H08
225A short	656D565G01	$\frac{1}{2}$ to $\frac{3}{4}$	$1\frac{1}{32}$		456D983H06
225A long	656D565G02	$\frac{1}{2}$ to $\frac{3}{4}$		$4\frac{1}{32}$	456D983H09
225A short	656D565G01	$\frac{1}{4}$ to $\frac{1}{2}$	$1\frac{1}{32}$		456D983H07
225A long	656D565G02	$\frac{1}{4}$ to $\frac{1}{2}$		$4\frac{1}{32}$	456D983H10

Stud complete consists of one stud assembly and one tube as per chart
Order long and short studs as required to obtain proper bus spacing.

Line End

1/4-20 Top
(4) Holes

3 31/32

4 15/32

5 5/16

Load End

[illegible][illegible][illegible]




March 1990
Supersedes Dimension Sheet 29-170,
pages 27-28, dated October 1977
Mailed to: E, D, C/29-100A, 31-400A,
31-500A


Page 27: Types LAB, LA and MARK 75®
Type HLA 400 Amperes
Page 28: Types LB, LBB and MARK 75®
Type HLB 400 Amperes

AB DE-ION® Circuit Breakers

Type LAB, LA and MARK 75® Type HLA Breakers 400 Amperes




Rear Connected Studs (For Non-Conductive Panels)




Ampere Rating	Style Number	Dimension A	Thread Size
225	1241345	3 3/32	1/2-13
225	1241346	6 3/32	1/2-13
225	1241392	4 3/32	1/2-13
400	0587383G15	5 15/32	3/4-16
400	0587383G16	7 3/32	3/4-16
400	0587383G17	10 15/32	3/4-16

Plug-In Adapter Kit




Poles	Ampere Rating	Style Number	Thread Size
2	70 to 400	313C644G25	3/4-16
3	70 to 400	313C644G26	3/4-16


Drilling Plans For Mounting Bolts




For Rear Connected Studs (Non-Conductive Panels)



For Plug-In Block




Front Cover Cutout






Type LB, LBB and MARK 75® Type HLB Breakers



Front Connected Terminals

Max. Amps	Catalog No.	Wire Size
For Copper Cable (Must be Specified)		
225	T225LA	Single Cable 6-350 MCM
225	T225LBF	Single Cable 6-250 MCM
350	T350DA	Single Cable 250-500 MCM
For AL/CU Cable (Supplied as Standard)		
225	TA225LA1	Single Cable 6-350 MCM Copper or 4-350 MCM Aluminum
350	TA350DA	Single Cable 250-500 MCM AL/CU
400A	T400DA2	Double Cable 3/0-250 MCM CU Only


Rear Connected Studs



Stud Ampere Rating	Stud Style Number	Panel Thickness A	Tube length B C	Tube Style Number
400A-short	656D565G03	3/4 to 1	2 1/2	313C909H17
400A-long	656D565G04	3/4 to 1	3 2 1/2	313C909H20
400A-short	656D565G03	1/2 to 3/4	1 3/2	313C909H18
400A-long	656D565G04	1/2 to 3/4	4 1/2	313C909H21
400A-short	656D565G03	1/4 to 1/2	1 1 1/2	313C909H19
400A-long	656D565G04	1/4 to 1/2	4 3/2	313C909H22


Stud complete consists of one stud assembly and one tube as per chart.

Drilling Plans
For Mounting Bolts




For Rear Connected Studs


Omit Holes in Center Pole
for 2 Pole Breaker



For Plug-in Block



Front Cover Cutout



Plug-In Adapter Kit


Poles	Ampere Rating	Kit Style Number	Thread Size
2	250-400	313C644G45	3/4-16
3	250-400	313C644G46	3/4-16

Reproduced From Drawing 5680D06


Westinghouse Electric Corporation
Distribution and Control Business Unit
Electrical Components Division
Pittsburgh, Pennsylvania, U.S.A. 15220




Type NC, NCG, NCY, MARK 75® Type HNC, HNCG Breakers®




Bolted Rear Connected Studs For 700-800 Amps




For 900-1200 Amps Only




Drilling Plans For Mounting Bolts



For Rear Connected Studs (Insulated Panel)



Front Cover Cutout






February 1991
Supersedes Dimension Sheet 29-170,
pages 35-36, dated November 1981
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Type NB and MARK 75® Type HNB


Page 35: Type NB, MARK 75® Type HNB
Page 36: Mounting Block for Type NB,
MARK 75 HNB, SELTRONIC™ Types NC,
MARK 75 HNC

AB DE-ION® Circuit Breakers

Type NB, MARK 75® Type HNB Breakers




Bolted Rear Connected Studs For 700 to 800 Amps




Style No.	A
623B222G01	5 1/2
623B222G02	8
623B222G03	10 1/2

For 900 to 1200 Amps Only



Front Cover Cutout



Style No.	A
623B222G01	5 1/2
623B222G02	8
623B222G03	10 1/2

Ⓢ Changed since previous issue.




Technical drawing of a circuit breaker assembly, showing front and side views with dimensions and labels.

Front View (Top):

- Overall width: 18
- Overall height: 19
- Breaker Mounting Hardware (indicated by a callout arrow)
- Dimensions from left edge: 5, 1/32, 47, 64, 23, 64.
- Dimensions from bottom edge: 1/16, 7, 1 1/2.
- Center of Handle (indicated by a callout arrow)

Front View (Bottom):

- Breaker Mounting Hardware (indicated by a callout arrow)
- Dimensions from left edge: 5, 1/32, 47, 64, 23, 64.
- Dimensions from bottom edge: 1/16, 7, 1 1/2.
- Center of Handle (indicated by a callout arrow)
- Dimensions from center of handle: 3/4, 3/4, 3/4, 3/4, 3/4, 3/4, 3/4, 3/4.
- Dimensions from center of handle: 3/4, 3/4, 3/4, 3/4, 3/4, 3/4, 3/4, 3/4.
- 9/16 Diameter (4 Holes) (indicated by a callout arrow)
- 9/16 Diameter (4 Holes) (indicated by a callout arrow)



Reproduced From Drawing 4990D37

Printed in U.S.A.




October, 1988
Supersedes Dimension Sheet 29-170,
pages 41-42, dated October, 1977
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Types PC, PCC SELTRONIC™ Circuit
Breakers

Page 41: 2000 and 2500 Amperes
Page 42: 3000 Amperes


AB DE-ION® Circuit Breakers

Type PC, PCC 2000 and 2500 Rear Connected Breakers





Type PC, PCC 3000 Rear Connected Breakers






December, 1988
Supersedes Dimension Sheet 29-170,
pages 43-44, dated October, 1977
Mailed to: E, D, C/29-100A, 31-400A, 31-500A

SELTRONIC™ Circuit Breakers

Page 43: Types PCF, PCCF, PCFG, PCCFG,
2000 and 2500 Amp Front Connected
Page 44: Ground Fault Indicator kit


AB DE-ION® Circuit Breakers

Type PCF, PCCF, PCFG, PCCFG 2000, 2500 Breakers







Ground Fault Indicator Kit for SELTRONIC™ Breakers



Drilling Plan and Cutout® For Face Mounting Bracket



Reproduced From Drawing 750B870


Ⓢ Changed or added since previous issue.

Westinghouse Electric Corporation
Distribution and Control Business Unit
Electrical Components Division
Pittsburgh, Pennsylvania, U.S.A. 15220

© Changed since previous issue.



Mounting Block for Type NB TRI-PAC® Breakers©



Reproduced From Drawing 4990D38

● Changed since previous issue.

January, 1989

Printed in USA



Type LCL 400 Amp Frame Current Limiting Breaker


Terminal Arrangements

For Use With Cu/Al Cable (Supplied As Standard)

Single	TA225LA1	125-225	#6-350 MCM Cu or #4-350 MCM Al
Double	TA400LA1	250-400	#4-250 MCM Cu/Al Plus 3/0-600 MCM Cu/Al


For Use With Copper Cable Only (Must Be Specified)

Cable	Catalog Number	Ampere Rating	Wire Size
Single	T225LA	125-225	#6-350 MCM
Double	T401LA	250-400	4-250 and 3/0-600 MCM



Rear Connected Studs

Stud Ampere Rating	Stud Style Number	Thread Dimension Size A
125-225	1241345	1/2-13 33/16
125-225	1241392	1/2-13 415/16
125-225	1241346	1/2-13 61/4
250-400	05B7383G15	3/4-16 515/32
250-400	05B7383G16	3/4-16 731/32
250-400	05B7383G17	3/4-16 1015/32





Do not Use More Than 25 Ft. Lbs.
Torque to Tighten Nuts

Plug-in Adapter Kit

Poles	Ampere Rating	Kit Style Number	Thread Size
2	125-400	313C644G25	3/4-16
3	125-400	313C644G26	3/4-16


Do not Use More Than 25 Ft. Lbs.
Torque to Tighten Nuts




Nameplate (Used with Ground Fault Trip)

Drilling Plans


For Plug-In Block




Rear Connected Studs (For Non-Conductive Panels)




For Mounting Bolts



Front Cover Cutout





Reproduced From Drawing 1371D33




Page 53: For Types JB, KB
Page 54: For Types LAB, LA, LC



Motor Operators for LAB, LA and LC Breakers



Drilling Plan and Cutout (Adapter Plate)



Reproduced From Drawing 5669D04

Westinghouse Electric Corporation
Distribution and Control Business Unit
Electrical Components Division
Pittsburgh, Pennsylvania, U.S.A. 15220



Cutler-Hammer

Dimension Sheet

29-170G

Page 1

June 1995
New Information
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Type GD Circuit Breakers

Page 1: Type GD One-Pole

Page 2: Type GD Two-Pole

Series C® Molded Case Circuit Breakers G-Frame 15-100 Amperes

Type GD One-Pole Only



Suitable for Cable Mounting, Line and Load

Terminal, Line and Load Side

Type Terminal	Breaker Amperes	Wire Type and Size
Clamp and Binding Screw	15-20	#14-#10 Cu/Al
Pressure Collar	25-100	#10-1/0 Cu/Al



Clamp Supplied on
15 thru 20 Amp Ratings
Wire Range #14-10 Cu/Al

Line End





Clamp Supplied on
15 thru 20 Amp Ratings
Wire Range #14-10 Cu/Al

Load End



Pressure Connectors are
Supplied on 25 thru 100 Amp
Ratings Wire Range #10-1/0
Cu/Al



Reproduced from drawing 1374D14

Dimensions in parentheses in millimeters

EATON



Series C Molded Case Circuit Breakers, G-Frame, 15-100 Amperes

Type GD Two-Pole Only


Suitable for Cable Mounting, Line and Load

Terminals, Load and Load Side


Type Terminal	Breaker Amperes	Wire Type and Size
Clamp and Binding Screw	15-20	#14-#10 Cu/Al
Pressure Collar	25-100	#10-1/0 Cu/Al

Clamp Supplied on
15 thru 20 Amp Ratings
Wire Range #14-10 Cu/Al


Line End



.141 (3.57) Dia. 2 Holes
.281 (7.14) Dia. C Bores
.218 (5.54) Deep
For Mounting Purposes





Pressure Connectors are
Supplied on 25 thru 100 Amp
Ratings Wire Range #10-1/0 Cu/Al



Clamp Supplied on
15 thru 20 Amp Ratings
Wire Range #14-10 Cu/Al

Load End



Reproduced from drawing 1374D15

Dimensions in parentheses in millimeters

Cutler-Hammer

Westinghouse & Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220

CH



Cutler-Hammer

Dimension Sheet

29-170G

Page 3

June 1995
New Information
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Types GD, GDB Bolt-On Panelboard
Circuit Breakers

Page 3: Type GD Three-Pole
Page 4: Type GDB Bolt-On One-Pole


Series C® Molded Case Circuit Breakers G-Frame 15-100 Amperes

Type GD Three-Pole Only


Terminals, Load and Load Side

Type Terminal	Breaker Amperes	Wire Type and Size
Clamp and Binding Screw	15-20	#14-#10 Cu/Al
Pressure Collar	25-100	#10-1/0 Cu/Al


Line End



Load End



Suitable for Cable Mounting, Line and Load



Reproduced from drawing 1374D16

Dimensions in parentheses in millimeters

EATON




Series C Molded Case Circuit Breakers, G-Frame, 15-100 Amperes

Type GDB Bolt-On One-Pole Only


Terminals, Load Side Only

Type Terminal	Breaker Amperes	Wire Type and Size
Clamp	15-20	#14-#10 Cu/Al
Pressure	25-100	#10-1/0 Cu/Al


Line End



Load End



Clamp Supplied on 15 thru 20 Amp Ratings Wire Range #14-#10 Cu/Al



Reproduced from drawing 1372D97

Dimensions in parentheses in millimeters

Cutler-Hammer

Westinghouse & Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220

EATON

Printed in U.S.A.

June 1995



Cutler-Hammer

Dimension Sheet

29-170G

Page 5

June 1995

New Information

Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Type GDB Bolt-On Panelboard
Circuit Breakers

Page 5: Type GDB Bolt-On Two-Pole

Page 6: Type GDB Bolt-On Three-Pole

Series C® Molded Case Circuit Breakers G-Frame 15-100 Amperes


Type GDB Bolt-On Two-Pole Only

Terminals, Load Side Only

Type Terminal	Breaker Amperes	Wire Type and Size
Clamp	15-20	#14-#10 Cu/Al
Pressure	25-100	#10-1/0 Cu/Al


Line End

.234 (5.95) Diameter Holes



Load End

Clamp Supplied on 15 thru 20 Amp
Ratings Wire Range #14-#10 Cu/Al



Reproduced from drawing 1373D57

Dimensions in parentheses in millimeters

EATON




Type GDB Bolt-On Three-Pole Breakers

Terminals, Load Side Only

Type Terminal	Breaker Amperes	Wire Type and Size
Clamp	15-20	#14-#10 Cu/Al
Pressure	25-100	#10-1/0 Cu/Al


Line End

.234 (5.95) Diameter Holes



Load End

Clamp Supplied on 15 thru
20 Amp Ratings Wire Range
#14-#10 Cu/Al



Reproduced from drawing 1370D84

Dimensions in parentheses in millimeters

Cutler-Hammer

Westinghouse & Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220



Cutler-Hammer

Dimension Sheet

29-170G

Page 7

June 1995
New Information
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Types GC, GHC Circuit Breakers

Page 7: Types GC, GHC One-Pole

Page 8: Types GC, GHC Two-Pole

Series C® Molded Case Circuit Breakers G-Frame 15-100 Amperes

Types GC, GHC One-Pole Only



Suitable for Cable Mounting, Line and Load

Terminals, Line and Load Side


Type Terminal	Breaker Amperes	Wire Type and Size
Clamp and Binding Screw	15-20	#14-#10 Cu/Al
Pressure Collar	25-100	#10-1/0 Cu/Al

Clamp Supplied on
15 thru 20 Amp Ratings
Wire Range #14-10 Cu/Al


Line End




Clamp Supplied on
15 thru 20 Amp Ratings
Wire Range #14-10 Cu/Al



Load End




Pressure Connectors are
Supplied on 25 thru 100 Amp
Ratings Wire Range #10-1/0
Cu/Al



ON
TRIP
18°
8°
7°
12°
OFF
RESET

Q of Handle



Reproduced from drawing 1374D14

Dimensions in parentheses in millimeters





EATON



Series C Molded Case Circuit Breakers, G-Frame, 15-100 Amperes
Types GC, GHC Two-Pole Only **Suitable for Cable Mounting, Line and Load**

Terminals, Load and Load Side

Type Terminal	Breaker Amperes	Wire Type and Size
Clamp and Binding Screw	15-20	#14-#10 Cu/Al
Pressure Collar	25-100	#10-1/0 Cu/Al



Reproduced from drawing 1374D15

Dimensions in parentheses in millimeters

Cutler-Hammer
Westinghouse & Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220





Cutler-Hammer

Dimension Sheet

29-170G

Page 9

June 1995
New Information
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Types GC, GHC and GB, GHB
Circuit Breakers

Page 9: Types GC, GHC Three-Pole
Page 10: Types GB, GHB One-Pole

Series C® Molded Case Circuit Breakers G-Frame 15-100 Amperes


Types GC, GHC Three-Pole Only

Suitable for Cable Mounting, Line and Load



Terminals, Load and Load Side

Type	Breaker	Wire Type
Terminal	Amperes	and Size
Clamp and	15-20	#14-#10 Cu/Al
Binding Screw		
Pressure Collar	25-100	#10-1/0 Cu/Al

Line End



Load End



Width of Mounting Slots

Reproduced from drawing 1374D16

Dimensions in parentheses in millimeters

EATON




Series C Molded Case Circuit Breakers, G-Frame, 15-100 Amperes

Types GB, GHB Bolt-On One-Pole Only



Terminals, Load Side Only

Type Terminal	Breaker Amperes	Wire Type and Size
Clamp	15-20	#14- #10 Cu/Al
Pressure	25-100	#10-1/0 Cu/Al

Line End



Load End



Reproduced from drawing 1372D97

Dimensions in parentheses in millimeters

Cutler-Hammer

Westinghouse & Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220

EATON

Printed in U.S.A.

June 1995



Cutler-Hammer

Dimension Sheet

29-170G

Page 11

June 1995
New Information
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Types GB, GHB Bolt-On Panelboard
Circuit Breakers

Page 11: Types GB, GHB Bolt-On Two-Pole
Page 12: Types GB, GHB Bolt-On Three-Pole

Series C® Molded Case Circuit Breakers G-Frame 15-100 Amperes


Types GB, GHB Bolt-On Two-Pole Only

Terminals, Load Side Only


Type	Breaker	Wire Type
Terminal	Amperes	and Size
Clamp	15-20	#14-#10 Cu/Al
Pressure	25-100	#10-1/0 Cu/Al

Line End


.234 (5.95) Diameter Holes



Load End



Clamp Supplied on 15 thru 20 Amp
Ratings Wire Range #14-#10 Cu/Al



Reproduced from drawing 1373D57

Dimensions in parentheses in millimeters

EATON



Series C Molded Case Circuit Breakers, G-Frame, 15-100 Amperes


Types GB, GHB Bolt-On Three-Pole Breakers

Terminals, Load Side Only



Type Terminal	Breaker Amperes	Wire Type and Size
Clamp	15-20	#14-#10 Cu/Al
Pressure	25-100	#10-1/0 Cu/Al

Line End

.234 (5.95) Diameter Holes



Load End




Reproduced from drawing 1370D84

Dimensions in parentheses in millimeters

Cutler-Hammer


Westinghouse & Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220



Type FD One-Pole

Westinghouse Series C® Molded Case Circuit Breakers F-Frame 10-225 Amperes

Front View



Breaker Status	Dimensions					Handle Force, Lbs.●
	A	B	C	D	E	
On	3.07 (77.98)	2.92 (74.17)	3.96 (100.58)	3.40 (86.36)	3.33 (84.58)	8 (3.63 kgs.)
Tripped	2.65 (67.31)	2.57 (65.28)	4.06 (103.12)	2.99 (75.94)	2.98 (75.69)	3② (1.36 kgs.)
Off	2.08 (52.83)	2.14 (54.36)	4.12 (104.65)	2.42 (61.47)	2.56 (65.02)	9 (4.08 kgs.)
Reset	1.98 (50.29)	2.05 (52.07)	4.11 (104.39)	2.30 (58.42)	2.48 (63.10)	10 (4.54 kgs.)


② Applied by breaker handle to external handle mechanism.

Reproduced from drawings 1490D61 and 1490D65



Dimensions in parentheses in millimeters



Front Cover Cutout



Rear Connected



Dimensions in parentheses in millimeters

Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220



Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220

Dimension Sheet
29-170F

Page 3


January 1995
New Information
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Type FD Two-Pole


Westinghouse Series C® Molded Case Circuit Breakers F-Frame 10-225 Amperes

Type FD Two-Pole Outline

Front View



Side View



Breaker Status	Dimensions					Handle Force, Lbs. ①
	A	B	C	D	E	
On	3.07 (77.98)	2.92 (74.17)	3.96 (100.58)	3.40 (86.36)	3.33 (84.58)	12 (5.44 kgs.)
Tripped	2.65 (67.31)	2.57 (65.28)	4.06 (103.12)	2.99 (75.94)	2.98 (75.69)	4② (1.81 kgs.)
Off	2.08 (52.83)	2.14 (54.36)	4.12 (104.65)	2.42 (61.47)	2.56 (65.02)	15 (6.80 kgs.)
Reset	1.98 (50.29)	2.05 (52.07)	4.11 (104.39)	2.30 (58.42)	2.48 (63.10)	20 (9.07 kgs.)

① Measured .125 (3.175) above Escutcheon.

② Applied by breaker handle to external handle mechanism.

Reproduced from drawings 1490D62 and 1490D66


Dimensions in parentheses in millimeters

EATON




Westinghouse Series C® Molded Case Circuit Breakers, F-Frame, 10-225 Amperes Type FD Two-Pole Outline


Front Cover Cutout



Drilling Plans Front Connected



Rear Connected



Reproduced from drawings 1490D62 and 1490D66


Dimensions in parentheses in millimeters

Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220




Westinghouse Series C® Molded Case Circuit Breakers, F-Frame, 10-225 Amperes Type FD Three-Pole Outline


Front Cover Cutout



Drilling Plans Front Connected




Rear Connected



Reproduced from drawings 1490D63 and 1490D67

Dimensions in parentheses in millimeters

Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220



Type FD Four-Pole

Westinghouse Series C® Molded Case Circuit Breakers F-Frame 10-225 Amperes

Line End

.188 R (4.78) R

.750 (19.05)

1.406 (35.71)

1.719 (43.66)

2.719 (69.06)

4.500 (114.30)

.090 (2.3) R (Typ.)

4-PLC S

.750 (19.05)

.172 (4.37)

.016 (.41)

1.375 (34.93)

.687 (17.37)

1.375 (34.93)

.344 (8.74)

.016 (.41)

1.375 (34.93)

1.375 (34.93)

1.375 (34.93)

.375 (9.53)

.375 (9.53)

.375 (9.53)

.375 (9.53)

.156 (3.96) R

On

Off

Push to Trip

.125 (.318) diameter x .484 (12.29) deep, 6 holes accept #8(M4) thread cutting screws

.450 (11.43) diameter 8 holes

.110 (2.79) diameter x .310 (7.87) deep, 4 holes accept #6(M3.5) thread cutting screws

.740 (18.80)

1.562 (39.67)

Load End

2.063 (52.40)

5.500 (139.70)

1.000 (25.40)

.500 (12.70)

1.562 (39.67)

.740 (18.80)

Breaker Status

On

Tripped

Off

Reset

[illegible]

Breaker Status	Dimensions					Handle Force, Lbs.●
	A	B	C	D	E	
On	3.07 (77.98)	2.92 (74.17)	3.96 (100.58)	3.40 (86.36)	3.33 (84.58)	14 (6.35 kgs.)
Tripped	2.65 (67.31)	2.57 (65.28)	4.06 (103.12)	2.99 (75.94)	2.98 (75.69)	4② (1.81 kgs.)
Off	2.08 (52.83)	2.14 (54.36)	4.12 (104.65)	2.42 (61.47)	2.56 (65.02)	16 (7.26 kgs.)
Reset	1.98 (50.29)	2.05 (52.07)	4.11 (104.39)	2.30 (58.42)	2.48 (63.10)	21 (9.53 kgs.)


① Measured .125 (3.175) above Escutcheon.

② Applied by breaker handle to external handle mechanism.




Westinghouse Series C® Molded Case Circuit Breakers, F-Frame, 10-225 Amperes Type FD Four-Pole Outline

Front Cover Cutout




Drilling Plans

Front Connected



Rear Connected



Reproduced from drawings 1490D64 and 1490D68

Dimensions in parentheses in millimeters

Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220



Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220

Dimension Sheet
29-170J

Page 1


January 1995
New Information
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Types JD, HJD, JDC Two- and Three-Pole


Westinghouse Series C® Molded Case Circuit Breakers J-Frame 70-250 Amperes

Types JD, HJD, JDC Two- and Three-Pole Breakers

Front View



Side View



Front Connected Terminals

Catalog Number	Cable	Amp Rating	Wire Size	Torque
T250KB	Cu Single	70-250	#4 to 350 MCM	180 Lb-in (20.3 Nm)
TA250KB	Cu-Al Single	70-250	#4 to 350 MCM	275 Lb-in (31.1 Nm)

Reproduced from drawings 1491D63 and 1491D67

Dimensions in parentheses in millimeters





EATON




Westinghouse Series C Molded Case Circuit Breakers, J-Frame, 70-250 Amperes

Types JD, HJD, JDC Two- and Three-Pole Breakers *Continued*

Drilling Plans




Breaker Shown in OFF Position



Drawout Support Blocks

Breaker Mounting Holes Use .250-.20 (M6X1) X 2.875 (73.025) Pan Head Screw With Sems. Tightening Torque 65 Lb-in (7.34) Nm.



Reproduced from drawings 1491D65 and 1491D67

Breaker Status	Dimension						Hdl. Oper. Force
	A	B	C	D	E	F	
On	5.24 (132.10)	5.12 (130.05)	5.54 (140.72)	5.49 (139.45)	4.77 (121.56)	4.72 (119.89)	32 Lb. (142.3 Nm)
Tripped	4.79 (121.67)	4.71 (119.63)	5.10 (129.54)	5.10 (129.54)	4.87 (123.70)	4.85 (123.19)	
Off	4.02 (102.11)	4.06 (103.12)	4.33 (109.82)	4.45 (113.03)	4.91 (124.71)	4.95 (125.73)	22 Lb. (97.9 Nm)
Reset	3.91 (99.31)	3.96 (100.58)	4.21 (106.93)	4.36 (110.74)	4.90 (124.46)	4.95 (125.73)	38 Lb. (169.0 Nm)

Dimensions in parentheses in millimeters

Cutler-Hammer

Westinghouse & Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220



Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220

Dimension Sheet
29-170J

Page 3



January 1995
New Information
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Types JD, HJD, JDC Four-Pole

Westinghouse Series C® Molded Case Circuit Breakers J-Frame 70-250 Amperes

Types JD, HJD, JDC Four-Pole Breakers

Front View



Front Connected Terminals

Catalog Number	Cable	Amp Rating	Wire Size	Torque
T250KB	Cu Single	70-250	#4 to 350 MCM	180 Lb-in (20.3 Nm)
TA250KB	Cu-Al Single	70-250	#4 to 350 MCM	275 Lb-in (31.1 Nm)

Reproduced from drawings 1491D64 and 1491D68

Dimensions in parentheses in millimeters



EAT•N



Westinghouse Series C Molded Case Circuit Breakers, J-Frame, 70-250 Amperes


Types JD, HJD, JDC Four-Pole Breakers *Continued*

Drilling Plans




Breaker Shown in OFF Position

Line End



Breaker Mounting Holes Use .250-20 (M6X1) X 2.875 (73.025) Pan Head Screw With Sems. Tightening Torque 65 Lb-in (7.34) Nm.

Line End




Reproduced from drawings 1491D64 and 1491D68

Dimensions in parentheses in millimeters

Breaker Status	Dimension						Hdl. Oper. Force
	A	B	C	D	E	F	
On	5.24 (132.10)	5.12 (130.05)	5.54 (140.72)	5.49 (139.45)	5.47 (124.71)	4.72 (119.89)	32 Lb. (142.3 Nm)
Tripped	4.79 (121.67)	4.71 (119.63)	5.10 (129.54)	5.10 (129.54)	4.87 (123.70)	4.85 (123.19)	
Off	4.02 (102.11)	4.06 (103.12)	4.33 (109.82)	4.45 (113.03)	4.91 (124.71)	4.95 (125.73)	22 Lb. (97.9 Nm)
Reset	3.91 (99.31)	3.96 (100.58)	4.21 (106.93)	4.36 (110.74)	4.90 (124.46)	4.95 (125.73)	38 Lb. (169.0 Nm)

Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220



Type KD Two- and Three-Pole

Electronic – 70-400 Amperes
Thermal-Magnetic – 100-400 Amperes

Front View



Trough for Attachment Leads

.188 (4.77) Dia.
C'Bore x .031 (.79)
DP .147 (12.7) Dia.
Hole x .500 DP to
Accept #8 (M4)
Thread Cutting
Screws (8 Places)

.125 (3.18) Wide x
.750 (19.05) Slots for
Attachment Leads



Load End

Breaker Status	Dimensions						Handle Force ⁽¹⁾
	A	B	C	D	E	F	
On	5.39 (136.9)	5.20 (132.1)	5.69 (144.5)	5.61 (142.5)	4.72 (119.9)	4.77 (121.2)	30 lbs. (13.61 kgs.)
Tripped	4.77 (121.2)	4.69 (119.1)	5.08 (129.0)	5.11 (129.8)	4.89 (124.2)	4.89 (124.2)	---
Off	4.16 (105.7)	4.21 (106.9)	4.46 (113.3)	4.64 (117.9)	4.95 (125.7)	4.91 (124.7)	25 lbs. (11.34 kgs.)
Reset	4.07 (103.4)	4.14 (105.2)	4.57 (116.1)	4.56 (115.8)	4.95 (125.7)	4.90 (124.5)	35 lbs. (15.87 kgs.)

① All handle forces measured approximately 0.125 (3.17) from top of handle.

Reproduced from drawings 1492D63 and 1492D67
Dimensions in parentheses in millimeters




Westinghouse Series C® Molded Case Circuit Breakers, K-Frame


Electronic – 70-400 Amperes; Thermal-Magnetic – 100-400 Amperes

Type KD Two- and Three-Pole Breakers, Drilling Plans



Rear Connected Studs



Front Connected Terminals



Front Cover Cutout



Reproduced from drawings 1492D63 and 1492D67
Dimensions in parentheses in millimeters

Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220



Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220

Dimension Sheet
29-170K

Page 3

January 1995
New Information
Mailed to: E, D, C/29-100A, 31-400A,
31-500A


Type KD Four-Pole

Westinghouse Series C® Molded Case Circuit Breakers K-Frame


Electronic – 70-400 Amperes
Thermal-Magnetic – 100-400 Amperes

Type KD Four-Pole Breakers

Front View



Side View



Breaker Status	Dimensions						Handle Force ^①
	A	B	C	D	E	F	
On	5.39 (136.9)	5.20 (132.1)	5.69 (144.5)	5.61 (142.5)	4.72 (119.9)	4.77 (121.2)	30 lbs. (13.61 kgs.)
Tripped	4.77 (121.2)	4.69 (119.1)	5.08 (129.0)	5.11 (129.8)	4.89 (124.2)	4.89 (124.2)	—
Off	4.16 (105.7)	4.21 (106.9)	4.46 (113.3)	4.64 (117.9)	4.95 (125.7)	4.91 (124.7)	25 lbs. (11.34 kgs.)
Reset	4.07 (103.4)	4.14 (105.2)	4.57 (116.1)	4.56 (115.8)	4.95 (125.7)	4.90 (124.5)	35 lbs. (15.87 kgs.)

① All handle forces measured approximately 0.125 (3.17) from top of handle.

Reproduced from drawings 1492D64 and 1492D68
Dimensions in parentheses in millimeters

EATON




Westinghouse Series C® Molded Case Circuit Breakers, K-Frame


Electronic – 70-400 Amperes; Thermal-Magnetic – 100-400 Amperes

Drilling Plans


Rear Connected Studs



Front Connected Terminals



Front Cover Cutout



Reproduced from drawings 1492D64 and 1492D68

Dimensions in parentheses in millimeters

Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220



Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220

Dimension Sheet
29-170L

Page 1


January 1995
New Information
Mailed to: E, D, C/29-100A,
31-400A,
31-500A

Types LD, HLD, LDC Two- and
Three-Pole


Westinghouse Series C® Molded Case Circuit Breakers L-Frame 300-600 Amperes

Types LD, HLD, LDC Two- and Three-Pole Breakers

Front View



Side View



Handle Forces (From End of Handle)①

On	45 lbs.
Off	50 lbs.
Reset	60 lbs.

① Measurements taken approximately 3/16 in. from end of handle.

Terminal Arrangements







Terminal Catalog No.	Wire Range (MCM)	Number of Cables	Torque
Copper Only Cable (Supplied in Kit Form)			
T602LD	250-350	2	275 Lb-in. (31.1 Nm)
Copper or Aluminum Cable (Supplied in Kit Form)			
TA602LD	250-350	2	275 Lb-in. (31.1 Nm)
TA603LD	400-500	2	275 Lb-in. (31.1 Nm)
TA401LD	4/0-600	1	400 Lb-in. (45.2 Nm)
TA450LD	4-4/0	2	275 Lb-in. (31.1 Nm)



Westinghouse Series C® Molded Case Circuit Breakers, L-Frame, 300-600 Amperes

Types LD, HLD, LDC Two- and Three-Pole Breakers, *Continued*

Drilling Plans



Reproduced from drawings 1493D63 and 1493D67

Dimensions in parentheses in millimeters

Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220



Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220

Dimension Sheet
29-170L

Page 3


January 1995
New Information
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Types LD, HLD, LDC Four-Pole


Westinghouse Series C® Molded Case Circuit Breakers L-Frame 300-600 Amperes

Types LD, HLD, LDC Four-Pole Breakers

Front View



Side View



Handle Forces (From End of Handle)①

On	45 lbs.
Off	50 lbs.
Reset	60 lbs.

① Measurements taken approximately 3/16 in. from end of handle.

Terminal Arrangements








Terminal Catalog No.	Wire Range (MCM)	Number of Cables	Torque
Copper Only Cable (Supplied in Kit Form)			
T602LD	250-350	2	275 Lb-in. (31.1 Nm)
Copper or Aluminum Cable (Supplied in Kit Form)			
TA602LD	250-350	2	275 Lb-in. (31.1 Nm)
TA603LD	400-500	2	275 Lb-in. (31.1 Nm)
TA401LD	4/0-600	1	400 Lb-in. (45.2 Nm)
TA450LD	4-4/0	2	275 Lb-in. (31.1 Nm)



Westinghouse Series C® Molded Case Circuit Breakers, L-Frame, 300-600 Amperes

Types LD, HLD, LDC Four-Pole Breakers, *Continued*

Drilling Plans



Reproduced from drawings 1493D64 and 1493D68


Dimensions in parentheses in millimeters

Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220




Type MD Two- and Three-Pole Breakers, Drilling Plans


For Plug-In Block




For Rear Connected Studs (For Non-Conductive Panels)



For Mounting Bolts



Front Cover Cutout



.563 (14.28) Diameter Hole for 125 to 225 Amps	1.188 (30.15) Diameter Hole for 700 to 800 Amps
.813 (20.63) Diameter Hole for 250 to 400 Amps	6 Holes for 3 Pole Breaker 4 Holes for 2 Pole Breaker
1.063 (26.98) Diameter Hole for 450 to 600 Amps	Omit 2 Center Holes for 2 Pole Breaker

Terminal Arrangements

Cable	Catalog Number	Ampere Rating	Wire Size
For Use With Copper Cable Only			
Single	T350MA	125-350	#1-600 MCM
Double	T600MA1	400-600	2/0-500 MCM
Triple	T800MA1	700-800	3/0-300 MCM
For Use With Al/Cu Cable			
Double	TA700MA1	125-600	#1-500 MCM
Triple	TA800MA2	700-800	3/0-400 MCM

Rear Connected Studs

Stud Ampere Rating	Stud Style Number	Thread Size	Dimension A
125-225	314C960G01	$\frac{1}{2}$ -13	$3\frac{1}{32}$
250-400	314C960G04	$\frac{3}{4}$ -16	$5\frac{29}{32}$
250-400	314C960G05	$\frac{3}{4}$ -16	$8\frac{1}{32}$
250-400	314C960G06	$\frac{3}{4}$ -16	$10\frac{29}{32}$
450-600	314C960G07	1-12	$5\frac{29}{32}$
450-600	314C960G08	1-12	$8\frac{1}{32}$
450-600	314C960G09	1-12	$10\frac{29}{32}$
700-800	314C960G10	$1\frac{1}{8}$ -12	$5\frac{29}{32}$
700-800	314C960G11	$1\frac{1}{8}$ -12	$8\frac{1}{32}$
700-800	314C960G12	$1\frac{1}{8}$ -12	$10\frac{29}{32}$

Plug-In Adapter Kit

Poles	Ampere Rating	Kit Style Number	Thread Size	Fig.
2	125-600	313C644G27	1 $\frac{1}{8}$ "-12	1
3	125-600	313C644G28	1 $\frac{1}{8}$ "-12	1
2	700-800	176C544G01	1 $\frac{1}{8}$ "-12	2
3	700-800	176C544G02	1 $\frac{1}{8}$ "-12	2






Figure 1 (Plug-In Type)



Do Not Use More Than 25 Ft. Lbs. Torque To Tighten Nuts

Figure 2 (Front Removable Bolted Type)

Reproduced from drawing 457D265

Dimensions in parentheses in millimeters

Cutler-Hammer

**Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220**

Printed in U.S.A.

January 1995





Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220

Dimension Sheet
29-170M

Page 3


January 1995
New Information
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Type MDS Two- and Three-Pole


Westinghouse Series C® Molded Case Circuit Breakers M-Frame 400-800 Amperes

Type MDS Two- and Three-Pole Breakers

Front View



Side View



Handle Forces (From End of Handle)

On	50 lbs. (22.68 kgs.)
Off	24 lbs. (10.89 kgs.)
Reset	60 lbs. (27.22 kgs.)

Reproduced from drawing 2605D21
Dimensions in parentheses in millimeters


EATON




Westinghouse Series C® Molded Case Circuit Breakers, M-Frame, 400-800 Amperes

Type MDS Two- and Three-Pole Breakers, Drilling Plans

For Mounting Block (Front Connected Terminals)




For Rear Connected Studs




.813 (20.63) Diameter Hole for 250 Amps to 400 Amps
1.063 (26.98) Diameter Hole for 450 Amps to 600 Amps
1.188 (30.15) Diameter Hole for 700 Amps to 800 Amps

For Plug-In Adapter Kit



Front Cover Cutout



Front Connected Terminals (Must be Ordered Separately)

Amp Rating	Catalog Number	Wire Size Number of Cables
For Al/Cu Cable		
600	TA700MA1	(2) #1-500 MCM
800	TA800MA2	(3) 3/0-400 MCM
For Copper Cable		
600	T600MA1	(2) 2/0-500 MCM
800	T800MA1	(3) 3/0-300 MCM

Rear Connected Studs

2 Required Per Pole (Not Supplied With Breaker)

Stud Ampere Rating	Stud Style Number	Thread Size	Dimension A
250-400	314C960G04	3/4-16	5 ²⁹ / ₃₂
250-400	314C960G05	3/4-16	8 ¹³ / ₃₂
250-400	314C960G06	3/4-16	10 ²⁹ / ₃₂
450-600	314C960G07	1-12	5 ²⁹ / ₃₂
450-600	314C960G08	1-12	8 ¹³ / ₃₂
450-600	314C960G09	1-12	10 ²⁹ / ₃₂
700-800	314C960G10	1 1/8-12	5 ²⁹ / ₃₂
700-800	314C960G11	1 1/8-12	8 ¹³ / ₃₂
700-800	314C960G12	1 1/8-12	10 ²⁹ / ₃₂

Plug-In Adapter Kit

1 Kit Per Breaker (Not Supplied With Breaker)

Poles	Ampere Rating	Kit Style Number	Thread Size	Fig.
2	125-600	313C644G27	1 1/8-12	1
3	125-600	313C644G28	1 1/8-12	1
2	700-800	313C544G01	1 1/8-12	2
3	700-800	313C544G02	1 1/8-12	2




Figure 1

Do Not Use More Than 25 Ft. Lbs. Torque To Tighten Nuts




Figure 2

Reproduced from drawing 260D521

Dimensions in parentheses in millimeters

Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220



Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220

Dimension Sheet
29-170N

Page 1


January 1995
New Information
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Type ND Two- and Three-Pole

Westinghouse Series C® Molded Case Circuit Breakers N-Frame 400-1200 Amperes

Type ND Two- and Three-Pole Breakers


Front View



Side View

Line End

Load End




Dimensions

Breaker Status	A	B
On	7.90 (200.66)	8.30 (210.82)
Tripped	6.50 (165.10)	6.90 (175.26)
Off	5.70 (144.78)	6.10 (154.94)
Reset	5.60 (142.24)	6.00 (152.40)

Handle Forces (At Handle Q)


On	130 lbs. (58.97 kgs.)
Off	105 lbs. (47.63 kgs.)
Reset	160 lbs. (72.57 kgs.)



Reproduced from drawing 1494D64

Dimensions in parentheses in millimeters

EATON




Westinghouse Series C Molded Case Circuit Breakers, N-Frame, 400-1200 Amperes


Type ND Two- and Three-Pole Breakers, *Continued*

Drilling Plans


Rear Connected




Front Connected



Front Cover Cutout



Line End



Load End

Terminal Arrangements

Catalog Number	Wire Range	Number of Cables	Torque Lb-in
Aluminum or Copper Cable			
TA700NB1	#1-500 MCM	2	375
TA1000NB1	3/0-400 MCM	3	375
TA1200NB1	4/0-500 MCM	4	375
TA1201NB1	500-750 MCM	3	450
Copper Cable Only			
T700NB1	2/0-500 MCM	2	300
T1000NB1	3/0-500 MCM	3	300
T1200NB3	3/0-400 MCM	4	275

Drilling Plan for Rear Connecting Studs

Amp Rating	Hole Diameter
700 & 800	1.188 (30.175) Diameter
900-1200	1.312 (33.325) Diameter

Reproduced from drawing 1494D64


Dimensions in parentheses in millimeters

Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220



Westinghouse Series C® Molded Case Circuit Breakers, R-Frame, 800-2500 Amperes


Types RD, RDC Three-Pole Breakers, 2500 Amp Frame, *Continued*



Reproduced from drawings 1495D63 and 1495D67

Dimensions in parentheses in millimeters



Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220




Types RD, RDC Four-Pole

Westinghouse Series C® Molded Case Circuit Breakers R-Frame 800-2500 Amperes

Front View



Side View



Terminal Arrangements

Terminal Catalog Number	Terminal Material (Body)	Screw Head Type	Wire Range	Wire Type	Torque
T1600RD	Copper	Socket	1-600[4] (50-300[4])	Cu	375 Lb-in. (42.38 Nm)
TA1600RD	Aluminum	Socket	500-1000[4] (300-500[4])	Cu/Al	550 Lb-in. (62.15 Nm)

Handle Forces●


On	140 lbs.
Off	80 lbs.
Reset	75 lbs.

① Measurements taken approximately 1/4 in. from end of handle.



Westinghouse Series C® Molded Case Circuit Breakers, R-Frame, 800-2500 Amperes

Types RD, RDC Four-Pole Breakers, 2500 Amp Frame, *Continued*



Reproduced from drawings 1495D64 and 1495D68

Dimensions in parentheses in millimeters

Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220



Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220

Dimension Sheet
29-170R

Page 5


January 1995
New Information
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Type FD Three-Pole


Westinghouse Series C[®] Molded Case Circuit Breakers R-Frame 800-2500 Amperes

Types RD 2000-Ampere Terminal Extensions

Front View



Side View



Reproduced from drawing 1495D73


Dimensions in parentheses in millimeters

EAT•N



Westinghouse Series C® Molded Case Circuit Breakers, R-Frame, 800-2500 Amperes

Type RD 2000-Ampere Terminal Extensions, *Continued*



Reproduced from drawing 1495D73

Dimensions in parentheses in millimeters

Cutler-Hammer

Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220



Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220

Dimension Sheet
29-170C

Page 1


January 1995
New Information
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Type FCL Current Limit-R
Current Limiting Breakers
15-100 Amperes


Westinghouse AB DE-ION® Current Limiting Circuit Breakers


Type FCL Current Limiting Breaker

Front View



Side View







Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220

Dimension Sheet
29-170C

Page 3


January 1995
New Information
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Type LCL Current Limit-R
Current Limiting Breakers
125-400 Amperes


Westinghouse AB DE-ION® Current Limiting Circuit Breakers

Type LCL Current Limiting Breakers

Front View



Side View





Type LCL Current Limiting Breakers, Drilling Plans

Technical drawing of a two-piece handle assembly. The drawing shows two symmetrical pieces joined at a central handle. Key dimensions and features include:

- Top Piece Dimensions:**
 - Overall width: 2.750 (69.82)
 - Inner width: 1.375 (34.91)
 - Outer radius: .500 (12.70) Dia
 - Mounting holes: (6) Holes for .375 (9.52) Mounting Bolts
 - Distance from center to mounting hole: 1.125 (28.56)
 - Distance from center to mounting hole (bottom): 1.750 (44.43)
 - Distance from center to mounting hole (right): 9.563 (242.79)
 - Distance from center to mounting hole (right, bottom): 14.750 (374.50)
 - Distance from center to mounting hole (right, bottom): 17.000 (431.63)
- Bottom Piece Dimensions:**
 - Overall width: 2.750 (69.82)
 - Inner width: 1.375 (34.91)
 - Outer radius: .500 (12.70)
 - Distance from center to mounting hole: 1.125 (28.56)
 - Distance from center to mounting hole (bottom): 1.000 (25.39)
 - Distance from center to mounting hole (right): 5.500 (139.65)
 - Distance from center to mounting hole (right, bottom): 1.125 (28.56)
- Assembly Features:**
 - Q Stud:** Indicated at the center of each piece.
 - Q Breaker:** Indicated at the center of the handle.
 - Q Handle:** Indicated at the center of the handle.
- Bottom Piece Label:** 1.094 R (27.77) R

Diagram illustrating the layout of a 3-Pole Breaker. The diagram shows a rectangular arrangement of six circular holes (three on the left, three on the right) connected by dashed lines. The dimensions and specifications are as follows:

- Vertical Dimensions (Right Side):**
 - Top section: 9.563 (242.79)
 - Middle section: 14.750 (374.50)
 - Bottom section: 5.188 (131.71)
- Horizontal Dimensions (Bottom):**
 - Left section: 2.750 (69.82)
 - Right section: 5.500 (139.65)
- Labels and Notes:**
 - 3-Pole Breaker
 - 563(14.28) Dia. Hole for 125 to 255 Amps
 - .813(20.63) Dia. Hole for 250 to 400 Amps
 - 6 Holes for 3-Pole Breaker
 - 4 Holes for 2-Pole Breaker
 - Omit 2 Center Holes for 2-Pole Breaker

250 R (6.35) R

9.531 (242.00)

14.688 (372.92)

5.156 (130.92)

2.750 (69.82)


(4) Holes

Figure 1 is a plan view of the test section showing the geometry of the handle and breaker. The diagram includes dimensions for the handle (3.250 R, 1.625 R, 1.969 R, 2.078 R, 6.016 R) and the breaker (3.500 R, 7.000 R, 1.88 R). The centerlines are labeled 'C Handle' and 'C Breaker'.


Cable	Catalog Number	Ampere Rating	Wire Size
For Use With Cu/Al Cable (Supplied as Standard)			
Single	TA225LA1	125-225	#6-350 MCM Cu or #4-350 MCM Al
Double	TA400LA1	250-400	#4-250 MCM Cu/Al Plus 3/0-600 MCM Cu/Al
For Use With Copper Cable Only (Must be Specified)			
Single	TA225LA	125-500	#6-350 MCM
Double	TA400LA	250-400	#4-250 MCM and 3/0-600 MCM

Stud Ampere Rating	Stud Style Number	Thread Size	Dimension A
125-225	1241345	.500 (12.70) - 13 (330.07)	3.188 (80.93)
125-225	1241392	.500 (12.70) - 13 (330.07)	4.938 (125.36)
125-225	1241346	.500 (12.70) - 13 (330.07)	6.250 (158.85)
250-400	05B7383G15	.750 (19.04) - 16 (406.24)	5.469 (138.85)
250-400	05B7383G16	.750 (19.04) - 16 (406.24)	7.969 (202.33)
250-400	05B7383G17	.750 (19.04) - 16 (406.24)	10.460 (265.80)

Poles	Ampere Rating	Kit Style Number	Thread Size
2	125-400	313C644G25	.750 (19.04) - 16 (406.24)
3	125-400	313C644G26	.750 (19.04) - 16 (406.24)




Do Not Use More Than 25 Ft. Lbs. Torque to Tighten Nuts



Do Not Use More Than 25 Ft.
Lbs. Torque to Tighten Nuts

Reproduced from drawing 1371D33
Dimensions in parentheses in millimeters


Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220




Type FB Tri-Pac® Breaker

Westinghouse AB DE-ION® Current Limiting Circuit Breakers

Front View



Side View




Reproduced from drawing 4979D67
Dimensions in parentheses in millimeters




Westinghouse AB DE-ION® Current Limiting Circuit Breakers

Type FB Tri-Pac Circuit Breaker, Drilling Plans


For Mounting Bolts




For Rear Connected Studs



For Plug-In Blocks




Front Cover Cutout




Terminal Arrangements


Wire Connection




Bus Connection



Stud Connection



Plug-In or Bolt-On Connection




For 15- to 100-Amp Breakers

Stud Ampere Rating Number	Stud Style	Panel Thickness A	Tube Length B	Tube Length C	Tube Style Number	D	E	F
100 A Short	451D874G01	1.000 (25.39)	1.063 (29.98)		32B9446H20			
100 A Short	451D874G01	.688 (17.46) - .938 (23.80)	1.375 (34.91)		32B9446H21			
100 A Short	451D874G01	.375 (9.52) - .625 (15.87)	1.688 (42.85)		32B9446H22	6.125 (155.51)	3.625 (92.04)	.313 (7.93)
100 A Short	451D874G01	.250 (6.35) - .313 (7.93)	2.000 (76.17)		32B9446H23			18.00 (457.02)
100 A Long	451D874G02	1.000 (25.39)	3.438 (87.28)		32B9446H24			
100 A Long	451D874G02	.688 (17.46) - .938 (23.80)	3.750 (95.21)		32B9446H25			
100 A Long	451D874G02	.375 (9.52) - .625 (15.87)	4.063 (103.15)		32B9446H26			
100 A Long	451D874G02	.250 (6.35) - .313 (7.93)	4.375 (111.08)		32B9446H27			

Ordering instructions. Stud complete consists of one stud assembly and one tube as per chart. Order long and short studs and tubes as required to obtain proper bus spacing.

Rear Connected Studs



Reproduced from drawing 4979D67

Dimensions in parentheses in millimeters

Cutler-Hammer

Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220

FAT-N

Printed in U.S.A.

January 1995



Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220

Dimension Sheet
29-170C

Page 7


January 1995
New Information
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Type LA Tri-Pac® Circuit Breaker

Westinghouse AB DE-ION® Current Limiting Circuit Breakers

Type LA Tri-Pac Circuit Breaker

Front View



Side View

Line End

1" Automatic Tripped


19 1/2" On

15" Reset

11 1/2" Off

Handle .438 (11.11)
Thick 1" Taper Both
Sides 1.563 (39.67)
Wide

Load End






Westinghouse AB DE-ION® Current Limiting Circuit Breakers

Type LA Tri-Pac Circuit Breaker, Drilling Plans


For Mounting Bolts



For Rear Connected Studs

For Plug-In Blocks

Front Cover Cutout



Terminal Arrangements



Cable	Catalog Number	Ampere Rating	Wire Size
For Use With Cu/Al Cable (Must be Specified)			
Single	TA225LA1	125-225	#6-350 MCM Cu or #4-350 MCM Al
Double	TA400LA1	250-400	#4-250 MCM Cu/Al Plus 3/0-600 MCM Cu/Al
For Use With Copper Cable Only (Supplied as Standard)			
Single	TA225LA	70-225	#6-350 MCM
Double	TA400LA	250-400	#4-250 MCM and 3/0-600 MCM

Rear Connected Studs

Stud Ampere Rating	Stud Style Number	Thread Size	Dimension A
125-225	1241345	.500 (12.70) - 13 (330.07)	3.219 (81.72)
125-225	1241392	.500 (12.70) - 13 (330.07)	6.281 (159.48)
125-225	1241346	.500 (12.70) - 13 (330.07)	4.969 (126.16)
250-400	05B7383G15	.750 (19.04) - 16 (406.24)	5.938 (176.14)
250-400	05B7383G16	.750 (19.04) - 16 (406.24)	7.969 (202.33)
250-400	05B7383G17	.750 (19.04) - 16 (406.24)	10.938 (277.70)

Plug-In Adapter Kit

Poles	Ampere Rating	Kit Style Number	Thread Size
2	125-400	313C644G25	.750 (19.04) - 16 (406.24)
3	125-400	313C644G26	.750 (19.04) - 16 (406.24)



Reproduced from drawing 655D300

Dimensions in parentheses in millimeters

Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220



Printed in U.S.A.

January 1995



Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220

Dimension Sheet
29-170C

Page 9


January 1995
New Information
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Type NB Tri-Pac® Circuit Breaker

Westinghouse AB DE-ION® Current Limiting Circuit Breakers


Type NB Tri-Pac Circuit Breaker

Front View



Side View

Line End



Load End

Reproduced from drawing 372D515

Dimensions in parentheses in millimeters

EATON




Westinghouse AB DE-ION® Current Limiting Circuit Breakers

Type NB Tri-Pac Circuit Breaker, Drilling Plans



For Mounting Bolts

(Front Connected Terminals)




For Rear Connected Studs

(Insulated Panel)




Bolted Rear Connected Studs

For 300-450 Amps





Front Cover Cutout



.438 (11.11) Dia. Mounting Holes (4 Total)

Front Connected Terminals

Catalog Number	Ampere Rating	Wire Size
For Use With Cu/Al Cable (Supplied as Standard)		
TA700 NB 1	300-700	Two #1-500 MCM
TA1000 NB 1	800	Three #3/0-400 MCM
For Use With Copper Cable Only (Optional)		
T350 NB	300-350	Single Cable 1-600 MCM
T700 NB 1	400-700	Double Cable 2/0-500 MCM
T1000 NB 1	800	Triple Cable 3/0-500 MCM



Reproduced from drawing 372D515

Dimensions in parentheses in millimeters

Reproduced from drawing 4990D38


Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220




Westinghouse AB DE-ION® Current Limiting Circuit Breakers

Type PB Tri-Pac Circuit Breaker, Drilling Plans

For Mounting Bolts



Front Cover Cutout



Reproduced from drawing 654D460


Dimensions in parentheses in millimeters

Cutler-Hammer
Westinghouse &
Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220


July 1996
New Information
Mailed to: E, D, C/29-100A

Series C[®] HMCP Motor Circuit Protectors 3-600 Amperes


**F-Frame
Front View**




Line End



Load End



Side View



Handle .344 (8.73) Wide
x .375 (9.52) Thick
0° Taper, Load End
7° Taper, Line End
To Top of Clip
Full Ribs on Load End Reject
Projection or Current Limiter
When Required (See Tabulation)

MCP Continuous Rating	Hole Size			Current Limiter Pockets
	.203 (5.15)	.234 (5.94)	.266 (6.75)	
3	X			N
5	X			N
7	X			N
10	X			Y
15	X			Y
25		X		N
30		X		N
50		X		Y
70		X		Y
100			X	N
150			X	Y

Breaker Status	Dimension				
	A	B	C	D	E
On	3.07 (77.94)	2.92 (74.13)	3.96 (100.54)	3.40 (86.32)	3.33 (84.54)
Tripped	2.65 (67.28)	2.57 (65.25)	4.06 (103.08)	2.99 (75.91)	2.98 (75.66)
Off	2.08 (52.81)	2.14 (54.33)	4.12 (104.60)	2.42 (61.44)	2.56 (64.99)
Reset	1.98 (50.27)	2.05 (52.04)	4.11 (104.35)	2.30 (58.39)	2.48 (62.96)

Note: For 2 Pole MCP, Current Carrying
Parts Omitted From Center Pole





Series C HMCP Motor Circuit Protectors, 3-600 Amperes

F-Frame

Front Cover Cutout

Drilling Plans



Reproduced from drawing 1490D54

Dimensions in parentheses in millimeters

Cutler-Hammer

Westinghouse & Cutler-Hammer Products
Five Parkway Center
Pittsburgh, Pennsylvania, U.S.A. 15220

CH

Printed in U.S.A.


July 1996

July 1996
New Information
Mailed to: E, D, C/29-100A


Series C[®] HMCP Motor Circuit Protectors 3-600 Amperes

J-Frame

Front View



Side View





Cutler-Hammer


Dimension Sheet
29-170H

Page 5


July 1996
New Information
Mailed to: E, D, C/29-100A

Series C[®] HMCP Motor Circuit Protectors 3-600 Amperes

**K-Frame
Front View**



Side View



Breaker Status	Dimensions						Handle Force ¹⁾
	A	B	C	D	E	F	
On	5.39 (136.9)	5.20 (132.1)	5.69 (144.5)	5.61 (142.5)	4.72 (119.9)	4.77 (121.2)	30 lbs. (13.61 kgs.)
Tripped	4.77 (121.2)	4.69 (119.1)	5.08 (129.0)	5.11 (129.8)	4.89 (124.2)	4.89 (124.2)	—
Off	4.16 (105.7)	4.21 (106.9)	4.46 (113.3)	4.64 (117.9)	4.95 (125.7)	4.91 (124.7)	25 lbs. (11.34 kgs.)
Reset	4.07 (103.4)	4.14 (105.2)	4.57 (116.1)	4.56 (115.8)	4.95 (125.7)	4.90 (124.5)	35 lbs. (15.87 kgs.)

¹⁾ All handle forces measured approximately 0.125 (3.17) from top of handle.

Reproduced from drawings 1492D63 and 1492D67
Dimensions in parentheses in millimeters


EATON




Series C HMCP Motor Circuit Protectors, 3-600 Amperes

K-Frame Drilling Plans





Rear Connected Studs



Front Connected Terminals



Front Cover Cutout



Reproduced from drawings 1492D63 and 1492D67
 Dimensions in parentheses in millimeters

Cutler-Hammer

Westinghouse & Cutler-Hammer Products
 Five Parkway Center
 Pittsburgh, Pennsylvania, U.S.A. 15220


E.T.N.

July 1996
New Information
Mailed to: E, D, C/29-100A


Series C[®] HMCP Motor Circuit Protectors 3-600 Amperes

L-Frame

Front View



Side View



Load End

Handle Forces (From End of Handle)①

On	45 lbs.
Off	50 lbs.
Reset	60 lbs.







① Measurements taken approximately 3/16 in. from end of handle.



Series C HMCP Motor Circuit Protectors, 3-600 Amperes

L-Frame

Drilling Plans



Reproduced from drawings 1493D63 and 1493D67

Dimensions in parentheses in millimeters

Cutler-Hammer

Westinghouse & Cutler-Hammer Products
 Five Parkway Center
 Pittsburgh, Pennsylvania, U.S.A. 15220

EATON

Printed in U.S.A.

July 1996



October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Outline Dimensions and Drilling Plans
for Standard, MARK 75® and TRI-PAC®
Molded Case Circuit Breakers

AB DE-ION® Circuit Breakers

Index Type Breaker	Page	Index Type Breaker	Page	Index Type Breaker	Page
Standard Breakers		1200 Amperes		300 Amperes	
100 Amperes		Type NC, NCG SELTRONIC Breakers	34	Type HLC SELTRONIC Breaker	29
Quicklag® Ground Fault, Types		Type NB	35	400 Amperes	
QPGF, QBGF 1 Pole	3	Mounting Block for Types NB, HNB,		Type HLA	27
Quicklag Ground Fault, Type QPGF,		NC, HNC	36	Type HLB	28
2 Poles	5	2000 Amperes		600 Amperes	
Quicklag Ground Fault, Type QBGF,		Type PB Rear Connected	37	Type HLC SELTRONIC Breaker	30
2 Poles	6	Type PBF Front Connected	38	800 Amperes	
Quicklag Types QPH, QHP, QNPL,		Fuse Mounting Base for Types PB,		Type HMA	32
1 Pole	7	PBF	39	Types HMC, HMCG SELTRONIC	
Quicklag Types QPH, QHP, QNPL,		Types PC, PCC Rear Connected		Breakers	33
HQNP, 2, 3 Poles	8	SELTRONIC Breakers	41	1200 Amperes	
Quicklag Types HQP, QPH, 1 Pole	9	Types PCF, PCCF, PCFG, PCCFG		Type HNB	35
Quicklag Type HQP, 2 Poles	10	Front Connected SELTRONIC		Types HNC, HNCG SELTRONIC	
Quicklag Type QBH and Types BA,		Breakers	43	Breakers	34
HBA 277 Volts, 1 Pole	11	2500 Amperes		TRI-PAC® Circuit Breakers	
Quicklag Type QBH and Types BA,		Type PB Rear Connected	40	100 Ampere Type FB	47
HBA, 2, 3 Poles	12	Type PC, PCC Rear Connected		400 Ampere Type LA	48
Quicklag Type QBH and Type BAB,		SELTRONIC Breakers	41	800 Ampere Type NB	49
1 Pole	13	Types PCF, PCCF, PCFG, PCCFG		1600 Ampere Type PB	51
Quicklag Type BAB, 2 Poles	14	Front Connected SELTRONIC		Mounting Block for NB TRI-PAC	50
Quicklag Types QCL, QHCL, QCH,		Breakers	43	Motor Operators	
1 Pole	15	3000 Amperes		For EB, EHB, FB, HFB, DA, JA, KA,	
Quicklag Types QCH, QHCL, HQC,		Type PB Rear Connected	40	HKA Breakers	52
QCL, QHC 2, 3 Poles	16	Types PC, PCC Rear Connected		For JB, KB, HKB Breakers	53
Quicklag Type QC 1 Pole	17	SELTRONIC Breakers	42	For LAB, LA, HLA, LC, HLC Breakers	54
Quicklag Type QC 2 Pole	18	High Interrupting Capacity Breakers		For MA, HMA, MC, HMC Breakers	55
Types EB, EHB	19	MARK 75® Circuit Breakers		For NB, HNB, NC, HNC Breakers	56
150 Amperes		100 Amperes		For PB, PC, PCC and PB TRI-PAC	
Type FB	19	Type QHP 1 Pole	7	Breakers	57
LFB Current Limiter for Type FB	21	Type QHP 2, 3 Poles	8	For LA TRI-PAC Breakers	58
Type LC SELTRONIC™ Breaker	29	Type HBA 1 Pole	11	For NB TRI-PAC Breakers	59
225 Ampere		Type HBA 2, 3 Poles	12	Drawout Frames	
Types CA, CAH	23	Type QHCL 1 Pole	15	For LA600, HLA, LC600, HLC600	
Types JA, KA	24	Types QHCL, QHC 2, 3 Poles	16	Breakers	60
250 Amperes		150 Amperes		For MA, HMA, MC, HMC, MCG,	
Types JB, KB	25	Type HFB	19	HMCG Breakers	61
300 Amperes		Type HLC SELTRONIC Breaker	29	For NB, HNB, NC HNC, NCG, HNCG	
Type LC SELTRONIC Breaker	29	225 Amperes		Breakers	62
400 Amperes		Type HKA	24	For PCC, PCCG 2000, 2500, 3000	
Type DA	26	Type HKB	25	Ampere Breakers	63
Types LAB, LA	27			For NB TRI-PAC Breakers	64
Types LB, LBB	28				
600 Amperes					
Type LC SELTRONIC Breaker	30				
Type LA	31				
800 Amperes					
Type MA	32				
Type MC, MCG SELTRONIC Breakers	33				





October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL


Quicklag® Ground Fault Circuit Breakers
Types P and B Single Pole

AB DE-ION® Circuit Breakers

Type P Plug-in, Single Pole Only

Terminals, Load Side Only


Type Terminal	Breaker Amperes	Wire Type and Size
Pressure	15-25	#14-#10 Cu. #12-#8 AL
Pressure	30	#14-#4 Cu. #8-#4 AL



Type B Bolt-on, Single Pole Only

Terminals, Load Side Only

Type Terminal	Breaker Amps	Wire Type and Size
Pressure	15-25	#14-#10 Cu. #12-#8 AL
Pressure	30	#14-#4 Cu. #8-#4 AL







October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Quicklag® Ground Fault Circuit Breakers


Page 5: Type P Plug-in, Two Pole
Page 6: Type B Plug-in, Two Pole

AB DE-ION® Circuit Breakers

Type P Plug-in, Two Pole Only

Terminals, Load Side Only

Type Terminal	Breaker Amperes	Wire Type and Size
Pressure	15-25	#14-#10 Cu., #12-#8 AL
Pressure	30	#14-#4 Cu., #8-#4 AL






Type B Bolt-on, Two Pole Only

Terminals, Load Side Only

Type Terminal	Breaker Amps	Wire Type and Size
Pressure	15-25	#14-#10 Cu, #12-#8 AL
Pressure	30	#14-#4 Cu, #8-#4 AL





October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Quicklag® Plug-in Circuit Breakers

Page 7: Types QPH, QHP, QNPL Single Pole
Page 8: Types QPH, QHP, QNPL, HQNP
Two and Three Poles

AB DE-ION® Circuit Breakers


Type QPH, QHP and QNPL Single Pole Breakers

Applies to The Following Type Breakers:


QPH	1 Pole	22,000 Amp I.C.	25-70 Amp
QHP	1 Pole	65,000 Amp I.C. Mark 75	15-30 Amp
QNPL	1 Pole		5 Amp

Terminal Arrangements, Load Side Only


Type	Ampere Rating	Wire Type	Wire Size
Wire Binding Screw	5-30	Copper	#14-#8
Pressure Type	35-70	Copper/Aluminum	#14-#2





Front View



Width of Mounting Slot



Side View





Type HQNP, QHP, QPH and QNPL Two and Three Pole Breakers


Applies to The Following Type Breakers:

HQNP	2 and 3 Pole	240 Volt	10,000 Amp I.C.	10-100 Amp
QHP	2 and 3 Pole	Mark 75	65,000 Amp I.C.	15- 30 Amp
QPH	2 and 3 Pole	120/240 or 240 Volt	22,000 Amp I.C.	15-100 Amp
QNPL	2 Pole			5 Amp


Terminal Arrangements, Load Side Only

Type	Ampere Rating	Wire Type	Wire Size
Wire Binding Screw	5-30	Copper	#14-# 8
Pressure Type	35-70	Copper/Aluminum	#14-# 2
Pressure Type	90-100	Copper/Aluminum	# 4-1/0


Front View (2 Pole)




Front View (3 Pole)




Line End View (3 Pole)




Side View (2 and 3 Pole)




Width of Mounting Slot



Width of Mounting Slot



Mounting Slot



Reproduced from Drawings 179C653 and 179C655

Westinghouse Electric Corporation
Low Voltage Breaker Division
Beaver, Pennsylvania 15009



October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Quicklag® Plug-in Circuit Breakers


Page 9: Types HQP, QPH Single Pole
Page 10: Type HQP Two Pole

AB DE-ION® Circuit Breakers

Type HQP and QPH Single Pole Breakers

Applies to The Following Type Breakers:


HQP	1 Pole	10,000 Amp I.C.	10-70 Amp
QPH	1 Pole	22,000 Amp I.C.	15-20 Amp



Type HQP Two Pole Breaker

Applies to The Following Type Breaker:

HQP 2 Pole 120/240 Volt 10,000 Amp I.C. 10-125 Amp



Reproduced from Drawing 1253C39

Westinghouse Electric Corporation
Low Voltage Breaker Division
Beaver, Pennsylvania 15009

October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Quicklag® Bolt-on and Type BA Circuit Breakers

Page 11: Types BA, QBH, HBA Single Pole
Page 12: Types BA, QBH, HBA Two and
Three Poles

AB DE-ION[®] Circuit Breakers

Type BA, QBH and HBA Single Pole Breakers

Terminal Arrangements, Load Side Only



Type	Ampere Rating	Wire Type	Wire Size
120/240 Volts Wire Binding Screw	15/30	Cu	#14-#8
Pressure	35/70	Cu/Al	#14-#2
277 Volts Pressure	15/30	Cu	#14-#6
		Al	#12-#6

Applies to The Following Type Breakers:

BA 1 Pole, 277 Volts Only

Applies to The Following Type Breakers:

QBH	1 Pole	22.000 Amp I.C.	25-70 Amp
HBA	1 Pole	65.000 Amp I.C. Mark 75	15-30 Amp






Applies to The Following Type Breakers:

BA	2 and 3 Pole	240 Volt	10.000 Amp I.C.	10-100 Amp
HBA	2 and 3 Pole	Mark 75	65.000 Amp I.C.	15- 30 Amp
QBH	2 and 3 Pole	120/240 or 240 Volt	22.000 Amp I.C.	15-100 Amp

Type	Ampere Rating	Wire Type	Wire Size
Wire Binding Screw	10- 30	Cu	# 14- # 8
Pressure	35- 70	Cu/Al	# 14- # 2
Pressure	90-100	Cu/Al	# 4- 1/0



Reproduced from Drawings 179C654 and 179C656

Westinghouse Electric Corporation
Low Voltage Breaker Division
Beaver, Pennsylvania 15009

October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Quicklag® Bolt-on and Type BA Circuit Breakers


Page 13: Type BAB, QBH Single Pole
Page 14: Type BAB Two Pole

AB DE-ION[®] Circuit Breakers

Type BAB and QBH Single Pole Breakers

Applies to The Following Type Breakers:

BAB	1 Pole	10,000 Amp I.C.	10-70 Amp
QBH	1 Pole	22,000 Amp I.C.	15-20 Amp







Type BAB Two Pole Breaker

Applies to The Following Type Breaker:


BAB 2 Pole 120/240 Volt 10.000 Amp I.C. 10-125 Amp





Front View (2 Pole)



Side View (2 Pole)



Pressure Connectors Approved for:
35- 50 Amp, #4 -14 Cu/Al (120/240 Volts)
55-125 Amp, #10 -8 Cu/Al (120/240 Volts)



Pressure Connectors Approved for:
10- 30 Amp, #8 -14 Cu/Al (120/240 Volts)

Reproduced from Drawing 1253C40

Westinghouse Electric Corporation
Low Voltage Breaker Division
Beaver, Pennsylvania 15009

October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Quicklag® Bolt-on Circuit Breakers

Page 15: Types QCL, QHCL, QCH Single Pole
Page 16: Types QCL, QHCL, QCH, QHC, HQC
Two and Three Poles

AB DE-ION[®] Circuit Breakers

Type QCL, QHCL and QCH Single Pole Breakers


Applies to The Following Type Breakers:

QCL	1 Pole		5 Amp
QHCL	1 Pole	65,000 Amp I.C.	Mark 75 15-30 Amp
QCH	1 Pole	22,000 Amp I.C.	15-70 Amp


Terminal Arrangements, Load Side Only

Type	Ampere Rating	Wire Type	Wire Size
Wire Binding Screw	5-30	Copper	#14-#8
Pressure Type	35-70	Copper/Aluminum	#14-#2


Line End View



Front View




Side View



Face Mounting Plate

Style Number 1614256





(For above Style Breakers Only)



Applies to The Following Type Breakers:


QCH	2 and 3 Pole	120/240 or 240 Volt	22,000 Amp I.C.	15-100 Amp
QHCL and QHC	2 and 3 Pole	Mark 75	65,000 Amp I.C.	15- 30 Amp
HQC	2 and 3 Pole	240 Volt	10,000 Amp I.C.	10-100 Amp
QCL	2 Pole			5 Amp

Type	Ampere Rating	Wire Type	Wire Size
Wire Binding Screw	5-30	Copper	# 14-#8
Pressure Type	35-70	Copper/Aluminum	# 14-#2
Pressure Type	90-100	Copper/Aluminum	# 4-#1



Technical drawing of a 6-hole diamond plate. The top view shows a rectangular plate with a width of 6 and a height of 4. The plate features six diamond-shaped holes arranged in a row. The distance between the centers of adjacent holes is 1. The holes are labeled "11/64 Diameter Holes". The side view shows the plate's thickness of 3/16 and a 45-degree chamfer on the edges. A 3D perspective view of the plate is shown on the right.

Reproduced from Drawings 315C110 and 503C881



October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E. D. C/1901, 1928, 1929/PL

Quicklag® Bolt-on Circuit Breakers

Page 17: Type QC Single Pole


Page 18: Type QC Two Poles

AB DE-ION[®] Circuit Breakers

Type QC Single Pole Breaker

Applies to The Following Type Breakers:

QC 1 Pole 10,000 Amp I.C. 10-70 Amp






Applies to The Following Type Breaker:

QC 2 Pole 120/240 Volt 10,000 Amp I C 10-100 Amp


[illegible][illegible]

Connector Approved for:

10 - 30 Amp, #14-8 Cu/Al
35 - 70 Amp, #14-4 Cu, #12-2 Al
90-100 Amp, # 6-1 Cu/Al



Face Mounting Plate
Style Number 1265C83G01
 (For Above Style Breakers Only)



.164-32 Tap (2) Holes
Reproduced from Drawing 1257C50

Printed in U.S.A.




October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Types EB, EHB, FB, MARK 75® HFB

Page 19: Outline Dimensions
Page 20: Drilling Plans


AB DE-ION® Circuit Breakers

Type EB, EHB, FB and MARK 75 HFB 1, 2, 3, 4 Pole Thermal Magnetic Breakers (See Note Below)



2 and 3 Pole FB and HFB Magnetic Only Breakers


Current carrying parts are omitted from center pole for 2-pole breakers.



Note: Mark 75 HFB Thermal Magnetic Breakers
Two-pole breakers are furnished in three-pole frame
with current carrying parts omitted from center pole.

Support Blocks for Line and Load Ends are not Supplied with Breaker and Must be Ordered Separately. Refer to Drawing 506CI44 When Ordering Support Blocks
All Parts Necessary to Convert a Standard Breaker are Included.

Plug-In and Bolt-On Detail



Plug-in
Bolt stab to breaker conductor, then plug into support block

Bolt-on
Bolt stab to support block, then bolt support block assembly to breaker conductors.




Drilling Plans for Type EB, EHB, FB and MARK 75 Type HFB Breaker


Drilling Plans 1, 2 and 3 Pole

2 Pole Mark 75 and 2 Pole Magnetic Only Use 3 Pole Drilling

For Mounting Bolts





For Rear Connected Studs



Plug-In Block


15 to 150 Amp 2 Pole Breakers
(Thermal Magnetic)

15 to 150 Amp 3 Pole Breakers, 2 Pole
Magnetic Only, and Mark 75 Breakers




Front Cover Cutout

1, 2 and 3 Pole



Front Cover Cutout


4 Pole




Reproduced From Drawing 4967D20, 4979D66 and 4967D30

Drilling Plans 4 Pole

For Mounting Bolts




For Rear Connected Studs




Terminal Arrangements

Removable Connector UL Listed Wire
Range #14 to 1/0 CU #12 to 1/0 AL
will Accomodate #14 to 3/0 Wire


Available Contact Surface
15 Line End 19 Load End



Wire Connection




Bus Connection



Stud Connection

Rear Connected Studs



For 15 to 100 amp Breakers

Stud Ampere Rating	Stud Style Number	Panel Thickness		Tube Length		Tube Style Number	D	E	F
		A	B	C					
100 A Short	451D874G01	1"	1 1/8"			32B9446H20			
100 A Short	451D874G01	1 1/8" to 1 3/8"	1 3/8"			32B9446H21			
100 A Short	451D874G01	3/8" to 3/4"	1 1/8"			32B9446H22	6 1/8"	3 3/8"	3/16"-18
100 A Short	451D874G01	1/4" to 3/16"	2"			32B9446H23			
100 A Long	451D874G02	1"		3 3/8"		32B9446H24			
100 A Long	451D874G02	1 1/8" to 1 3/8"		3 3/8"		32B9446H25			
100 A Long	451D874G02	3/8" to 3/4"		4 1/8"		32B9446H26			
100 A Long	451D874G02	1/4" to 3/16"		4 3/8"		32B9446H27			

For 125 to 150 amp Breakers

Stud Ampere Rating	Stud Style Number	Panel Thickness		Tube Length		Tube Style Number	D	E	F
		A	B	C					
150 A Short	374D883G01	1"	1 1/8"			374D883H06			
150 A Short	374D883G01	1 1/8" to 1 3/8"	1 3/8"			374D883H07			
150 A Short	374D883G01	3/8" to 3/4"	1 1/8"			374D883H08			
150 A Short	374D883G01	1/4" to 3/16"	2"			374D883H09	7 1/2"	4 1/4"	1/16"-14
150 A Long	374D883G02	1"		3 3/8"		374D883H10			
150 A Long	374D883G02	1 1/8" to 1 3/8"		3 3/8"		374D883H11			
150 A Long	374D883G02	3/8" to 3/4"		4 1/8"		374D883H12			
150 A Long	374D883G02	1/4" to 3/16"		4 3/8"		374D883H13			

Ordering Instructions: Stud complete consists of one stud assembly and one tube as per chart. Order long and short studs and tubes as required to obtain proper bus spacing.




October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Type LFB Current Limiting Attachment
for Type FB Circuit Breakers

AB DE-ION® Circuit Breakers

Type LFB Current Limiting Attachment






October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL


Page 23: Types CA and CAH 225 Amperes
Page 24: Types JA, KA, MARK 75®
Type HKA 225 Amperes

AB DE-ION[®] Circuit Breakers


Type CA and CAH Breakers



Drilling Plan




Front Cover Cutout



Reproduced From Drawing 374D130



Type JA, KA and MARK 75® Type HKA Breakers






October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Page 25: Types JB, KB and MARK 75®
Type HKB 250 Amperes
Page 26: Type DA 400 Amperes

AB DE-ION® Circuit Breakers

Type JB, KB and MARK 75® Type HKB Breakers




Terminal Arrangements


Cable	Catalog Number	Amp Rating	Wire Size
Cu/Al Single	T250KB	70 to 250	#4 to 350MCM/Cu #2 to 350MCM/Al
*Cu/Al Single	TA250KB	70 to 250	#4 to 350MCM

*Aluminum Body


Drilling Plans For Mounting Bolts (Front Connected Terminals)




For Rear Connected Studs



For Plug-in Blocks




Front Cover Cutout







Type DA Breaker




Drilling Plans For Mounting Bolts




For Rear Connected Studs



For Plug-in Block



Front Cover Cutout



Reproduced From Drawing 374D640

Westinghouse Electric Corporation
Low Voltage Breaker Division
Beaver, Pennsylvania 15009




October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL


Page 27: Types LAB, LA and MARK 75®
Type HLA 400 Amperes
Page 28: Types LB, LBB and MARK 75®
Type HLB 400 Amperes

AB DE-ION® Circuit Breakers

Type LAB, LA and MARK 75® Type HLA Breakers 400 Amperes




Rear Connected Studs (For Non-Conductive Panels)




Ampere Rating	Style Number	Dimension A	Thread Size
225	1241345	3 1/32	1/2-13
225	1241346	6 1/32	1/2-13
225	1241392	4 1/32	1/2-13
400	05B7383G15	5 1/32	3/4-16
400	05B7383G16	7 3/32	3/4-16
400	05B7383G17	10 1/32	3/4-16

Plug-In Adapter Kit




Poles	Ampere Rating	Style Number	Thread Size
2	70 to 400	313C644G25	3/4-16
3	70 to 400	313C644G26	3/4-16


Drilling Plans For Mounting Bolts




For Rear Connected Studs (Non-Conductive Panels)



For Plug-In Block




Front Cover Cutout





Type LB, LBB and MARK 75® Type HLB Breakers




Front Connected Terminals

Amp Rating	Catalog No.	Wire Size
For Copper Cable (Supplied as Standard)		
70-225	T225LA	Single Cable
250-350	T350DA	Single Cable
400A	T400DA2	Double Cable
		6-350 MCM
		250-500 MCM
		3/0-250 MCM

For AL/CU Cable (Must be specified)

70 to 225	TA225LA1	Single Cable	6-350 MCM Copper or 4-350 MCM Aluminum
250 to 350	TA350DA	Single Cable	250-500 MCM
400A	TA400DA1	Double Cable	3/0-250 MCM


Rear Connected Studs



Stud Ampere Rating	Stud Style Number	Panel Thickness A	Tube length B C	Tube Style Number
400A-short	656D565G03	3/4 to 1	2 7/32	313C909H17
400A-long	656D565G04	3/4 to 1	3 2 3/32	313C909H20
400A-short	656D565G03	1/2 to 3/4	1 3/32	313C909H18
400A-long	656D565G04	1/2 to 3/4	4 1/32	313C909H21
400A-short	656D565G03	1/4 to 1/2	1 1 1/32	313C909H19
400A-long	656D565G04	1/4 to 1/2	4 3/32	313C909H22


Stud complete consists of one stud assembly and one tube as per chart

**Drilling Plans
For Mounting Bolts**




For Rear Connected Studs


Omit Holes in Center Pole
for 2 Pole Breaker



For Plug-in Block



Front Cover Cutout



Plug-In Adapter Kit

Poles	Ampere Rating	Kit Style Number	Thread Size
2	250-400	313C644G45	3/4-16
3	250-400	313C644G46	3/4-16

Reproduced From Drawing 5680D06

Westinghouse Electric Corporation
Low Voltage Breaker Division
Beaver, Pennsylvania 15009




October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Type LC and MARK 75® Type HLC
SELTRONIC™ Circuit Breakers

Page 31: Types LC-150, LC-300, MARK 75®
Types HLC-150, HLC-300
Page 32: Types LC-600, MARK 75® HLC-600


AB DE-ION® Circuit Breakers

Type LC-150, LC-300, MARK 75® Type HLC-150, HLC-300 Breakers



Rear Connected Studs (For Non-Conductive Panels)


Do Not Use More Than 25 Ft. Lbs.
Torque to Tighten Nuts



Maximum Ampere Rating	Style Number	Dimension A	Thread Size
225	1241345	3 1/32	1/2 - 13
225	1241346	6 9/32	1/2 - 13
225	1241392	4 3/32	1/2 - 13
300	05B7383G15	5 1/32	3/4 - 16
300	05B7383G16	7 31/32	3/4 - 16
300	05B7383G17	10 19/32	3/4 - 16


Plug-In Adapter Kit

Do Not Use More Than 25 Ft. Lbs.
Torque to Tighten Nuts




Poles	Ampere Rating	Style Number	Thread Size
2	75 to 300	313C644G25	3/4 - 16
3	75 to 300	313C644G26	3/4 - 16


Drilling Plans For Mounting Bolts




For Rear Connected Studs (Non-Conductive Panels)



For Plug-in Block




Front Cover Cutout






Type LC-600, MARK 75® Type HLC-600 Breakers




Rear Connected Studs



Ampere Rating	Style Number	Thread Size	Dimension A
300 to 600	314C960G07	1 - 12	5 1/32
300 to 600	314C960G08	1 - 12	7 3/32
300 to 600	314C960G09	1 - 12	10 1/32

Plug-In-Adapter Kit



Poles	Ampere Rating	Style Number	Thread Size
2	300 to 600	313C644G50	1 - 12
3	300 to 600	313C644G51	1 - 12


Terminal Arrangements

Copper Cable Only
(Must be Ordered Separately)
Cat. #T600LA Wire Size (2) 250-500 MCM


Optional AL/CU Cable
(Must be Ordered Separately)
Cat. #TA600LA Wire Size (2) 250-500 MCM

Drilling Plans


For Mounting Bolts
(Front Connected Terminals)




For Rear Connected Studs
(Insulated Panel)



For Plug-in Block



Front Cover Cutout




October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL


Page 31: Types LA and MARK 75® Type HLA
600 Amperes
Page 32: Types MA and MARK 75® Type
HMA 800 Amperes

AB DE-ION[®] Circuit Breakers

Type LA and MARK 75® Type HLA Breakers




Rear Connected Studs



Do not Use More Than
25 Ft. Lbs. Torque
to Tighten Nuts

Ampere Rating	Style Number	Thread Size	Dimension A
250 to 600	314C960G07	1 - 12	5 $\frac{1}{2}$ ₃₂
250 to 600	314C960G08	1 - 12	7 $\frac{3}{32}$
250 to 600	314C960G09	1 - 12	10 $\frac{1}{32}$

Plug-In-Adapter Kit



Do not Use More
Than 25 Ft. Lbs.
Torque to
Tighten Nuts

Poles	Ampere Rating	Style Number	Thread Size
2	250 to 600	313C644G50	1 - 12
3	250 to 600	313C644G51	1 - 12


Terminal Arrangements

Copper Cable Only (Supplied as Standard)
Cat. #T600LA Wire Size (2) 250-500 MCM


AL/CU Cable (Must be Specified)
Cat. #TA600LA Wire Size (2) 250-500 MCM

Drilling Plans


For Mounting Bolts




For Rear Connected Studs
(Insulated Panel)



For Plug-in Block



Front Cover Cutout



Reproduced From Drawing 375D401




Type MA and MARK 75® Type HMA Breakers

Terminal Arrangements For Use With Copper Cable Only (Supplied As Standard)

Cable	Catalog No.	Ampere Rating	Wire Size
Single	T350MA	125-350	#1-600 MCM
Double	T600MA1	400-600	2/0-500 MCM
Triple	T800MA1	700-800	3/0-300 MCM

For Use With Al/Cu Cable (Must Be Specified)


Double	TA700MA1	125-600	#1-500 MCM
Triple	TA800MA2	700-800	3/0-400 MCM



Rear Connected Studs

Stud Ampere Rating	Stud Style Number	Thread Size	Dimension A
125-225	314C960G01	1/2-13	3 1/32
250-400	314C960G04	3/4-16	5 7/32
250-400	314C960G05	3/4-16	8 7/32
250-400	314C960G06	3/4-16	10 7/32
450-600	314C960G07	1-12	5 7/32
450-600	314C960G08	1-12	8 7/32
450-600	314C960G09	1-12	10 7/32
700-800	314C960G10	1 1/8-12	5 7/32
700-800	314C960G11	1 1/8-12	8 7/32
700-800	314C960G12	1 1/8-12	10 7/32

Rear Connected Studs—2 Required Per Pole (Not Supplied With Breaker)



Plug-In Adapter Kit

Poles	Ampere Rating	Kit Style Number	Thread Size	Fig
2	125-600	313C644G27	1 1/8-12	1
3	125-600	313C644G28	1 1/8-12	1
2	700-800	176C544G01	1 1/8-12	2
3	700-800	176C544G02	1 1/8-12	2






Figure 1 (Plug-In Type)




Do not Use More Than 25 Ft. Lbs. Torque to Tighten Nuts

Figure 2 (Front Removable Bolted Type)


Drilling Plans For Plug-In Block




Rear Connected Studs (For Non-Conductive Panels)



For Mounting Bolts



Front Cover Cutout






October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Page 33: Types MC, MCG, MARK 75®
Types HMC, HMC 800 Ampere
SELTRONIC™ Circuit Breakers


Page 34: Types NC, NCG, MARK 75®
Types HNC, HNC 1200 Ampere
SELTRONIC™ Breakers

AB DE-ION® Circuit Breakers

Type MC, MCG, MARK 75® Type HMC, HMC 800 Breakers



Rear Connected Studs 2 Required Per Pole (Not Supplied With Breaker)



Stud Ampere Rating	Stud Style Number	Thread Size	Dimension A
250-400	314C960G04	3/4-16	5 29/32
250-400	314C960G05	3/4-16	8 13/32
250-400	314C960G06	3/4-16	10 29/32
450-600	314C960G07	1-12	5 29/32
450-600	314C960G08	1-12	8 13/32
450-600	314C960G09	1-12	10 29/32
700-800	314C960G10	1 1/2-12	5 29/32
700-800	314C960G11	1 1/2-12	8 13/32
700-800	314C960G12	1 1/2-12	10 29/32

Plug-In Adapter Kit 1 Kit Per Breaker (Not Supplied With Breaker)

Poles	Ampere Rating	Kit Style Number	Thread Size	Fig
2	125-600	313C644G27	1 1/2-12	1
3	125-600	313C644G28	1 1/2-12	1
2	700-800	176C544G01	1 1/2-12	2
3	700-800	176C544G02	1 1/2-12	2

Figure 1






Figure 2




Do Not Use More Than 25Ft. Lbs.
Torque to Tighten Nuts

	B
2 Terminal Unit	13 1/16
4 Terminal Unit	1 9/16


Drilling Plans For Mounting Bolts (Front Connected Terminals)




For Rear Connected Studs



For Plug-In Adapter Kit




Front Cover Cutout




Reproduced from Drawing 2605D21




Type NC, NCG, MARK 75® Type HNC, HNCG Breakers




Bolted Rear Connected Studs For 700-800 Amps




For 900-1200 Amps Only




Drilling Plans For Mounting Bolts



For Rear Connected Studs (Insulated Panel)



Front Cover Cutout






October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Type NB and MARK 75® Type HNB


Page 35: Type NB, MARK 75® Type HNB
Page 36: Mounting Block for Type NB,
MARK 75 HNB, SELTRONIC™ Types NC,
MARK 75 HNC

AB DE-ION® Circuit Breakers


Type NB, MARK 75® Type HNB Breakers



Drilling Plans For Mounting Bolts (Front Connected Terminals)




For Rear Connected Studs (Insulated Panel)




Style No.	A
623B222G01	5 1/2
623B222G02	B
623B222G03	10 1/2

Bolted Rear Connected Studs For 700 to 800 Amps




Style No.	A
623B222G01	5 1/2
623B222G02	B
623B222G03	10 1/2

For 900 to 1200 Amps Only




Front Cover Cutout





Mounting Block for Type NB, NC, MARK 75® Type HNB, HNC Breakers





October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Type PB 2000 Ampere Circuit Breakers

Page 37: Type PB Rear Connected
Page 38: Type PBF Front Connected

AB DE-ION[®] Circuit Breakers


Type PB Rear Connected Breaker




Connectors May
be Mounted
Edgewise or
Flatwise

Current Carrying Parts are
Omitted from Center
Pole for 2 Pole Breakers

Drilling Plans For Mounting Bolts



Front Cover Cutout




Technical drawing of a Type PBF Front Connected Breaker, showing front and side views with dimensions.

Front View (Left):

- Line End:** Dimensions include $1\frac{1}{2}$, $3\frac{3}{4}$, $2\frac{1}{2}$, $1\frac{1}{4}$, $7\frac{1}{16}$ Dia. Holes, $1\frac{1}{16}$, $9\frac{15}{16}$, $11\frac{1}{16}$, $5\frac{1}{32}$, $3\frac{3}{64}$, $2\frac{23}{32}$, $5\frac{5}{16}$, $6\frac{5}{32}$, $5\frac{25}{32}$, $22\frac{1}{8}$, $3\frac{3}{4}$, $7\frac{1}{16}$ Dia. Holes, $1\frac{1}{2}$, $2\frac{1}{2}$, $3\frac{3}{4}$, $1\frac{1}{2}$.
- Center of Breaker:** C of Breaker.
- Center of Handle:** C of Handle.
- Magnetic Trip Adjustment:** Dimensions include $4\frac{1}{2}$, $4\frac{1}{2}$, $4\frac{1}{2}$, $4\frac{1}{2}$, 1 , $5\frac{1}{64}$, $3\frac{3}{64}$.
- Operating HI/LO:** Dimensions include $5\frac{1}{8}$, $5\frac{1}{16}$.

Side View (Right):

- Line:** Dimensions include $9\frac{15}{16}$, $1\frac{1}{32}$, $3\frac{13}{32}$, $2\frac{3}{8}$, $7\frac{1}{16}$, $1\frac{1}{2}$, $25\frac{1}{32}$ Dia., $13\frac{1}{32}$ Dia., $2\frac{1}{32}$ Dia., $14\frac{13}{16}$, $29\frac{5}{8}$.
- Load:** Dimensions include $1\frac{1}{2}$, $2\frac{7}{8}$.
- Radius and Angles:** $15\frac{1}{16}$ Wide, 1° Taper Each Side, $6\frac{1}{4}$ Radius, 18° On, 3° Tripped, 12° Off, 18° Reset Maximum, $10\frac{1}{2}$ Radius.






October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Types PC, PCC SELTRONIC™ Circuit
Breakers

Page 41: 2000 and 2500 Amperes
Page 42: 3000 Amperes


AB DE-ION® Circuit Breakers

Type PC, PCC 2000 and 2500 Rear Connected Breakers






	A
2 Terminal Unit	$1\frac{13}{16}$
4 Terminal Unit	$1\frac{9}{16}$



Nameplate (Used with Ground Fault Trip)



Line End

$4\frac{1}{32}$

$2\frac{1}{64}$

$13\frac{3}{32}$ Diameter (4)
Holes or $3\frac{3}{8}$ -16 Tap

$9\frac{5}{16}$

$13\frac{1}{16}$

ϕ of Handle

ϕ of Breaker

Load End

$5\frac{1}{32}$

$2\frac{33}{64}$

[illegible]




October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Page 39: Type PB 2000 Ampere Fuse
Mounting Base
Page 40: Type PB 2500 and 3000 Ampere
Rear Connected


AB DE-ION® Circuit Breakers

Fuse Mounting Base for Type PB 2000 Breaker Standard Back Connection




Breaker Dimension Reference:
Front Connection Drawing 375D565
Back Connection Drawing 654D460

Direct Bus Connection



Class L Fuse Rating	A	B
801-1200	3/8	2
1201-1600	7/16	2 3/8
1601-2000	1/2	2 3/4

Cable Connection




Terminals

Style No	Wire Range	C Max	D
672B655G01	3/0-400 MCM	5 1/32	5/8
180C046G03	Triple Cable 400-500 MCM 4 Cables	6 3/4	9/32



Type PB 2500, PB 3000 Rear Connected Breakers






October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

SELTRONIC™ Circuit Breakers

Page 43: Types PCF, PCCF, PCFG, PCCFG,
2000 and 2500 Amp Front Connected
Page 44: Ground Fault Indicator kit


AB DE-ION®
Circuit Breakers

Type PCF, PCCF, PCFG, PCCFG 2000, 2500 Breakers







Ground Fault Indicator Kit for SELTRONIC™ Breakers



Drilling Plan and Cutout
For Face Mounting Bracket



Reproduced From Drawing 750B870

Westinghouse Electric Corporation
Low Voltage Breaker Division
Beaver, Pennsylvania 15009




October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL


External (Fourth) Current Monitor
Used with SELTRONIC™ Breakers with
Built-in Ground Fault Protection

AB DE-ION® Circuit Breakers


MCG and HMCB Breakers



PCG, PCCG, PCFG and PCCFG Breakers



NCG and HNCB Breakers






October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Type FB and LA TRI-PAC® Circuit Breakers

Page 47: Type FB TRI-PAC Breaker
Page 48: Type LA TRI-PAC Breaker

AB DE-ION[®] Circuit Breakers


Type FB TRI-PAC Breaker




Terminal Arrangements

Wire Connection


Removable Connector UL
Listed Wire Range 14 to
1/0 CU 12 to 1/0 AL
Will Accomodate
14 to 3/0 Wire




Stud Connection



Plug-in or Bolt-on Connection



Bus Connection



Plug-in
Bolt stab to breaker
conductor, then plug
into support block.

Bolt-on
Bolt stab to support block, then bolt support block assembly to breaker conductors.


For 15 to 100 amp Breakers

Stud Ampere Rating	Stud Style Number	Panel Thickness A	Tube Length		Tube Style Number	D	E	F
			B	C				
100 A Short	451D874G01	1"	1 $\frac{1}{16}$		32B9446H20			
100 A Short	451D874G01	1 $\frac{1}{16}$ to 1 $\frac{5}{16}$	1 $\frac{3}{8}$		32B9446H21			
100 A Short	451D874G01	$\frac{3}{8}$ to $\frac{5}{8}$	1 $\frac{1}{16}$		32B9446H22	6%	3%	$\frac{5}{16}$
100 A Short	451D874G01	$\frac{1}{4}$ to $\frac{3}{8}$	2		32B9446H23			18
100 A Long	451D874G02	1"		3 $\frac{3}{16}$	32B9446H24			
100 A Long	451D874G02	1 $\frac{1}{16}$ to 1 $\frac{5}{16}$		3"	32B9446H25			
100 A Long	451D874G02	$\frac{3}{8}$ to $\frac{5}{8}$		4 $\frac{1}{16}$	32B9446H26			
100 A Long	451D874G02	$\frac{1}{4}$ to $\frac{3}{8}$		4 $\frac{3}{8}$	32B9446H27			


Ordering Instructions: Stud complete consists of one stud assembly and one tube as per chart. Order long and short studs and tubes as required to obtain proper bus spacing.

Drilling Plans

For Mounting Bolts For Rear Connected Studs For Plug-in Block




Front Cover Cutout





Type LA TRI-PAC® Breaker



Terminal Arrangements


Copper Cable Only (Supplied As Standard)

Cable	Catalog Number	Ampere Rating	Wire Size
Single	T225LA	70 to 225	6 to 350 MCM
	T401LA	250 to 400	One #4-250 MCM Plus One #3/0-600 MCM Cables

Al/Cu Cable (Must Be Specified)


Cable	Catalog Number	Ampere Rating	Wire Size
Single	TA225LA1	70 to 225	6 to 350 MCM Copper or #4-350 MCM Al
	TA400LA1	250 to 400	One #4-250 MCM Plus One #3/0-600 MCM Cables

Rear Connected Studs



Ampere Rating	Style Number	Dimension A	Thread Size
70-225	1241345	3 3/32	1/2-13
70-225	1241346	6 3/32	1/2-13
70-225	1241392	4 3/32	1/2-13
250-400	05B7383G15	5 1/32	3/4-16
250-400	05B7383G16	7 3/32	3/4-16
250-400	05B7383G17	10 1/32	3/4-16


Plug-In Adapter Kit




Poles	Ampere Rating	Style Number	Thread Size
2	250-400	313C644G41	3/4-16
3	250-400	313C644G42	3/4-16

Drilling Plans


For Mounting Bolts




For Rear Connected Studs



For Plug-In Block



Front Cover Cutout







October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Type NB TRI-PAC® Circuit Breakers

Page 49: Outline Dimensions, Drilling Plans
Page 50: Mounting Block Dimensions

AB DE-ION® Circuit Breakers


Type NB TRI-PAC® Breaker



Drilling Plans

For Mounting Bolts

(Front Connected Terminals)



Front Connected Terminals

Amp Rating Catalog No. Wire Size


For Copper Cable (Supplied as Standard)

300 to 350	T350 NB	Single Cable 1 to 600 MCM
400 to 700	T700 NB 1	Double Cable 2/0 to 500 MCM
800	T1000 NB 1	Triple Cable 3/0 to 500 MCM


For AL/CU Cable (Must be Specified)

300 to 700	TA700 NB 1	Two #1 500 MCM
800	TA1000 NB 1	Three #3/0 400 MCM

For Rear Connected Studs (Insulated Panel)




Bolted Rear Connected Studs For 300 to 450 Amps




Style No.	A
623B222G01	5 1/2
623B222G02	8
623B222G03	10 1/2

For 500 to 800 Amps Only




Center Pole Stud Style
Number 373B375G03
(Omit for 2 Pole Breaker)

Front Cover Cutout





Mounting Block for Type NB TRI-PAC® Breakers






October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Page 51: Type PB TRI-PAC®
Page 52: Motor Operator for Types EB, EHB,
FB, HFB, DA, JA, KA, LB, LBB, HKA, HLB
Breakers

AB DE-ION® Circuit Breakers


Type PB TRI-PAC® Breaker






Motor Operators


EB, EHB, FB and HFB Breaker and Operator




Drilling Plan




Motor Operator Only




DA, JA, KA, LB, LBB, HKA and HLB Breaker and Operator



Drilling Plan



Motor Operator Only





October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL


Motor Operators for Types JB, KB, LAB,
LA, LC Circuit Breakers

Page 53: For Types JB, KB
Page 54: For Types LAB, LA, LC


AB DE-ION® Circuit Breakers

Motor Operators


JB, KB and HKB Breaker and Operator (Assembled to Base Plate)



Drilling Plan




Motor Operator Only






Motor Operators for LAB, LA and LC Breakers



Drilling Plan and Cutout (Adapter Plate)






October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Motor Operators for Types MA, HMA, NB,
HNB, and SELTRONIC Type MC, HMC, NC,
HNC Circuit Breakers


Page 55: For Types MA, HMA, MC, HMC
Page 56: For Types NB, HNB, NC, HNC

AB DE-ION® Circuit Breakers

Motor Operator for MA, HMA, MC, HMC Breakers




Drilling Plan and Cutout (Adapter Plate)






Motor Operator for NB, HNB, NC, HNC Breakers



Drilling Plan and Cutout (Adapter Plate)



Reproduced From Drawing 5669D02




October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Motor Operators for Types PB and
LA TRI-PAC® Circuit Breakers


Page 57: For Type PB
Page 58: For Type LA TRI-PAC

AB DE-ION® Circuit Breakers

Motor Operator for Type PB Breaker




Drilling Plan and Cutout Adapter Plate







Motor Operator for Type LA TRI-PAC® Breaker



Switchboard Cutout For Motor Operator



Transformer 480/120 Volts (Supplied for Separate Mounting by Customer for 480 Volt Operators)



Reproduced From Drawing 5677D75

Westinghouse Electric Corporation
Low Voltage Breaker Division
Beaver, Pennsylvania 15009




October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Motor Operator for NB TRI-PAC® Circuit
Breakers and Draw-out Frame for LA, HLA,
LC, HLC 600 Ampere Circuit Breakers


AB DE-ION® Circuit Breakers

Page 59: Motor Operator for NB TRI-PAC
Breaker
Page 60: Drawout Frame for LA, HLA,
LC, HLC 600 Ampere Breakers


Motor Operator for Type NB TRI-PAC Breaker



Switchboard Cutout For Motor Operator




Transformer 480/120 Volts (Supplied for Separate Mounting by Customer for 480 Volt Operators)






Drawout Frame for Type LA, HLA, LC, HLC 600 Ampere Breakers



Front Cover Cutout






October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Drawout Frames for MA, HMA, NB, HNB,
and Types MC, HMC, NC, HNC
SELTRONIC™ Circuit Breakers


AB DE-ION® Circuit Breakers

Page 61: For MA, HMA, MC, MCG, HMC,
HMCg
Page 62: For NB, HNB, NC, NCG, HNC,
HNCg

Drawout Frame for Type MA, HMA, MC, MCG, HMC, HMCg Breakers




Front Cover Cutout






Drawout Frame for Type NB, HNB, NC, NCG, HNC, HNCG Breakers



Front Cover Cutout



Reproduced From Drawing 5677D81

Westinghouse Electric Corporation
Low Voltage Breaker Division
Beaver, Pennsylvania 15009



October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL


Drawout Frames for Types PCC, PCCG
SELTRONIC™ Circuit Breakers and Type NB
TRI-PAC® 800 Amp

Page 63: For Types PC, PCCG
Page 64: For NB TRI-PAC 800 Amp



AB DE-ION® Circuit Breakers

Drawout Frame for Type PC, PCCG Breakers


2500 and 3000 Amp Bus Arrangement



2000 Amp Bus Arrangement




Front Cover Cutout





Drawout Frame for Type NB TRI-PAC® 800 Ampere Frame



Reproduced From Drawing 2603D31

Westinghouse Electric Corporation
Low Voltage Breaker Division
Beaver, Pennsylvania 15009



October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Outline Dimensions and Drilling Plans
for Standard, MARK 75® and TRI-PAC®
Molded Case Circuit Breakers

AB DE-ION® Circuit Breakers

Index Type Breaker	Page	Index Type Breaker	Page	Index Type Breaker	Page
Standard Breakers		1200 Amperes		300 Amperes	
100 Amperes		Type NC, NCG SELTRONIC Breakers	34	Type HLC SELTRONIC Breaker.	29
Quicklag® Ground Fault, Types		Type NB	35	400 Amperes	
QPGF, QBGF 1 Pole	3	Mounting Block for Types NB, HNB,		Type HLA	27
Quicklag Ground Fault, Type QPGF,		NC, HNC	36	Type HLB	28
2 Poles	5	2000 Amperes		600 Amperes	
Quicklag Ground Fault, Type QBGF,		Type PB Rear Connected	37	Type HLC SELTRONIC Breaker.	30
2 Poles	6	Type PBF Front Connected	38	800 Amperes	
Quicklag Types QPH, QHP, QNPL,		Fuse Mounting Base for Types PB,		Type HMA	32
1 Pole	7	PBF	39	Types HMC, HMCg SELTRONIC	
Quicklag Types QPH, QHP, QNPL,		Types PC, PCC Rear Connected		Breakers	33
HQNP, 2, 3 Poles	8	SELTRONIC Breakers	41	1200 Amperes	
Quicklag Types HQP, QPH, 1 Pole	9	Types PCF, PCCF, PCFG, PCCFG		Type HNB	35
Quicklag Type HQP, 2 Poles	10	Front Connected SELTRONIC		Types HNC, HNCg SELTRONIC	
Quicklag Type QBH and Types BA,		Breakers	43	Breakers	34
HBA 277 Volts, 1 Pole	11	2500 Amperes		TRI-PAC® Circuit Breakers	
Quicklag Type QBH and Types BA,		Type PB Rear Connected	40	100 Ampere Type FB	47
HBA, 2, 3 Poles	12	Type PC, PCC Rear Connected		400 Ampere Type LA	48
Quicklag Type QBH and Type BAB,		SELTRONIC Breakers	41	800 Ampere Type NB	49
1 Pole	13	Types PCF, PCCF, PCFG, PCCFG		1600 Ampere Type PB	51
Quicklag Type BAB, 2 Poles	14	Front Connected SELTRONIC		Mounting Block for NB TRI-PAC	50
Quicklag Types QCL, QHCL, QCH,		Breakers	43	Motor Operators	
1 Pole	15	3000 Amperes		For EB, EHB, FB, HFB, DA, JA, KA,	
Quicklag Types QCH, QHCL, HQC,		Type PB Rear Connected	40	HKA Breakers	52
QCL, QHC 2, 3 Poles	16	Types PC, PCC Rear Connected		For JB, KB, HKB Breakers	53
Quicklag Type QC 1 Pole	17	SELTRONIC Breakers	42	For LAB, LA, HLA, LC, HLC Breakers	54
Quicklag Type QC 2 Pole	18	High Interrupting Capacity Breakers		For MA, HMA, MC, HMC Breakers	55
Types EB, EHB	19	MARK 75® Circuit Breakers		For NB, HNB, NC, HNC Breakers	56
150 Amperes		100 Amperes		For PB, PC, PCC and PB TRI-PAC	
Type FB	19	Type QHP 1 Pole	7	Breakers	57
LFB Current Limiter for Type FB	21	Type QHP 2, 3 Poles	8	For LA TRI-PAC Breakers	58
Type LC SELTRONIC™ Breaker	29	Type HBA 1 Pole	11	For NB TRI-PAC Breakers	59
225 Ampere		Type HBA 2, 3 Poles	12	Drawout Frames	
Types CA, CAH	23	Type QHCL 1 Pole	15	For LA600, HLA, LC600, HLC600	
Types JA, KA	24	Types QHCL, QHC 2, 3 Poles	16	Breakers	60
250 Amperes		150 Amperes		For MA, HMA, MC, HMC, MCG,	
Types JB, KB	25	Type HFB	19	HMCg Breakers	61
300 Amperes		Type HLC SELTRONIC Breaker	29	For NB, HNB, NC HNC, NCG, HNCg	
Type LC SELTRONIC Breaker	29	225 Amperes		Breakers	62
400 Amperes		Type HKA	24	For PCC, PCCg 2000, 2500, 3000	
Type DA	26	Type HKB	25	Ampere Breakers	63
Types LAB, LA	27			For NB TRI-PAC Breakers	64
Types LB, LBB	28				
600 Amperes					
Type LC SELTRONIC Breaker	30				
Type LA	31				
800 Amperes					
Type MA	32				
Type MC, MCG SELTRONIC Breakers	33				





October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL


Quicklag® Ground Fault Circuit Breakers
Types P and B Single Pole

AB DE-ION® Circuit Breakers

Type P Plug-in, Single Pole Only

Terminals, Load Side Only


Type Terminal	Breaker Amperes	Wire Type and Size
Pressure	15-25	#14-#10 Cu. #12-#8 AL
Pressure	30	#14-#4 Cu. #8-#4 AL



Type B Bolt-on, Single Pole Only

Terminals, Load Side Only

Type Terminal	Breaker Amps	Wire Type and Size
Pressure	15-25	#14-#10 Cu. #12-#8 AL
Pressure	30	#14-#4 Cu. #8-#4 AL







October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Quicklag® Ground Fault Circuit Breakers


Page 5: Type P Plug-in, Two Pole
Page 6: Type B Plug-in, Two Pole

AB DE-ION® Circuit Breakers

Type P Plug-in, Two Pole Only

Terminals, Load Side Only

Type Terminal	Breaker Amperes	Wire Type and Size
Pressure	15-25	#14-#10 Cu. #12-#8 AL
Pressure	30	#14-#4 Cu. #8-#4 AL






Type B Bolt-on, Two Pole Only

Terminals, Load Side Only

Type Terminal	Breaker Amps	Wire Type and Size
Pressure	15-25	#14-#10 Cu, #12-#8 AL
Pressure	30	#14-# 4 Cu, # 8-#4 AL




July, 1985
Supersedes Dimension Sheet 29-170,
pages 9-10, dated October, 1977.
Mailed to: E, D, C/29-100A

Quicklag® Plug-in Circuit Breakers

Page 9: Types HQP, QPH, QHP Single Pole
Page 10: Type HQP, QPH, QHP Two and
Three Poles

AB DE-ION® Circuit Breakers

Type HQP, QPH, QHP Single Pole Breakers







AB DE-ION Circuit Breakers

Type HQP Two and Three Pole Breaker


Line End View
(3 Pole)






Front View
(2 Pole)



Front View
(3 Pole)



Side View
(2, 3 Pole)



Wire Sizes for Pressure Connectors

Poles	Amps	Volts	Wire Size, Type
2	10-30	120/240	#8-#14 Cu/Al
2	35-50	120/240	#4-#14 Cu/Al
2	55-125	120/240	1/0-#8 Cu/Al
2, 3	10-50	240	#4-#14 Cu/Al
2, 3	55-100	240	1/0-#8 Cu/Al

Reproduced from Drawings 1251C82, 1253C39, 2612D61


Westinghouse Electric Corporation
Distribution and Protection Business Unit
Commercial Division - Components
Beaver, Pennsylvania 15009

Printed in USA



AB DE-ION Circuit Breakers

Type BAB, HBA, QBH Two Pole Breakers



Printed in USA

Reproduced from Drawings 1251C92, 1253C40, 2612D62

Westinghouse Electric Corporation
Distribution and Protection Business Unit
Commercial Division - Components
Beaver, Pennsylvania 15009



October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Quicklag® Bolt-on Circuit Breakers


Page 17: Type QC Single Pole
Page 18: Type QC Two Poles

AB DE-ION® Circuit Breakers

Type QC Single Pole Breaker

Applies to The Following Type Breakers:


QC 1 Pole 10,000 Amp I.C. 10-70 Amp





Applies to The Following Type Breaker :

QC 2 Pole 120/240 Volt 10,000 Amp I.C 10-100 Amp



10-15 and 20 Amp

.164-32 Tap (2) Holes

Reproduced from Drawing 1257C50




July, 1985
Supersedes Dimension Sheet 29-170,
pages 17-18, dated October, 1977.
Mailed to: E, D, C/29-100A

Quicklag® Bolt-on Circuit Breakers

Page 17: Type QC, QCH, QHC Single Pole
Page 18: Type QC, QCH, QHC Two and
Three Poles

AB DE-ION® Circuit Breakers


Type QC, QCH, QHC Single Pole Breaker




AB DE-ION Circuit Breakers

Type QC, QCH, QHC Two and Three Pole Breakers


Line End View
(3 Pole)



Front View
(2 Pole)




Front View
(3 Pole)



Side View
(2 Pole)

Connector Listed for:

10 - 30 Amp, #14 - 8 Cu/Al
35 - 70 Amp, #14 - 4 Cu, #12 - 2Al
90 - 100 Amp, #6 - 1 Cu/Al



Connector Listed for:


10 - 20 Amp, #14 - 10 Cu/Al
25 - 50 Amp, #14 - 4 Cu/Al
55 - 100 Amp, #8 - 1/0 Cu/Al

Face Mounting Plate


Style Number 1265C83G02 - 2 Pole

Style Number 1265C83G03 - 3 Pole

(For Above Style Breakers Only)



Base Mounting Plate (For All Type "C" Breakers)



Mounting Plate Style Number 207B513G01 Maximum of Six 1-Poles,
Three 2-Poles or Two 3-Poles; Plates May be Separated When Necessary

July, 1982
New Information
Mailed to: E, D, C/1901, 1928, 1929/PL

Type GB, Type GBH Bolt-on Panelboard Circuit Breakers


Page 18.1: Type GB, GBH One Pole
Page 18.2: Type GB, GBH Two Pole

AB DE-ION[®] Circuit Breakers

Type GB, GBH Bolt-on, One Pole Only

Terminals, Load Side Only

Type Terminal	Breaker Amperes	Wire Type and Size
Clamp Pressure	15-20 25-100	# 14-# 10 Cu/Al # 10-1/0 Cu/Al




Clamp Supplied on 15 thru 20 Amp Ratings
Wire Range #14-#10 Cu/Al

Reproduced From Drawing 1372D97



Terminals, Load Side Only

Type Terminal	Breaker Amps	Wire Type and Size
Clamp Pressure	15-20 25-100	# 14-#10 Cu/Al # 10-I/O Cu/Al



Reproduced From Drawing 1373D57

Westinghouse Electric Corporation
Low Voltage Breaker Division
Beaver, Pennsylvania 15009

Printed in USA

July, 1987
Supersedes Dimension Sheet 29-170,
pages 18.3-18.4, dated July, 1982
Mailed to: E, D, C/29-100A, 31-400A,
31-500A

Type GB, Type GHB Bolt-on Panelboard
Circuit Breakers
Type GHBS Circuit Breaker


Page 18.3: Type GB, GHB Bolt-on
Three Pole
Page 18.4: Type GHBS One Pole

AB DE-ION® Circuit Breakers

Type GB, GHB Bolt-on Three Pole Breakers

Terminal Arrangements, Load Side Only

Type	Ampere Rating	Wire Type and Size
Clamp Pressure	15-20 25-100	#14-#10 Cu/Al #10-1/O Cu/Al




Reproduced From Drawing 1370D84

AB DE-ION® Circuit Breakers

Type GHBS, One Pole Only

Terminals, Load Side Only

Type Terminal	Breaker Amperes	Wire Type and Size
Clamp	15-20	#14-#10 Cu/Al



Reproduced From Drawing 2613D06


Westinghouse Electric Corporation
Distribution and Control Business Unit
Electrical Components Division
Pittsburgh, Pennsylvania, U.S.A. 15220

AB DE-ION® Circuit Breakers

Type GC, GHC Two Pole Only

Suitable for Cable Mounting, Line and Load
Terminals, Load and Load Side

Type Terminal	Breaker Amps	Wire Type and Size
Clamp and Binding Screw	15-20	#14-#10 Cu/Al
Pressure Collar	25-100	#10-I/O Cu/Al



Reproduced From Drawing 1374D15

Westinghouse Electric Corporation
Distribution and Control Business Unit
Electrical Components Division
Pittsburgh, Pennsylvania, U.S.A. 15220



AB DE-ION® Circuit Breakers

Printed in U.S.A.

Westinghouse Electric Corporation
Distribution and Control Business Unit
Electrical Components Division
Pittsburgh, Pennsylvania, U.S.A. 15220

July, 1987




October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Types EB, EHB, FB, MARK 75® HFB

Page 19: Outline Dimensions
Page 20: Drilling Plans


AB DE-ION® Circuit Breakers

Type EB, EHB, FB and MARK 75 HFB 1, 2, 3, 4 Pole Thermal Magnetic Breakers (See Note Below)



2 and 3 Pole FB and HFB Magnetic Only Breakers


Current carrying parts are omitted from center pole for 2-pole breakers.



Note: Mark 75 HFB Thermal Magnetic Breakers
Two-pole breakers are furnished in three-pole frame
with current carrying parts omitted from center pole

Support Blocks for Line and Load Ends are not Supplied with Breaker and Must be Ordered Separately. Refer to Drawing 506CI44 When Ordering Support Blocks
All Parts Necessary to Convert a Standard Breaker are Included.

Plug-In and Bolt-On Detail



Plug-in
Bolt stab to breaker conductor, then plug into support block.

Bolt-on
Bolt stab to support block, then bolt support block assembly to breaker conductors.




Drilling Plans for Type EB, EHB, FB and MARK 75 Type HFB Breaker


Drilling Plans 1, 2 and 3 Pole

2 Pole Mark 75 and 2 Pole Magnetic Only Use 3 Pole Drilling

For Mounting Bolts




For Rear Connected Studs




Plug-In Block

15 to 150 Amp 2 Pole Breakers (Thermal Magnetic) 15 to 150 Amp 3 Pole Breakers, 2 Pole Magnetic Only, and Mark 75 Breakers




Front Cover Cutout

1, 2 and 3 Pole




Front Cover Cutout

4 Pole




Drilling Plans 4 Pole

For Mounting Bolts




Terminal Arrangements

Removable Connector UL Listed Wire Range #14 to 1/0 CU #12 to 1/0 AL will Accomodate #14 to 3/0 Wire



Rear Connected Studs



For 15 to 100 amp Breakers

Stud Ampere Rating	Stud Style Number	Panel Thickness			Tube Length	Tube Style Number	D	E	F
		A	B	C					
100 A Short	451D874G01	1"	1 1/8"		3 1/2"	32B9446H20			
100 A Short	451D874G01	1 1/8" to 1 3/8"	1 3/8"		3 1/2"	32B9446H21			
100 A Short	451D874G01	3/8" to 3/4"	1 1/8"		3 1/2"	32B9446H22	6 3/8"	3 3/8"	3/16" 18
100 A Short	451D874G01	1/4" to 3/8"	2"		3 1/2"	32B9446H23			
100 A Long	451D874G02	1"		3 3/8"	3 1/2"	32B9446H24			
100 A Long	451D874G02	1 1/8" to 1 3/8"		3 3/8"	3 1/2"	32B9446H25			
100 A Long	451D874G02	3/8" to 3/4"		4 1/8"	3 1/2"	32B9446H26			
100 A Long	451D874G02	1/4" to 3/8"		4 3/8"	3 1/2"	32B9446H27			

For 125 to 150 amp Breakers

Stud Ampere Rating	Stud Style Number	Panel Thickness			Tube Length	Tube Style Number	D	E	F
		A	B	C					
150 A Short	374D883G01	1"	1 1/8"		3 1/2"	374D883H06			
150 A Short	374D883G01	1 1/8" to 1 3/8"	1 3/8"		3 1/2"	374D883H07			
150 A Short	374D883G01	3/8" to 3/4"	1 1/8"		3 1/2"	374D883H08			
150 A Short	374D883G01	1/4" to 3/8"	2"		3 1/2"	374D883H09	7 1/2"	4 1/4"	3/16" 14
150 A Long	374D883G02	1"		3 3/8"	3 1/2"	374D883H10			
150 A Long	374D883G02	1 1/8" to 1 3/8"		3 3/8"	3 1/2"	374D883H11			
150 A Long	374D883G02	3/8" to 3/4"		4 1/8"	3 1/2"	374D883H12			
150 A Long	374D883G02	1/4" to 3/8"		4 3/8"	3 1/2"	374D883H13			


Ordering Instructions: Stud complete consists of one stud assembly and one tube as per chart. Order long and short studs and tubes as required to obtain proper bus spacing.

October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Type LFB Current Limiting Attachment for Type FB Circuit Breakers

AB DE-ION[®] Circuit Breakers

Type LFB Current Limiting Attachment








October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL


Page 23: Types CA and CAH 225 Amperes
Page 24: Types JA, KA, MARK 75®
Type HKA 225 Amperes

AB DE-ION® Circuit Breakers


Type CA and CAH Breakers



Drilling Plan




Front Cover Cutout






Type JA, KA and MARK 75® Type HKA Breakers





Type DA Breaker



Plug-in Adapter Kit

Poles	Ampere Rating	Kit Style Number	Thread Size
2	250-400	313C644G45	3/4-16
3	250-400	313C644G46	3/4-16

Front Connected Terminals

For Copper Cable (Supplied as Standard)

Cat. #T350DA Wire Size 250-500 MCM (Single Cable)

Cat. #T400DA2 Wire Size 3/0-250 MCM (Double Cable)

For AL/CU Cable (Must be Specified)


Cat. #TA350DA Wire Size 250-500 MCM (Single Cable)

Cat. #TA400DA1 Wire Size 3/0-250 MCM (Double Cable)


Stud Ampere Rating	Stud Style Number	Panel Thickness		Tube length		Tube Style Number
		A	B	C		
400A-short	656D565G03	3/4 to 1	2 1/32			313C909H17
400A-long	656D565G04	3/4 to 1		3 29/32		313C909H20
400A-short	656D565G03	1/2 to 3/4	1 3/32			313C909H18
400A-long	656D565G04	1/2 to 3/4		4 1/32		313C909H21
400A-short	656D565G03	3/4 to 1	1 11/32			313C909H19
400A-long	656D565G04	3/4 to 1		4 9/32		313C909H22

Stud complete consists of one stud assembly and one tube as per chart


Drilling Plans For Mounting Bolts




For Rear Connected Studs



For Plug-in Block



Front Cover Cutout



Reproduced From Drawing 374D640

Westinghouse Electric Corporation
Low Voltage Breaker Division
Beaver, Pennsylvania 15009




October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL


Page 27: Types LAB, LA and MARK 75®
Type HLA 400 Amperes
Page 28: Types LB, LBB and MARK 75®
Type HLB 400 Amperes

AB DE-ION® Circuit Breakers

Type LAB, LA and MARK 75® Type HLA Breakers 400 Amperes




Rear Connected Studs (For Non-Conductive Panels)




Ampere Rating	Style Number	Dimension A	Thread Size
225	1241345	$3\frac{1}{32}$	$\frac{1}{2}$ -13
225	1241346	$6\frac{1}{32}$	$\frac{1}{2}$ -13
225	1241392	$4\frac{3}{16}$	$\frac{1}{2}$ -13
400	05B7383G15	$5\frac{1}{2}$	$\frac{3}{4}$ -16
400	05B7383G16	$7\frac{3}{16}$	$\frac{3}{4}$ -16
400	05B7383G17	$10\frac{1}{32}$	$\frac{3}{4}$ -16

Plug-In Adapter Kit




Poles	Ampere Rating	Style Number	Thread Size
2	70 to 400	313C644G25	$\frac{3}{4}$ -16
3	70 to 400	313C644G26	$\frac{3}{4}$ -16


Drilling Plans For Mounting Bolts




For Rear Connected Studs (Non-Conductive Panels)



For Plug-In Block




Front Cover Cutout





Type LB, LBB and MARK 75® Type HLB Breakers




Front Connected Terminals

Amp Rating	Catalog No.	Wire Size
For Copper Cable (Supplied as Standard)		
70-225	T225LA	Single Cable
250-350	T350DA	Single Cable
400A	T400DA2	Double Cable
		6-350 MCM
		250-500 MCM
		3/0-250 MCM

For AL/CU Cable (Must be specified)

70 to 225	TA225LA1	Single Cable	6-350 MCM Copper or 4-350 MCM Aluminum
250 to 350	TA350DA	Single Cable	250-500 MCM
400A	TA400DA1	Double Cable	3/0-250 MCM


Rear Connected Studs



Stud Ampere Rating	Stud Style Number	Panel Thickness A	Tube length B C	Tube Style Number
400A-short	656D565G03	3/4 to 1	2 7/32	313C909H17
400A-long	656D565G04	3/4 to 1	3 2 3/32	313C909H20
400A-short	656D565G03	1/2 to 3/4	1 3/32	313C909H18
400A-long	656D565G04	1/2 to 3/4	4 1/32	313C909H21
400A short	656D565G03	1/4 to 1/2	1 1 1/32	313C909H19
400A-long	656D565G04	1/4 to 1/2	4 3/32	313C909H22


Stud complete consists of one stud assembly and one tube as per chart.

Drilling Plans
For Mounting Bolts




For Rear Connected Studs


Omit Holes in Center Pole
for 2 Pole Breaker



For Plug-in Block



Front Cover Cutout



Plug-In Adapter Kit

Poles	Ampere Rating	Kit Style Number	Thread Size
2	250-400	313C644G45	3/4-16
3	250-400	313C644G46	3/4-16

Reproduced From Drawing 5680D06

Westinghouse Electric Corporation
Low Voltage Breaker Division
Beaver, Pennsylvania 15009


October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E. D. C/1901, 1928, 1929/PL

Type LC and MARK 75® Type HLC SELTRONIC™ Circuit Breakers

Page 31: Types LC-150, LC-300, MARK 75®
Types HLC-150, HLC-300
Page 32: Types LC-600, MARK 75® HLC-600


AB DE-ION[®] Circuit Breakers

Type LC-150, LC-300, MARK 75® Type HLC-150, HLC-300 Breakers



Rear Connected Studs (For Non-Conductive Panels)

Do Not Use More Than 25 Ft. Lbs.
Torque to Tighten Nuts




$\frac{3}{8}$ -24 Thread

Maximum Ampere Rating	Style Number	Dimension A	Thread Size
225	1241345	$3\frac{1}{32}$	$\frac{1}{2} \times 13$
225	1241346	$6\frac{3}{32}$	$\frac{1}{2} \times 13$
225	1241392	$4\frac{31}{32}$	$\frac{1}{2} \times 13$
300	0587383G15	$5\frac{15}{32}$	$\frac{3}{4} \times 16$
300	0587383G16	$7\frac{31}{32}$	$\frac{3}{4} \times 16$
300	0587383G17	$10\frac{15}{32}$	$\frac{3}{4} \times 16$

Plug-In Adapter Kit


Do Not Use More Than 25 Ft. Lbs.
Torque to Tighten Nuts




3/8"-24 Thread

Poles	Ampere Rating	Style Number	Thread Size
2	75 to 300	313C644G25	3/4" - 16
3	75 to 300	313C644G26	3/4" - 16


Drilling Plans For Mounting Bolts



For Rear Connected Studs (Non-Conductive Panels)




Front Cover Cutout






Type LC-600, MARK 75® Type HLC-600 Breakers




Rear Connected Studs



Ampere Rating	Style Number	Thread Size	Dimension A
300 to 600	314C960G07	1 - 12	5 15/32
300 to 600	314C960G08	1 - 12	7 3/32
300 to 600	314C960G09	1 - 12	10 15/32

Plug-In-Adapter Kit




Poles	Ampere Rating	Style Number	Thread Size
2	300 to 600	313C644G50	1 - 12
3	300 to 600	313C644G51	1 - 12

Terminal Arrangements


Copper Cable Only
(Must be Ordered Separately)
Cat. #T600LA Wire Size (2) 250-500 MCM

Optional AL/CU Cable
(Must be Ordered Separately)
Cat. #TA600LA Wire Size (2) 250-500 MCM


Drilling Plans
For Mounting Bolts
(Front Connected Terminals)




For Rear Connected Studs
(Insulated Panel)



For Plug-in Block



Front Cover Cutout



RECEIVED

SEP 28 1981


S.W.B.D. CO.

August, 1981
Supersedes Dimension Sheet 29-170,
pages 31-32, dated July, 1981.
Mailed to: E, D, C/1901, 1928, 1929/PL

Page 31: Types LA and MARK 75® Type HLA
600 Amperes
Page 32: Types MA and MARK 75® Type
HMA 800 Amperes

AB DE-ION[®] Circuit Breakers


Type LA and MARK 75® Type HLA Breakers



Drilling Plans For Mounting Bolts (Front Connected Terminals)

For Plug-In Block

Front Cover Cutout



Do Not Use More Than 25 Foot
Lbs. Torque to Tighten Nuts

① Type LA Breaker, 600 Amperes


Poles	Ampere Rating	Style Number
2	250-600	506C144G21
3	250-600	506C144G22

Terminal Arrangements

Copper Cable Only (Supplied as Standard)
Cat. #T600LA Wire Size (2) 250-500 MCM

AL/CU Cable (Must be Specified)
Cat. #TA600LA Wire Size (2) 250-500 MCM

Rear Connected Studs



Do Not Use More Than 25 Foot
Lbs. Torque to Tighten Nuts

Ampere Rating	Style Number	Thread Size	Dimension A
250 to 600	314C960G07	1-12	5 ¹⁵ / ₃₂
250 to 600	314C960G08	1-12	7 ³ / ₃₂
250 to 600	314C960G09	1-12	10 ¹⁵ / ₃₂

Reproduced From Drawing 1374D20

Terminal Arrangements


Cable	Catalog No.	Ampere Rating	Wire Size
Single	T350MA	125-350	#1-600 MCM
Double	T600MA1	400-600	2/0-500 MCM
Triple	T800MA1	700-800	3/0-300 MCM

Double	TA700MA1	125-600	#1-500 MCM
Triple	TA800MA2	700-800	3/0-400 MCM



Stud Ampere Rating	Stud Style Number	Thread Size	Dimension A
125-225	314C960G01	1/2-13	3 ² 1/32
250-400	314C960G04	3/4-16	5 ⁹ 32
250-400	314C960G05	3/4-16	8 ¹ 32
250-400	314C960G06	3/4-16	10 ²⁹ 32
450-600	314C960G07	1-12	5 ²⁹ 32
450-600	314C960G08	1-12	8 ¹ 32
450-600	314C960G09	1-12	10 ²⁹ 32
700-800	314C960G10	1 1/2-12	5 ²⁹ 32
700-800	314C960G11	1 1/2-12	8 ¹ 32
700-800	314C960G12	1 1/2-12	10 ²⁹ 32

Rear Connected Studs—2 Required Per Pole (Not Supplied With Breaker)



Plug-In Adapter Kit

Poles	Ampere Rating	Kit Style Number	Thread Size	Figs
2	125-600	313C644G27	1 $\frac{1}{8}$ -12	1
3	125-600	313C644G28	1 $\frac{1}{8}$ -12	1
2	700-800	176C544G01	1 $\frac{1}{8}$ -12	2
3	700-800	176C544G02	1 $\frac{1}{8}$ -12	2





Figure 1 (Plug-In Type)




Do not Use More Than 25 Ft. Lbs.
Torque to Tighten Nuts

Figure 2 (Front Removable Bolted Type)


Drilling Plans

For Plug-In Block




Rear Connected Studs


(For Non-Conductive Panels)



For Mounting Bolts



Front Cover Cutout






November, 1981
Supersedes Dimension Sheet 29-170,
pages 33-34, dated October, 1977
Mailed to: E, D, C/1901, 1928, 1929/PL

Page 33: Types MC, MCG, MARK 75®
Types HMC, HMC 800 Ampere
SELTRONIC™ Circuit Breakers

Page 34: Types NC, NCG, MARK 75®
Types HNC, HNC 1200 Ampere
SELTRONIC™ Breakers

AB DE-ION® Circuit Breakers

Type MC, MCG, MARK 75® Type HMC, HMC 800 Breakers



Nameplate (Used with Ground Fault Trip)

Front Connected Terminals (Must be Ordered Separately)

Amp Rating	Catalog No	Wire Size
		Number of Cables

For Copper Cable


600	T600MA1	(2) 2/0-500MCM
800	T800MA1	(3) 3/0-300MCM

For AL/CU Cable

600	TA700MA1	(2) #1-500MCM
800	TA800MA2	(3) 3/0-400MCM

Rear Connected Studs

2 Required Per Pole (Not Supplied With Breaker)



Stud Ampere Rating	Stud Style Number	Thread Size	Dimension A
250-400	314C960G04	3/4-16	5 29/32
250-400	314C960G05	3/4-16	8 13/32
250-400	314C960G06	3/4-16	10 29/32
450-600	314C960G07	1-12	5 29/32
450-600	314C960G08	1-12	8 13/32
450-600	314C960G09	1-12	10 29/32
700-800	314C960G10	1 1/2-12	5 29/32
700-800	314C960G11	1 1/2-12	8 13/32
700-800	314C960G12	1 1/2-12	10 29/32

Plug-In Adapter Kit

1 Kit Per Breaker (Not Supplied With Breaker)

Poles	Ampere Rating	Kit Style Number	Thread Size	Fig
2	125-600	313C644G27	1 1/8-12	1
3	125-600	313C644G28	1 1/8-12	1
2	700-800	176C544G01	1 1/2-12	2
3	700-800	176C544G02	1 1/2-12	2

Figure 1







Figure 2




Drilling Plans For Mounting Bolts (Front Connected Terminals)




For Rear Connected Studs



For Plug-In Adapter Kit




Front Cover Cutout



Reproduced from Drawing 2605D21



Type NC, NCG, MARK 75® Type HNC, HNCG Breakers©



Nameplate (Used with Ground Fault Trip)

Front Connected Terminals
(Must be Ordered Separately)

Amp Rating	Catalog No	Wire Size Number of Cables
------------	------------	-------------------------------


For Copper Cable

600	T700NB1	(2) 2/0-500MCM
1000	T1000NB1	(3) 3/0-500MCM
1200	T1200NB1	(4) 3/0-400MCM


For AL/CU Cable

600	TA700NB1	(2) #1-500MCM
1000	TA1000NB1	(3) 3/0-400MCM
1200	TA1201NB1	(3) 500-750MCM
1200	TA1200NB1	(4) 4/0-500MCM

Drilling Plans
For Mounting Bolts




For Rear Connected Studs
(Insulated Panel)




Amp Rating	Hole Dia
700-800	1 3/16
900-1200	1 5/16


Bolted Rear Connected Studs
For 700-800 Amps



For 900-1200 Amps Only



Front Cover Cutout






November, 1981
Supersedes Dimension Sheet 29-170,
pages 35-36, dated October, 1977
Mailed to: E, D, C/1901, 1928, 1929/PL

Type NB and MARK 75® Type HNB

Page 35: Type NB, MARK 75® Type HNB
Page 36: Mounting Block for Type NB,
MARK 75 HNB, SELTRONIC™ Types NC,
MARK 75 HNC


AB DE-ION® Circuit Breakers

Type NB, MARK 75® Type HNB Breakers




Current Carrying Parts
Omitted from Center Pole
for 2 Pole Breaker

Drilling Plans For Mounting Bolts (Front Connected Terminals)




For Rear Connected Studs (Insulated Panel)




Style No	A
623B222G01	5 1/2
623B222G02	8
623B222G03	10 1/2

Bolted Rear Connected Studs For 700 to 800 Amps




Style No	A
623B222G01	5 1/2
623B222G02	8
623B222G03	10 1/2

For 900 to 1200 Amps Only



Front Cover Cutout





Technical drawing of a 125A 2-pole circuit breaker assembly, showing front and side views with dimensions in inches.

Front View Dimensions:

- Overall width: 19 1/2
- Overall height: 18
- Mounting holes: 8 holes, arranged in two rows of four. Diameter: 9/16. Spacing: 3/4 between columns, 1 3/4 between rows.
- Breaker mounting hardware: 2 holes, spaced 1/16 apart.
- Center of handle: 11 1/2 from the bottom edge.
- Top mounting holes: 5/32, 3/32, 1/16, 23/64, 5/32, 47/64, 6/4.

Side View Dimensions:

- Overall height: 8 1/4
- Mounting holes: 4 holes, arranged in two rows of two. Diameter: 7/16. Spacing: 17/32 between columns, 7/32 between rows.
- Breaker mounting hardware: 2 holes, spaced 1/16 apart.
- Center of handle: 11 1/2 from the bottom edge.
- Top mounting holes: 5/32, 3/32, 1/16, 23/64, 5/32, 47/64, 6/4.

Detail View Dimensions:

- Overall width: 6 3/8
- Mounting holes: 4 holes, arranged in two rows of two. Diameter: 7/16. Spacing: 17/32 between columns, 7/32 between rows.
- Breaker mounting hardware: 2 holes, spaced 1/16 apart.
- Center of handle: 11 1/2 from the bottom edge.
- Top mounting holes: 5/32, 3/32, 1/16, 23/64, 5/32, 47/64, 6/4.

Printed in USA



October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Type PB 2000 Ampere Circuit Breakers


Page 37: Type PB Rear Connected
Page 38: Type PBF Front Connected

AB DE-ION® Circuit Breakers


Type PB Rear Connected Breaker



Drilling Plans For Mounting Bolts



Front Cover Cutout






Technical drawing of a PBF Front Connected Breaker, showing front and side views with dimensions.

Front View (Left):

- Line End:** Dimensions include $1\frac{1}{2}$, $3\frac{3}{4}$, $2\frac{1}{2}$, $1\frac{1}{4}$, $7\frac{1}{16}$ Dia. Holes, $1\frac{1}{16}$, $4\frac{1}{32}$, $2\frac{1}{64}$, $5\frac{1}{32}$, $2\frac{33}{64}$, $9\frac{15}{16}$, $11\frac{1}{16}$, $13\frac{11}{16}$, $3\frac{9}{64}$, $4\frac{23}{32}$, $5\frac{8}{8}$, $6\frac{3}{32}$, $5\frac{25}{32}$, $22\frac{1}{8}$, $3\frac{3}{4}$, $7\frac{1}{16}$ Dia. Holes, $1\frac{1}{2}$, $2\frac{1}{2}$, $3\frac{3}{4}$, $1\frac{1}{2}$.
- Center of Breaker:** ϕ of Breaker.
- Center of Handle:** ϕ of Handle.
- Magnetic Trip Adjustment:** Dimensions include $4\frac{1}{2}$, $4\frac{1}{2}$, $4\frac{1}{2}$, $4\frac{1}{2}$, 1 , $3\frac{1}{64}$, $3\frac{1}{64}$.
- Load End:** Dimensions include $1\frac{1}{2}$, $3\frac{3}{4}$, $1\frac{1}{2}$, $2\frac{1}{2}$.

Side View (Right):

- Line:** Dimensions include $9\frac{15}{16}$, $9\frac{15}{32}$, $3\frac{13}{32}$, $3\frac{3}{8}$, $7\frac{1}{16}$, $1\frac{1}{2}$, $13\frac{1}{32}$ Dia., $2\frac{1}{32}$ Dia., $14\frac{13}{16}$, $5\frac{5}{8}$, $29\frac{5}{8}$.
- Load:** Dimensions include $1\frac{1}{2}$, $2\frac{7}{8}$.
- Other Dimensions:** $25\frac{3}{32}$ Dia., $15\frac{1}{16}$ Wide, 1° Taper Each Side, $6\frac{1}{4}$ Radius, 18° On, 3° Tripped, 12° Off, 18° Reset Maximum, $10\frac{1}{2}$ Radius.




May, 1982
Supersedes Dimension Sheet 29-170,
pages 39-40, dated October, 1981
Mailed to: E. D. C/1901. 1928. 1929/PL

Page 39: Type PB 2000 Ampere Fuse
Mounting Base
Page 40: Type PB 2500 Ampere Rear
Connected

AB DE-ION® Circuit Breakers


Fuse Mounting Base for Type PB 2000 Breaker©

Standard Back Connection




Breaker Dimension Reference:
Front Connection Drawing 375D565
Back Connection Drawing 654D460

Direct Bus Connection



Cable Connection





Terminals

Style No	Wire Range	C Max	D
672B655G01	3/0-400 MCM Triple Cable	5 ¹¹ / ₃₂	⁹ / ₈
1B0C046G03	400-500 MCM 4 Cables	6 ³ / ₄	⁹ / ₃₂


Reproduced From Drawing 4975D99

© Changed since previous issue.


Type PB 2500 Rear Connected Breakers



Drilling Plans
For Mounting Bolts




Front Cover Cutout





Type PC, PCC 3000 Rear Connected Breakers




October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

SELTRONIC™ Circuit Breakers

Page 43: Types PCF, PCCF, PCFG, PCCFG,
2000 and 2500 Amp Front Connected
Page 44: Ground Fault Indicator kit


AB DE-ION[®] Circuit Breakers

Type PCF, PCCF, PCFG, PCCFG 2000, 2500 Breakers




Nameplate (Used with Ground Fault Trip)


Drilling Plans For Mounting Bolts



Front Cover Cutout

Removable Handle Extension
Supplied With Breaker


Terminal Block Assembly
Used Only on Ground
Fault Breaker





Current Carrying Parts are Omitted From Center Pole for 2 Pole Breaker



Ground Fault Indicator Kit for SELTRONIC™ Breakers



Drilling Plan and Cutout
For Face Mounting Bracket



Reproduced From Drawing 750B870

Westinghouse Electric Corporation
Low Voltage Breaker Division
Beaver, Pennsylvania 15009




March, 1985
Supersedes Dimension Sheet 29-170
pages 45-46 dated October, 1977
Mailed to: E, D, C/29-100A


External (Fourth) Current Monitor
Used with SELTRONIC™ Breakers with
Built-in Ground Fault Protection

AB DE-ION® Circuit Breakers


LCG and HLCG Breakers, LCL Breakers, MCG and HMCG Breakers



NCG and HNCG Breakers



PCG, PCCG, PCFG and PCCFG Breakers






June, 1979
New Information
Mailed to: E, D, C/1901, 1928, 1929/DS

Type FCL and LCL Current Limit-R Current Limiting Breakers

Page 46.1: Type FCL, 15-100 Amperes
Page 46.2: Type LCL, 125-400 Amperes

AB DE-ION[®] Circuit Breakers


Type FCLCurrentLimiting Breaker




Terminal Arrangements

Wire Connection


Removable Connector UL
Listed Wire Range 14 to
1/0 CU 12 to 1/0 AL
Will Accomodate
14 to 3/0 Wire




Stud Connection



Plug-in or Bolt-on Connection



Bus Connection



Plug-in
Bolt stab to breaker
conductor, then plug
into support block.

Bolt-on
Bolt stab to support block, then bolt support block assembly to breaker conductors.

For 15 to 100 amp Breakers

Stud Ampere Rating	Stud Style Number	Panel Thickness	Tube Length		Tube Style Number	D	E
			A	B C			
100 A Short	451D874G01	1"	1 1/6		32B9446H20		3%
100 A Short	451D874G01	1 1/16 to 1 5/16	1 1/6		32B9446H21		↓
100 A Short	451D874G01	3/8 to 5/8	1 1/16		32B9446H22		
100 A Short	451D874G01	1/4 to 3/8	2		32B9446H23		↓
100 A Long	451D874G02	1"		3 1/6	32B9446H24	6%	
100 A Long	451D874G02	1 1/16 to 1 5/16		3 3/4	32B9446H25		↓
100 A Long	451D874G02	3/8 to 5/8		4 1/6	32B9446H26		
100 A Long	451D874G02	1/4 to 3/8		4 3/4	32B9446H27		


Ordering Instructions: Stud complete consists of one stud assembly and one tube as per chart. Order long and short studs and tubes as required to obtain proper bus spacing.

Drilling Plans


For Mounting Bolts

For Rear Connected Studs

For Plug-in Block



Front Cover Cutout



Type LCL 400 Amp Frame Current Limiting Breaker

Terminal Arrangements


For Use With Copper Cable Only
(Supplied As Standard)

Cable	Catalog Number	Ampere Rating	Wire Size
Single	T225LA	125-225	#6-350 MCM
Double	T401LA	250-400	4-250 and 3/0-600 MCM

For Use With Cu/Al Cable
(Must Be Specified)


Single	TA225LA1	125-225	#6-350 MCM Cu or #4-350 MCM Al
Double	TA400LA1	250-400	#4-250 MCM Cu/Al Plus 3/0-600 MCM Cu/Al

Line End




Load End


Drilling Plans For Plug-In Block



Rear Connected Studs (For Non-Conductive Panels)




For Mounting Bolts



Rear Connected Studs

Stud Ampere Rating	Stud Style Number	Thread Dimension Size A
125-225	1241345	1/2-13 33/16
125-225	1241392	1/2-13 415/16
125-225	1241346	1/2-13 61/4
250-400	05B7383G15	3/4-16 515/32
250-400	05B7383G16	3/4-16 731/32
250-400	05B7383G17	3/4-16 1015/32




Do not Use More Than 25 Ft. Lbs.
Torque to Tighten Nuts


Plug-in Adapter Kit

Poles	Ampere Rating	Kit Style Number	Thread Size
2	125-400	313C644G25	3/4-16
3	125-400	313C644G26	3/4-16

Do not Use More Than 25 Ft. Lbs.
Torque to Tighten Nuts




Front Cover Cutout




Reproduced From Drawing 1371D33



Type LA TRI-PAC® Breaker




Rear Connected Studs



Ampere Rating	Style Number	Dimension A	Thread Size
70-225	1241345	3 1/32	1/2-13
70-225	1241346	6 9/32	1/2-13
70-225	1241392	4 3/32	1/2-13
250-400	05B7383G15	5 1 1/32	3/4-16
250-400	05B7383G16	7 3 1/32	3/4-16
250-400	05B7383G17	10 1 1/32	3/4-16

Plug-In Adapter Kit



Terminal Arrangements

Copper Cable Only (Supplied As Standard)


Cable	Catalog Number	Ampere Rating	Wire Size
Single	T225LA	70 to 225	6 to 350 MCM
	T401LA	250 to 400	One #4-250 MCM Plus One #3/0-600 MCM Cables

Al/Cu Cable (Must Be Specified)


Cable	Catalog Number	Ampere Rating	Wire Size
Single	TA225LA1	70 to 225	6 to 350 MCM Copper or #4-350 MCM Al
	TA400LA1	250 to 400	One #4-250 MCM Plus One #3/0-600 MCM Cables

Poles	Ampere Rating	Style Number	Thread Size
2	250-400	313C644G41	3/4-16
3	250-400	313C644G42	3/4-16


Drilling Plans For Mounting Bolts




For Rear Connected Studs



For Plug-In Block



Front Cover Cutout





November, 1981
Supersedes Dimension Sheet 29-170,
pages 49-50, dated October, 1977
Mailed to: E, D, C/1901, 1928, 1929/PL

Type NB TRI-PAC® Circuit Breakers

Page 49: Outline Dimensions, Drilling Plans
Page 50: Mounting Block Dimensions

AB DE-ION[®] Circuit Breakers


Type NB, TRI-PAC® Breaker©



Drilling Plans

For Mounting Bolts

(Front Connected Terminals)



Front Connected Terminals

Amp Rating	Catalog No.	Wire Size
10	7-600	No. 8
15	7-601	No. 6
20	7-602	No. 4
25	7-603	No. 3
30	7-604	No. 2
35	7-605	No. 1
40	7-606	No. 0
50	7-607	No. 00
60	7-608	No. 000
75	7-609	No. 0000
100	7-610	No. 00000


For Copper Cable (Supplied as Standard)

300 to 350	T350 NB	Single Cable 1 to 600 MCM
400 to 700	T700 NB 1	Double Cable 2/0 to 500 MCM
800	T1000 NB 1	Triple Cable 3/0 to 500 MCM


For AL/CU Cable (Must be Specified)

300 to 700	TA700 NB 1	Two #1-500 MCM
800	TA1000 NB 1	Three #3/0-400 MCM

For Rear Connected Studs (Insulated Panel)




Bolted Rear Connected Studs For 300 to 450 Amps




Style No	A
623B222G01	5%
623B222G02	8
623B222G03	10%

For 500 to 800 Amps Only



Front Cover Cutout




Reproduced From Drawing 372D515

© Changed since previous issue.



Mounting Block for Type NB TRI-PAC® Breakers




October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Page 51: Type PB TRI-PAC®
Page 52: Motor Operator for Types EB, EHB,
FB, HFB, DA, JA, KA, LB, LBB, HKA, HLB
Breakers

AB DE-ION[®] Circuit Breakers

Type PB TRI-PAC® Breaker




Reproduced From Drawing 654D460





Motor Operators


EB, EHB, FB and HFB Breaker and Operator




Drilling Plan

**Motor Operator Only**


DA, JA, KA, LB, LBB, HKA and HLB Breaker and Operator



Drilling Plan



Motor Operator Only





October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL


Motor Operators for Types JB, KB, LAB,
LA, LC Circuit Breakers

Page 53: For Types JB, KB
Page 54: For Types LAB, LA, LC


AB DE-ION® Circuit Breakers

Motor Operators


JB, KB and HKB Breaker and Operator (Assembled to Base Plate)



Drilling Plan




Motor Operator Only






Motor Operators for LAB, LA and LC Breakers



Drilling Plan and Cutout (Adapter Plate)






October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Motor Operators for Types MA, HMA, NB,
HNB, and SELTRONIC Type MC, HMC, NC,
HNC Circuit Breakers


AB DE-ION® Circuit Breakers

Page 55: For Types MA, HMA, MC, HMC
Page 56: For Types NB, HNB, NC, HNC

Motor Operator for MA, HMA, MC, HMC Breakers




Drilling Plan and Cutout (Adapter Plate)






Motor Operator for NB, HNB, NC, HNC Breakers



Drilling Plan and Cutout (Adapter Plate)



Reproduced From Drawing 5669D02




October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Motor Operators for Types PB and
LA TRI-PAC® Circuit Breakers


Page 57: For Type PB
Page 58: For Type LA TRI-PAC

AB DE-ION® Circuit Breakers

Motor Operator for Type PB Breaker




Drilling Plan and Cutout Adapter Plate







Motor Operator for Type LA TRI-PAC® Breaker



Switchboard Cutout For Motor Operator



Transformer 480/120 Volts (Supplied for Separate Mounting by Customer for 480 Volt Operators)



Reproduced From Drawing 5677D75

Westinghouse Electric Corporation
Low Voltage Breaker Division
Beaver, Pennsylvania 15009



October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL


Motor Operator for NB TRI-PAC® Circuit
Breakers and Draw-out Frame for LA, HLA,
LC, HLC 600 Ampere Circuit Breakers

AB DE-ION® Circuit Breakers


Page 59: Motor Operator for NB TRI-PAC
Breaker

Page 60: Drawout Frame for LA, HLA,
LC, HLC 600 Ampere Breakers


Motor Operator for Type NB TRI-PAC Breaker



Switchboard Cutout For Motor Operator




Transformer 480/120 Volts (Supplied for Separate Mounting by Customer for 480 Volt Operators)






Drawout Frame for Type LA, HLA, LC, HLC 600 Ampere Breakers



Front Cover Cutout






October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Drawout Frames for MA, HMA, NB, HNB,
and Types MC, HMC, NC, HNC
SELTRONIC™ Circuit Breakers


AB DE-ION® Circuit Breakers

Page 61: For MA, HMA, MC, MCG, HMC,
HMCg
Page 62: For NB, HNB, NC, NCG, HNC,
HNCg

Drawout Frame for Type MA, HMA, MC, MCG, HMC, HMCg Breakers




Front Cover Cutout






Drawout Frame for Type NB, HNB, NC, NCG, HNC, HNCG Breakers



Front Cover Cutout



Reproduced From Drawing 5677D81

Westinghouse Electric Corporation
Low Voltage Breaker Division
Beaver, Pennsylvania 15009




October, 1977
Supersedes Dimension Sheet 29-170
all previous issues.
Mailed to: E, D, C/1901, 1928, 1929/PL

Drawout Frames for Types PCC, PCCG
SELTRONIC™ Circuit Breakers and Type NB
TRI-PAC® 800 Amp

AB DE-ION® Circuit Breakers


Page 63: For Types PC, PCCG
Page 64: For NB TRI-PAC 800 Amp

Drawout Frame for Type PC, PCCG Breakers





Drawout Frame for Type NB TRI-PAC® 800 Ampere Frame



Reproduced From Drawing 2603D31

Westinghouse Electric Corporation
Low Voltage Breaker Division
Beaver, Pennsylvania 15009



AB De-ion® circuit breakers

dimension
sheet

29-170

page 1

index

index of loose leaf dimension sheets

description	page numbers
standard circuit breakers	
70 ampere breakers	
Quicklag P	3, 4
Quicklag C	5, 6
100 ampere breakers	
type E offcenter and centerline	7, 8
type EH	9
type F	11
type G	13
225 ampere breakers	
type J	15, 16
type JK	17, 18
type K	19, 20
400 ampere breakers	
type JKL	17, 18
type KL	21, 22
800 ampere breakers	
type LM	23, 24
high interrupting capacity breakers	
MARK 75*	
100 ampere HF	25
225 ampere HK	27, 28
400 ampere HKL	29, 30
800 ampere HLM	31, 32
TRI-PAC®	
100 ampere TRI-PAC	33
225 ampere TRI-PAC	34
400 ampere TRI-PAC	35
600 ampere TRI-PAC	36
Visi-Flex switches	37-40
De-ion switches	41, 42

October, 1959

supersedes dimension sheet 29-170, pages 1 and 2, dated January, 1956
mailed to: E/243/DS; D63-2C; C25-2Y

Westinghouse Electric Corporation

Standard Control Division: Beaver Plant • Beaver, Pa.
printed in U.S.A.

www.ElectricalPartManuals.com




Quicklag C 70 ampere AB De-ion circuit breakers

dimension
sheet

29-170


page 5

1-pole



surface mounting plate

style no. 1614256




reproduced from drawing 133-A-059

supersedes dimension sheet 29-170, page 12.1, dated June, 1959
mailed to: E/243/DS; D63-2C; C25-2Y

type JK	225 ampere
type JKL	400 ampere

AB De-ion circuit breakers motor operated 2 and 3-pole



solderless terminals


breaker type	cable	style & catalog no.	amp. rating	wire size
JK	single	S # 207B510G05	50 to 225	6 to 350MCM
JKL		Cat. T225JKL		
JKL	single	S # 207B743G02	250 to 350	1 to 600MCM
		Cat. T350JKL		
JKL	double	S # 314C540G01 Cat. T400JKL	400	3/0 to 4/0

rear connected stud information

breaker type	amp. rating	style number	thd. size	dim. A
JK	50 to 225	1241 345	1/2-13	3 3/4
JK	50 to 225	1241 392	1/2-13	4 3/4
JK	50 to 225	1241 346	1/2-13	6 1/2
JKL	50 to 400	05B7 383G15	3/4-16	5 1/2
JKL	50 to 400	05B7 383G16	3/4-16	8
JKL	50 to 400	05B7 383G17	3/4-16	10 1/2


drilling plans (front view)

front cover content ▲




▲ for front panel (switchboard)
mounting— using $\frac{5}{16}$ - 18 x 4 $\frac{3}{4}$
mounting screws S 314 C982G03 — req 1

for rear connected studs




for front mounting bolts



type LA 400 ampere AB De-ion circuit breaker

motor operated
2 and 3-pole



solderless terminals

breaker type	cable	style number	amp. rating	wire size	B	C
LA	single	94B0488G06	50 to 225	4 to 350 MCM	$1\frac{1}{4}$	$1\frac{1}{32}$
LA	single	25B4621G06	250 to 350	1 to 600 MCM	$1\frac{1}{4}$	$1\frac{1}{32}$
LA	double	314C540G02	400	3.0 to 4.0	$1\frac{1}{32}$	1

rear connected stud information




breaker type	amp. rating	style number	thd. size	dim. A
LA	50 to 400	05B7383G15	$\frac{3}{4}$ -16	$5\frac{1}{2}$
LA	50 to 400	05B7383G16	$\frac{3}{4}$ -16	8
LA	50 to 400	05B7383G17	$\frac{3}{4}$ -16	$10\frac{1}{2}$

drilling plans (front view)

front cover cutout A

for rear connected studs

for front mounting bolts



▲ for front panel (switchboard)
mounting - using $\frac{5}{16}$ -18 x $4\frac{3}{4}$
mounting screws S 314C982G03 - req 1
reproduced from drawing 314-C-985



**type LA 400 ampere
AB De-ion circuit breakers**

2 and 3-pole

dimension
sheet


29-170

page 19.1


**front cover cutout**

drilling plans

for mounting panel drawout studs



**for rear connected studs for mtg. bolts
front connected terminals**




reproduced from drawing 455-D-789

June, 1960

supersedes dimension sheet 29-170, pages 17 and 18, dated October, 1959
mailed to: E/243/ DS; D63-2C; C/308/DB; C/312/CB

type LA 400 ampere AB De-ion circuit breaker

motor operated
2 and 3-pole



solderless terminals

breaker type	cable	style number	amp. rating	wire size	B	C
LA	single	94B0488G06	50 to 225	4 to 350 MCM	1 1/4	1 1/2
LA	single	25B4621G06	250 to 350	1 to 600 MCM	1 1/4	1 1/2
LA	double	314C540G02	400	3/0 to 4/0	1 1/2	1

rear connected stud information


breaker type	amp. rating	style number	thd. size	dim. A
LA	50 to 400	05B7383G15	3/4-16	5 1/2
LA	50 to 400	05B7383G16	3/4-16	8
LA	50 to 400	05B7383G17	3/4-16	10 1/2

drilling plans (front view)



front cover cutout A

for rear connected studs

for front mounting bolts



9/16 dia holes for 50 to 225 amp
13/16 dia holes for 250 to 400 amp
6 holes for 3 pole breaker
4 holes for 2 pole breaker
omit 2 center holes for 2 pole breaker



▲ for front panel (switchboard)
mounting - using 5/16 -18 x 4 3/4
mounting screws S 314C982G03 - req 1

reproduced from drawing 314-C-985




type LM 800 ampere AB De-ion circuit breakers

2 and 3-pole


dimension
sheet

29-170


page 23




note a:
the following solderless
terminals are supplied:
single cable for 125 to 350A ratings
double cable for 400 to 800A ratings
triple cable for 700 to 800A ratings



rear connected studs




support blocks




support blocks are not supplied with breaker but must be ordered separately; refer to dwg 313C644 when ordering support block (all parts necessary to convert a standard breaker are included).

drilling plans (front view)

for front mounting bolts



for rear connecting studs




rear connecting studs


2-pole breakers require 4 studs
3-pole breakers require 6 studs

maximum stud ampere rating	extension		style number
	diameter inches and thread	back of breaker inches A	
125 to 225	1/2-13	3 1/4	1241338
250 to 400	3/4-16	5 1/2	1241339
250 to 400	3/4-16	8	1241340
250 to 400	3/4-16	10 1/2	1241341
450 to 600	1-12	5 1/2	1241342
450 to 600	1-12	8	1241343
450 to 600	1-12	10 1/2	1241344
700 to 800	1 1/2-12	5 1/2	05B738 3 G19
700 to 800	1 1/2-12	8	05B738 3 G20
700 to 800	1 1/2-12	10 1/2	05B738 3 G21

drilling plan for mounting panel (front view)



front cover cutout




reproduced from drawings 313-C-366, 313-C-367

February, 1960

supersedes dimension sheet 29-170, pages 23 and 24, dated October, 1959
mailed to: E/243/DS; D63-2C; C25-2Y

type LM 800 ampere AB De-ion circuit breakers


motor operated
2 and 3-pole



drilling plans

for mounting front connected breaker using mounting studs

for mounting rear connected breaker using rear terminal studs



rear connecting studs

2-pole breakers require 4 studs
3-pole breakers require 6 studs

maximum stud ampere rating	extension diameter inches and thread	back of breaker inches A	style number
125 to 225	1/2-13	3 3/4	1241338
250 to 400	3/4-16	5 1/2	1241339
250 to 400	3/4-16	8	1241340
250 to 400	3/4-16	10 1/2	1241341
450 to 800	1-12	5 1/2	1241342
450 to 800	1-12	8	1241343
450 to 800	1-12	10 1/2	1241344

solderless terminals

wire size MCM	style number	solderless terminals, type
1 to 600	1614688	single cable +
500 to 1000	1614689	single cable +
2 0 to 300	1532172	double cable ▲
300 to 500	1532173	double cable ▲
600 to 700	313C234G01	double cable ▲
300 to 500	451D243G01	triple cable ▲

+extended terminals (standard for electrically operated breakers)
▲motor mech and cover must be removed to make connections for these terminals.

reproduced from drawing 313-C-368

Westinghouse Electric Corporation
Standard Control Division: Beaver Plant . Beaver, Pa.
 printed in U.S.A.

www.ElectricalPartManuals.com



MARK 75 HF 100 ampere AB De-ion circuit breakers

2 and 3-pole


dimension
sheet
29-170
page 25

2-pole

3-pole


4-poles protected

3 poles protected, 1 pole non-automatic




terminal arrangements


bus connection




wire connection



drilling plans (front view) for front mounting bolts




for rear connecting studs




drilling plan

for plug-in block




front cover cutout

bkr dims shown only.
for cutout
recommend $\frac{3}{32}$ be
added to dims shown




rear connecting stud identification



mtg. strap thkns. A	type stud	stud style no.	tube style no.	B	C	D	E	F
3/8 & 1/2	short	1222 937	1222929	1 11/32	3 3/8	1 3/4	4 1/8	6 1/4
3/8 & 1/2	long	1222 938	1222930					
3/4	short	1222 937	1222931	3 1/2	3 3/8	1 3/4	4 1/8	6 1/4
3/4	long	1222 938	1222932					
1	short	1222 937	1222933	2 3/2	3 1/8	1 3/4	4 1/8	6 1/4
1	long	1222 938	1222934					
3/8 & 1/2	short	1300 057	1222929	1 11/32	2 13/16	1 3/4	3 1/4	5 3/8
3/8 & 1/2	long	1300 058	1222930					
3/4	short	1300 057	1222931	3 1/2	3 1/8	1 3/4	3 1/4	5 3/8
3/4	long	1300 058	1222932					
1	short	1300 057	1222933	2 3/2	2 13/16	1 3/4	3 1/4	5 3/8
1	long	1300 058	1222934					
1 1/2	short	1300 057		0	2 3/8	1 3/4	3 1/4	5 3/8
1 1/2	long	1300 058	1577278					
2	short	1300 057		0	1 13/16	1 3/4	3 1/4	5 3/8
2	long	1300 058	1577279					

ordering instructions: stud complete consists of one stud assembly and one tube as per chart—order long and short studs as required to obtain proper bus spacing


plug-in mounting block



reproduced from drawing 1-A-4143


www.ElectricalPartManuals.com

*motor operated
2 and 3-pole*




ampere rating	style number	dimension A
70 to 225	1241 345	3 $\frac{7}{16}$
70 to 225	1241 346	6 $\frac{7}{16}$
70 to 225	1241 392	4 $\frac{3}{16}$

for front mounting bolts



for rear connecting studs



Westinghouse Electric Corporation
Standard Control Division: Beaver Plant • Beaver, Pa.
 printed in U.S.A.


MARK 75 HLM 800 ampere
AB De-ion circuit breakers

dimension
sheet

29-170

page 31

2 and 3-pole




note a:
the following solderless
terminals are supplied:
single cable for 125 to 350A ratings
double cable for 400 to 800A ratings
triple cable for 700 to 800A ratings

support blocks

$\frac{5}{16}$ - 18 mounting screws and washers
furnished with support block

do not use more
than 25 ft lbs
torque to
tighten bolts



support blocks are not supplied with breaker but must be ordered separately; refer to dwg 313C644 when ordering support block (all ports necessary to convert a standard breaker are included).


rear connecting studs

2-pole breakers require 4 studs
3-pole breakers require 6 studs


maximum stud ampere rating	extension		style number
	diameter inches and thread	back of breaker inches A	
125 to 225	½-13	3¼	1241338
250 to 400	¾-16	5½	1241339
250 to 400	¾-16	8	1241340
250 to 400	¾-16	10½	1241341
450 to 600	1-12	5½	1241342
450 to 600	1-12	8	1241343
450 to 600	1-12	10½	1241344
700 to 800	1½-12	5½	05B738 3 G19
700 to 800	1½-12	8	05B738 3 G20
700 to 800	1½-12	10½	05B738 3 G21

solderless terminals

ampere rating	style number	wire size MCM	solderless terminals, type
125 to 350	1154 307	4 0 to 600	single cable
400 to 500	1532 172	2 2 0 to 2,300	double cable
550 to 600	1532 173	2,300 to 2,500	double cable
700 to 800	313C234G01	2,600 to 2,700	double cable
700 to 800	451D243G01	3,300 to 3,400	triple cable




rear connected studs




drilling plans (front view)



for front mounting bolts



for rear connecting studs



**drilling plan for mounting panel
(front view)**

**front cover cutout**

reproduced from drawings 313-C-366, 313-C-367

February, 1960

February, 1980
supersedes dimension sheet 29-170, pages 31 and 32, dated October, 1959
mailed to: E/243/DS; D63-2C; C25-2Y

*motor operated
2 and 3-pole*

